

Random and Adversarial Bit Error Robustness: Energy-Efficient and Secure DNN Accelerators

David Stutz, Nandhini Chandramoorthy, Matthias Hein, and Bernt Schiele

Abstract—Deep neural network (DNN) accelerators received considerable attention in recent years due to the potential to save energy compared to mainstream hardware. Low-voltage operation of DNN accelerators allows to further reduce energy consumption significantly, however, causes bit-level failures in the memory storing the quantized DNN weights. Furthermore, DNN accelerators have been shown to be vulnerable to adversarial attacks on voltage controllers or individual bits. In this paper, we show that a combination of **robust fixed-point quantization, weight clipping**, as well as **random bit error training (RANDBET)** or **adversarial bit error training (ADVBET)** improves **robustness against random or adversarial bit errors in quantized DNN weights significantly**. This leads not only to high energy savings for low-voltage operation *as well as* low-precision quantization, but also improves security of DNN accelerators. Our approach generalizes across operating voltages and accelerators, as demonstrated on bit errors from profiled SRAM arrays, and achieves robustness against both targeted and untargeted bit-level attacks. Without losing more than 0.8%/2% in test accuracy, we can reduce energy consumption on CIFAR10 by 20%/30% for 8/4-bit quantization using RANDBET. Allowing up to 320 adversarial bit errors, ADVBET reduces test error from above 90% (chance level) to 26.22% on CIFAR10.

Index Terms—DNN Accelerators, Bit Error Robustness, Adversarial Bit Errors, Robustness, DNN Quantization

1 INTRODUCTION

ENERGY-efficiency is an important goal to lower carbon-dioxide emissions of deep neural network (DNN) driven applications and is a critical prerequisite to enable applications in edge computing. *DNN accelerators*, i.e., specialized hardware for inference, are used to reduce and limit energy consumption alongside cost and space compared to mainstream hardware, e.g., GPUs. These accelerators generally feature on-chip SRAM used as scratchpads, e.g., to store DNN weights. Data access/movement constitutes a dominant component of accelerator energy consumption [1]. Besides reduced precision [2], DNN accelerators [3], [4], [5] further lower memory supply voltage to increase energy efficiency since dynamic power varies quadratically with voltage. However, aggressive SRAM supply voltage scaling causes bit-level failures on account of process variation [6], [7] with direct impact on the stored DNN weights. The rate p of these errors increases exponentially with lowered voltage, causing devastating drops in DNN accuracy. Thus, DNN accelerators are also vulnerable to maliciously reducing voltage [8] or adversarially inducing individual bit errors [9], [10]. In this paper, we aim to enable very low-voltage operation of DNN accelerators by developing DNNs robust to *random bit errors* in their (quantized) weights. This also improves security against manipulation of voltage settings [8]. Furthermore, we address robustness against a limited number of *adversarial bit errors*, similar to [11], [12], [13]. In general, DNN robustness to bit errors is a desirable

goal to maintain safe operation and should become a standard performance metric in low-power DNN design.

Fig. A shows the average bit error rates of SRAM arrays as supply voltage is scaled below V_{\min} , i.e., the measured lowest voltage at which there are no bit errors. Voltage (x-axis) and energy (red, right y-axis) are normalized wrt. V_{\min} and the energy per access at V_{\min} , respectively. DNNs robust to a bit error rate (blue, left y-axis) of, e.g., $p = 1\%$ allow to reduce SRAM energy by roughly 30%. To improve DNN robustness to the induced *random bit errors*, we first consider the impact of fixed-point quantization on robustness. While prior work [14], [15], [16] studies robustness to quantization, the impact of random bit errors *in* quantized weights has not been considered so far. We find that the choice of quantization scheme has tremendous impact on robustness, even though accuracy is not affected. In particular, we identify a particularly **robust quantization scheme**, RQUANT in Fig. 2 (red). Additionally, independent of the quantization scheme, we propose aggressive **weight clipping** during training. This acts as an explicit regularizer leading to spread out weight distributions, improving robustness significantly, CLIPPING in Fig. 2 (blue). This is in contrast to, e.g., [16], [17] ignoring weight outliers to reduce quantization range, with sole focus of improving accuracy.

Conventional error mitigation strategies or circuit techniques are not applicable to mitigate larger rates of bit errors or incur a significant energy/space overhead. For example, common error correcting codes (ECCs such as SECDED), cannot correct *multiple* bit errors per word (containing multiple DNN weights). However, for $p = 1\%$, the probability of two or more random bit errors in a 64-bit word is 13.5%. Furthermore, an adversary may intentionally target multiple bits per word. Considering low-voltage induced random bit errors, error detection via redundancy [3] or supply voltage boosting [5] allow error-free operation at

- David Stutz and Bernt Schiele are with the Max Planck Institute for Informatics, Saarland Informatics Campus, Germany.
E-mail: {david.stutz,schiele}@mpi-inf.mpg.de
- Nandhini Chandramoorthy is with the IBM T. J. Watson Research Center, Yorktown Heights, NY.
E-mail: nandhini.chandramoorthy@ibm.com
- Matthias Hein is with the University of Tübingen, Germany.
E-mail: matthias-hein@uni-tuebingen.de




Fig. 1: **Energy and Low-Voltage Operation.** Average bit error rate p (blue, left y-axis) from 32 14nm SRAM arrays of size 512×64 from [5] and energy (red, right y-axis) vs. voltage (x-axis). Voltage is normalized by V_{\min} , the minimal measured voltage for error-free operation, and the energy per SRAM access at V_{\min} . SRAM accesses have significant impact on the DNN accelerator’s energy [18]. Reducing voltage leads to exponentially increasing bit error rates.

the cost of additional energy or space. Therefore, [4] and [19] propose a co-design approach of training DNNs on *profiled* bit errors (i.e., post-silicon characterization) from SRAM or DRAM, respectively. These approaches work as long as the spatial bit error patterns can be assumed fixed for a *fixed* accelerator *and* voltage. However, the random nature of variation-induced bit errors requires profiling to be carried out for each voltage, memory array and individual chip in order to obtain the corresponding bit error patterns. This makes training DNNs on profiled bit error patterns an expensive process. We demonstrate that the obtained DNNs do *not* generalize across voltages or to unseen bit error patterns, e.g., from other memory arrays, and propose **random bit error training (RANDBET)**, in combination with weight clipping and robust quantization, to obtain robustness against completely random bit error patterns, see Fig. 2 (violet). Thereby, it generalizes across chips *and* voltages, without any profiling, hardware-specific data mapping or other circuit-level mitigation strategies. Finally, in contrast to [4], [19], we also consider bit errors in activations and inputs, as both are temporally stored on the chip’s memory and thus subject to bit errors.

Besides low-voltage induced random bit errors, [9], [10] demonstrate the possibility of *adversarially* flipping specific bits. The bit flip attack (BFA) of [11], an untargeted search-based attack on (quantized) DNN weights, demonstrates that such attacks can easily degrade DNN accuracy with few bit flips. [13] proposes a binarization strategy to “defend” against BFA. However, the approach was shown to be ineffective shortly after considering a targeted version of BFA [12], leaving the problem unaddressed. We propose a novel attack based on projected gradient descent, inspired by recent work on adversarial examples [20], [21]. We demonstrate that our attack is both more effective and more efficient. Moreover, in contrast to BFA, our adversarial bit attack enables **adversarial bit error training (ADVBET)**. As shown in Fig. 2 (right), ADVBET (magenta) improves robustness against adversarial bit errors considerably, outperforming CLIPPING (blue) and RANDBET (violet) which, surprisingly, provide very strong baselines. As a result, we are able to




Fig. 2: **Robustness to Random Bit Errors.** *Left:* Robust test error RErr after injecting *random* bit errors (lower is better ↓, y-axis) plotted against bit error rate p (x-axis). For 8 bit, robust quantization (RQUANT, red), additionally weight clipping (CLIPPING, dotted blue) or *per-layer* weight clipping (PLCLIPPING, solid blue) and finally adding random bit error training (RANDBET, violet) robustness improves significantly. Robustness to higher bit error rates allows more energy efficient operation, cf. Fig. A. The Pareto optimal frontier is shown for 8 bit (black solid) and 4 bit (dashed) quantization. *Right:* RErr against up to 320 *adversarial* bit errors, showing that CLIPPING combined with RANDBET or ADVBET also allow secure operation.

obtain robustness to both random and adversarial bit errors, enabling energy-efficient *and* secure DNN accelerators.

Contributions: We combine our **robust fixed-point quantization RQUANT** with **weight clipping** and **random bit error training (RANDBET)** or **adversarial bit error training (ADVBET)** in order to obtain high robustness against low-voltage induced, *random bit errors* or maliciously crafted, *adversarial bit errors*. We consider fixed-point quantization schemes in terms of robustness *and* accuracy, instead of *solely* focusing on accuracy as related work. Furthermore, we show that aggressive weight clipping, as regularization during training, is an effective strategy to improve robustness through redundancy. In contrast to [4], [19], the robustness obtained through RANDBET generalizes across chips *and* voltages, as evaluated on profiled SRAM bit error patterns from [5]. In contrast to [11], [12], our (untargeted or targeted) adversarial bit error attack is based on gradient descent, improving effectiveness and efficiency, and our ADVBET improves robustness against targeted and untargeted attacks, outperforming the recently broken binarization approach of [13]. Finally, we discuss the involved trade-offs regarding robustness (against random or adversarial bit errors) and accuracy and make our code publicly available to facilitate research in this practically important area of DNN robustness. Fig. 2 (left) highlights key results for RANDBET on CIFAR10: with 8/4 bit quantization and an increase in test error of less than 0.8%/2%, roughly 20%/30% energy savings are possible – on top of energy savings from using low-precision quantization. Similarly, ADVBET, cf. Fig. 2 (right), obtains 26.22% (robust) test error against up to 320 adversarial bit errors in the weights.

A preliminary version of this work has been accepted at MLSys’21 [22]. We further improved robustness against low-voltage induced random bit errors using *per-layer* weight clipping (PLCLIPPING, solid blue in Fig. 2). Furthermore, we consider random bit errors in activations and inputs




Fig. 3: **Exemplary SRAM Bit Error Patterns.** Measured bit errors from two chips with on-chip SRAM (left and right), showing bit flip probability for a segment of size 64×128 bits: **yellow** indicates a bit flip probability of one, **violet** indicates zero probability. We show measurements corresponding to two supply voltages. With lower voltage, bit error rate increases. Also, the bit errors for higher voltage (= lower bit error rate) are a subset of those for lower voltage (= higher rate), cf. Sec. 3. Our error model randomly distributes bit errors across space. However, as example, we also show SRAM chip 2 which has a different spatial distribution with bit errors distributed along columns. We aim to obtain robustness across different memory arrays, voltages *and* allowing arbitrary DNN weight to memory mappings.

which are also (temporally) stored on the SRAM and thus subject to bit errors. In both cases, the negative impact can be limited using approaches similar to **RANDBET**. Beyond our work on low-voltage induced, random bit errors in [22], we tackle the more challenging task of *adversarial bit errors*, cf. Fig. 2 (right). We devise a flexible adversarial bit error attack based on projected gradient descent that can be used in an untargeted or targeted setting and is more effective and efficient compared to related work [11]. Moreover, our attack enables adversarial bit error training (**ADVBET**, **magenta**), which improves robustness significantly. We also show that **RANDBET** (**violet**) provides surprisingly good robustness against adversarial bit errors, thereby enabling both energy-efficient and secure DNN accelerators.

Outline: We review related work in Sec. 2 and provide a detailed description and discussion of the considered low-voltage, random bit error model as well as our adversarial bit error model in Sec. 3. In Sec. 4, we discuss fixed-point quantization and its influence on bit error robustness and present weight clipping and **RANDBET** as effective strategies to improve robustness. Similarly, we discuss **ADVBET** to improve robustness against adversarial, i.e., worst-case, bit errors. Finally, Sec. 5 includes our experimental results and we conclude in Sec. 6. Additional discussion and further experiments are provided in the **supplementary material**.

2 RELATED WORK

Quantization: DNN Quantization [23] is usually motivated by faster DNN inference, e.g., through fixed-point quantization and arithmetic [2], [24], [25], and energy savings. To avoid reduced accuracy, quantization is considered during training [26], [27] instead of post-training or with fine-tuning [28], [29], [30], [31], enabling low-bit quantization such as binary DNNs [32], [33]. Some works also consider quantizing activations [32], [34], [35] or gradients [36], [37], [38]. While works such as [14], [15], [16], [39] study the robustness of DNNs *to* quantization, the robustness of various quantization schemes *against* random bit errors has not been studied. This is in stark contrast to our findings that quantization impacts robustness significantly. We note that [38] or [26], [40] do *not* quantize the batch normalization parameters (i.e., scale and bias) or “fold” the batch normalization operation into the preceding convolution. In con-

trast, we quantize *all* weights, including batch normalization parameters and biases to realistically study the impact of bit errors in these parameters. Furthermore, works such as [16], [17], [41] clip weight outliers to reduce approximation error of inliers, improving accuracy. In contrast, we consider *weight clipping* independent of quantization *as regularization during training* which spreads out the weight distribution and improves robustness to bit errors.

Low-Voltage, Random Bit Errors in DNN Accelerators: Recent work [6], [42] demonstrates that bit flips in SRAMs increase exponentially when reducing voltage below V_{\min} . The authors of [5] study the impact of bit flips in different layers of DNNs, showing severe accuracy degradation. Similar observations hold for DRAM [43]. To prevent accuracy drops at low voltages, [3] combines SRAM fault detection with logic to set faulty data reads to zero. [5] uses supply voltage boosting for SRAMs to ensure error-free, low-voltage operation, while [44] proposes storing critical bits in specifically robust SRAM cells. However, such methods incur power and area overhead. Thus, [4] and [19] propose co-design approaches combining training on profiled SRAM/DRAM bit errors with hardware mitigation strategies and clever weight to memory mapping. Besides low-voltage operation for energy efficiency, recent work [8] shows that an attacker can reduce voltage maliciously. In contrast to [4], [19], our *random bit error training* (**RANDBET**) obtains robustness that generalizes across chips and voltages without expensive chip-specific profiling or hardware mitigation strategies. Furthermore, [4], [19] do not address the role of quantization and we demonstrate that these approaches can benefit from our weight clipping, as well. We show that energy savings from low-voltage operation and low-precision [41] can be combined. Finally, in contrast to existing work [4], [19], we also study low-voltage induced bit errors in DNN activations and inputs.

Adversarial Bit Errors in DNN Accelerators: Works such as [9], [10] demonstrate software-based approaches to induce few, but targeted, bit flips in DRAM. The impact of such attacks on (quantized) DNN weights has recently been studied in [11]: The proposed bit flip attack (BFA) is a search-based strategy to find as few bit errors as possible such that accuracy reduces to chance level. However, the binarization approach of [13], improving robustness against




Fig. 4: **Quantization and Random Bit Errors.** Original weights (x-axis) plotted against perturbed weights with bit errors (y-axis), for different fixed-point quantization schemes with $m = 8$ bit (left) and $p = 2.5\%$. We also show the $m = 4$ bit case with CLIPPING at $w_{\max} = 0.1$, cf. Sec. 4.2. Color indicates absolute error: from zero (violet) to the maximal possible error (yellow) of 1 (left) and 0.1 (right). Asymmetric per-layer quantization reduces the impact of bit errors compared to the symmetric per-layer/global quantization. Clipping reduces absolute error, but the errors *relative* to w_{\max} increase.

untargeted BFA, has been shown to be ineffective against a targeted version of BFA [12]. Moreover, the authors of [13] conclude that training on adversarial bit errors is *not* a promising defense. In contrast, we propose a more effective and efficient, gradient-based adversarial bit error attack and demonstrate that *adversarial bit error training* (ADVBET) using our attack improves robustness against both untargeted and targeted attacks, including BFA. ADVBET is similar in spirit to training on adversarial examples which received considerable attention recently [20], [21], [45], [46].

Weight Robustness: Only few works consider weight robustness: [47] certify the robustness of weights with respect to L_∞ perturbations and [48] study Gaussian noise on weights. [11], [13] consider identifying and (adversarially) flipping few vulnerable bits in quantized weights. Fault tolerance, in contrast, describes structural changes such as removed units, and is rooted in early work such as [49], [50]. Finally, [51], [52] explicitly manipulate weights in order to integrate backdoors. We study robustness against *random bit errors*, which exhibit a quite special noise pattern compared to L_∞ or Gaussian noise, cf. Fig. 4.

3 BIT ERRORS IN QUANTIZED DNN WEIGHTS

In the following, we introduce the bit error models considered in this paper: random bit errors (Sec. 3.1), induced through low-voltage operation of accelerator memory, and adversarial bit errors (Sec. 3.2), maliciously crafted and injected by an adversary to degrade DNN accuracy.

Notation: Let $f(x; w)$ be a DNN taking an example $x \in [0, 1]^D$, e.g., an image, and weights $w \in \mathbb{R}^W$ as input. The DNN is trained by minimizing the cross-entropy loss \mathcal{L} on a training set $\{(x_n, y_n)\}_{n=1}^N$ consisting of examples x_n and corresponding labels $y_n \in \{1, \dots, K\}$, K denoting the number of classes. We assume a weight $w_i \in [q_{\min}, q_{\max}]$, i.e., within the *quantization range*, to be quantized using a function Q . As we will detail in Sec. 4.1, Q maps floating-point values to m -bit (signed or unsigned) integers. With $v_i = Q(w_i)$, we denote the integer corresponding to the quantized value of w_i , i.e., v_i is the bit representation of w_i after quantization represented as integer. Finally, $d_H(v, v')$ denotes the bit-level Hamming distance between the integers v and v' .

3.1 Low-Voltage Induced Random Bit Errors

We assume the quantized DNN weights to be stored on multiple memory banks, e.g., SRAM in the case of on-chip scratchpads or DRAM for off-chip memory. As shown in [4], [5], [6], the probability of memory bit cell failures increases exponentially as operating voltage is scaled below V_{\min} , i.e., the minimal voltage required for reliable operation, see Fig. A. This is done intentionally to reduce energy consumption [4], [5], [19] or adversarially by an attacker [8]. Process variation during fabrication causes a variation in the vulnerability of individual bit cells. As shown in Fig. 3 (left), for a specific memory array, bit cell failures are typically approximately random and independent of each other [6] even so chips showing patterns with stronger dependencies are possible, cf. Fig. 3 (right). Nevertheless, there is generally an “inherited” distribution of bit cell failures across voltages: as described in [42], if a bit error occurred at a given voltage, it is likely to occur at lower voltages, as made explicit in Fig. 3. However, across different SRAM arrays in a chip or different chips, the patterns or spatial distributions of bit errors is usually different and can be assumed random [5]. Throughout the paper, we use the following bit error model:

Random Bit Error Model: *The probability of a bit error is p (in %) for all weight values and bits. For a fixed memory array, bit errors are persistent across supply voltages, i.e., bit errors at probability $p' \leq p$ also occur at probability p . A bit error flips the currently stored bit. Random bit error injection is denoted $BErr_p$.*

This error model realistically captures the nature of low-voltage induced bit errors, from both SRAM and DRAM as confirmed in [4], [5], [19]. However, our approach in Sec. 4 is model-agnostic: the error model can be refined if extensive memory characterization results are available for individual chips. For example, faulty bit cells with 1-to-0 or 0-to-1 flips might not be equally likely. Similarly, as in [19], bit errors might be biased towards alignment along rows or columns of the memory array. The latter case is illustrated in Fig. 3 (right). However, estimating these specifics requires testing infrastructure and detailed characterization of individual chips. More importantly, it introduces the risk of overfitting to few specific memories/chips. Furthermore, we demonstrate that the robustness obtained using our uniform error model generalizes to bit error distributions with strong spatial biases as in Fig. 3 (right).

We assume the quantized weights to be mapped linearly to the memory. This is the most direct approach and, in

Algorithm 1 Adversarial Bit Errors. We maximize cross-entropy loss using projected gradient ascent while ensuring that at most ϵ bits are flipped. Line 9 may include backtracking and Line 7 may include gradient normalization. **Quantized weights** shown in **red**; **de-quantized weights** in **blue**; and **floating-point operations** in **magenta**.

```

1: procedure ADVBITERRORS( $w, \epsilon$ )
2:    $v = Q(w)$ 
3:   initialize:  $d_H(\tilde{v}^{(0)}, v) \leq \epsilon, d_H(\tilde{v}_i^{(0)}, v_i) \leq 1$ 
4:   for  $t = 0, \dots, T - 1$  do {fixed  $\{(x_b, y_b)\}_{b=1}^B$ }
5:      $\tilde{w}_q^{(t)} = Q^{-1}(\tilde{v}^{(t)})$ 
6:     {forward pass using de-quantized weights:}
7:      $\Delta^{(t)} = \nabla_w \sum_{b=1}^B \mathcal{L}(f(x_b; \tilde{w}_q^{(t)}), y_b)$ 
8:     {optional: normalize  $\Delta^{(t)}$  and/or use momentum}
9:      $\tilde{w}^{(t+1)} = \tilde{w}^{(t)} + \gamma \Delta^{(t)}$  {update without quantization}
10:     $\tilde{v}^{(t+1)} = Q(\tilde{w}^{(t+1)})$ 
11:    project:  $d_H(\tilde{v}^{(t+1)}, v) \leq \epsilon, d_H(\tilde{v}_i^{(t+1)}, v_i) \leq 1$ 
12:  return  $\tilde{w}_q^{(T)} = Q^{-1}(Q(\tilde{w}^{(T)}))$ 

```

contrast to [19], does not require knowledge of the exact spatial distribution of bit errors. This also means that we do not map particularly vulnerable weights to more reliable memory cells, and therefore no changes to the hardware or the application are required. Thus, in practice, for W weights and m bits per weight value, we sample uniformly $u \sim U(0, 1)^{W \times m}$. Then, the j -th bit in the quantized weight $v_i = Q(w_i)$ is flipped iff $u_{ij} \leq p$. Our model assumes that the flipped bits at lower probability $p' \leq p$ are a subset of the flipped bits at probability p and that bit flips to 1 and 0 are equally likely. The noise pattern of random bit errors is illustrated in Fig. 4: for example, a bit flip in the most-significant bit (MSB) of the signed integer v_i results in a change of half of the quantized range (also cf. Sec. 4.1).

In the case of on-chip SRAM, inputs and activations will also be subject to low-voltage induced bit errors. This is because the SRAM memory banks are used as scratchpads to temporally store intermediate computations such as inputs and activations. As described in detail in Sec. 5.4, inputs are subject to random bit errors *once* before being fed to the DNN. Activations, i.e., the result of intermediate layers of the DNN, are subject to random bit errors multiple times throughout a forward pass. This is modeled by (independently) injecting random bit errors in the activations after each “block” consisting of convolution, normalization and ReLU layers. This assumes that activations are temporally stored on the SRAM scratchpads after each such block. In practice, the data flow of a DNN accelerator is manually tailored to the DNN architecture *and* chip design, which is also why energy estimation for DNN accelerators is very difficult [53], [54]. Furthermore, normalization schemes (group [55] or batch normalization [56]) and ReLU activations can be “folded into” the preceding convolutional layer [26], [40]. Thus, considering the activations to go through temporal storage on the SRAM after each block is a realistic approximation of the actual data flow.

3.2 Adversarial Bit Errors

Following recent attacks on memory [9], [10], [11], [57] and complementing our work on random bit errors [22], we also consider adversarial bit errors. We constrain the number

Algorithm 2 Random Bit Error Training (RANDBET). The forward passes are performed using **de-quantized weights (blue)**. Perturbed weights are obtained by injecting bit errors in the **quantized weights (in red)**. The update, averaging gradients from both forward passes, is performed in **floating-point (magenta)**. Also see Fig. 5.

```

1: procedure RANDBET( $p$ )
2:   initialize  $w^{(0)}$ 
3:   for  $t = 0, \dots, T - 1$  do
4:     sample batch  $\{(x_b, y_b)\}_{b=1}^B$ 
5:      $w^{(t)} = \min(w_{\max}, \max(-w_{\max}, w^{(t)}))$  {element-wise clipping}
6:      $v^{(t)} = Q(w^{(t)})$  {quantization}
7:      $w_q^{(t)} = Q^{-1}(v^{(t)})$  {de-quantization}
8:     {clean forward and backward pass:}
9:      $\Delta^{(t)} = \nabla_w \sum_{b=1}^B \mathcal{L}(f(x_b; w_q^{(t)}), y_b)$ 
10:    {perturbed forward and backward pass:}
11:     $\tilde{w}_q^{(t)} = Q^{-1}(\text{BErr}_p(v^{(t)}))$  (or ADVBITERRORS( $\tilde{w}_q^{(t)}, \epsilon$ ))
12:     $\tilde{\Delta}^{(t)} = \nabla_w \sum_{b=1}^B \mathcal{L}(f(x_b; \tilde{w}_q^{(t)}), y_b)$ 
13:    {average gradients and weight update:}
14:     $w^{(t+1)} = w^{(t)} - \gamma(\Delta^{(t)} + \tilde{\Delta}^{(t)})$ 
15:  return  $w_q^{(T)} = Q^{-1}(Q(w^{(T)}))$ 

```

of induced bit errors by ϵ , similar to the L_p -constrained adversarial inputs [58]. Furthermore, we consider only one bit flip per weight value to simplify the projection onto the discrete constraint set. Then, given knowledge of memory layout and addressing schemes, an adversary can use, e.g., RowHammer [9], in order to flip as many of the adversarially selected bits. Note that, in practice, not all of these bits will be vulnerable to an end-to-end RowHammer attack on memory, which we do not focus on. However, from a robustness viewpoint, it makes sense to consider a slightly stronger threat model than actually realistic. Overall, our white-box threat model is defined as follows:

Adversarial Bit Error Model: *An adversary can flip up to ϵ bits, at most one bit per (quantized) weight, to reduce accuracy and has full access to the DNN, its weights and gradients.*

Note that we do *not* consider adversarial bit errors in inputs (i.e., adversarial examples) or activations. Following the projected gradient ascent approach of [20] and letting d_H be the (bit-level) Hamming distance, we intend to maximize cross-entropy loss \mathcal{L} on a mini-batch $\{(x_b, y_b)\}_{b=1}^B$ of examples as *untargeted* attack:

$$\begin{aligned} \max_{\tilde{v}} \sum_{b=1}^B \mathcal{L}(f(x_b; Q^{-1}(\tilde{v})), y_b) \\ \text{s.t. } d_H(\tilde{v}, v) \leq \epsilon, \quad d_H(\tilde{v}_i, v_i) \leq 1 \end{aligned} \quad (1)$$

Note that y_b are the ground truth labels. We also consider a targeted version of Eq. (1), similar to [12], where we minimize the cross-entropy loss between predictions and an arbitrary but fixed target label: $\min_{\tilde{v}} \sum_{b=1}^B \mathcal{L}(f(x_b; Q^{-1}(\tilde{v})), y_t)$ where y_t is the same target label across all examples x_b . As made explicit in Eq. (1), we work on bit-level, i.e., optimize over the two’s complement signed integer representation $\tilde{v}_i \in \{-2^{m-1} - 1, \dots, 2^{m-1} - 1\}$ corresponding to the underlying bits of the perturbed weights $\tilde{w} = Q(\tilde{v})$. We will adversarially inject bit errors based on the gradient of Eq. (1) and perform a projection onto the Hamming constraints $d_H(\tilde{v}, v) \leq \epsilon$ and $d_H(\tilde{v}_i, v_i) \leq 1$ with respect to




Fig. 5: **Random Bit Error Training (RANDBET)**. We illustrate the data-flow for RANDBET as in Alg. 2. Here, $BErr_p$ injects random bit errors in the **quantized weights** $v^{(t)} = Q(w^{(t)})$, resulting in $\tilde{v}^{(t)}$, while the forward pass is performed on the **de-quantized perturbed weights** $\tilde{w}_q^{(t)} = Q^{-1}(\tilde{v}^{(t)})$, i.e., fixed-point arithmetic is not emulated. The weight update during training is not affected by bit errors and computed in **floating point**.

the quantized, clean weights $v = Q(w)$. This means that we maximize Eq. (1) through projected gradient ascent where the forward and backward pass are performed in floating point:

$$\begin{aligned} \tilde{w}^{(t+1)} &= \tilde{w}^{(t)} + \gamma \Delta^{(t)} \quad \text{with} \\ \Delta^{(t)} &= \sum_{b=1}^B \nabla_w \mathcal{L}(f(x_b; \tilde{w}_q^{(t)}), y_b), \quad \tilde{w}_q^{(t)} = Q^{-1}(Q(\tilde{w}^{(t)})) \end{aligned} \quad (2)$$

followed by the projection of $\tilde{v}^{(t+1)} = Q(\tilde{w}^{(t+1)})$ onto the (bit-level) Hamming constraints of Eq. (1). Here, γ is the step size. The updates are performed in floating point, while the forward pass is performed using the de-quantized weights $\tilde{w}_q^{(t)}$. The perturbed weights $\tilde{w}^{(0)} = Q^{-1}(\tilde{v}^{(0)})$ are initialized by uniformly picking $k \in [0, \epsilon]$ bits to be flipped in $v = Q(w)$ in order to obtain $\tilde{v}^{(0)}$. Our adversarial bit attack is summarized in pseudo code in Alg. 1.

The Hamming-projection is similar to the L_0 projection used for adversarial inputs, e.g., in [59]. Dropping the superscript t for brevity, in each iteration, we solve the following projection problem:

$$\begin{aligned} \min_{\tilde{v}'} \quad & \|Q^{-1}(\tilde{v}) - Q^{-1}(\tilde{v}')\|_2^2 \\ \text{s.t.} \quad & d_H(v_i, \tilde{v}'_i) \leq 1, \quad d_H(v, \tilde{v}') \leq \epsilon \end{aligned} \quad (3)$$

where $\tilde{v} = Q(\tilde{w})$ are the quantized, perturbed weights after Eq. (2) and $v = Q(w)$ are the quantized, clean weights. We optimize over \tilde{v}' which will be the perturbed weights after the projection, i.e., as close as possible to \tilde{v} while fulfilling the constraints above. This can be solved in two steps as the objective and the constraint set are separable: The first step involves keeping only the top- ϵ changed values, i.e., the top- ϵ weights with the largest difference $|w_i - \tilde{w}_i|$. The second step can be solved by keeping only the most significant bit changed in \tilde{v}_i compared to v_i as detailed in our supplementary material. The optimization problem in Eq. (1) is challenging due to the projection onto the non-convex set of Hamming constraints. We adopt best practices from computing adversarial inputs: normalizing the gradient [59] (per-layer using the L_∞ norm) and momentum [60].

4 ROBUSTNESS AGAINST BIT ERRORS

We address robustness against random and/or adversarial bit errors in three steps: First, we analyze the impact of fixed-point quantization schemes on bit error robustness. This has been neglected both in prior work on low-voltage DNN accelerators [4], [19] and in work on quantization robustness [14], [15], [16]. This yields our **robust quantization** (Sec. 4.1). On top, we propose aggressive **weight clipping** as regularization during training (Sec. 4.2). Weight clipping enforces a more uniformly distributed, i.e., redundant, weight distribution, improving robustness. We show that this is due to minimizing the cross-entropy loss, enforcing large logit differences. Finally, in addition to robust quantization and weight clipping, we perform **random bit error training (RANDBET)** (Sec. 4.3) or **adversarial bit error training (ADVBET)** (Sec. 4.4). For RANDBET, in contrast to the fixed bit error patterns in [4], [19], we train on completely *random* bit errors and, thus, generalize across chips and voltages. Regarding ADVBET, we train on *adversarial* bit errors, computed as outlined in Sec. 3.2. Generalization of bit error robustness is measured using *robust test error (RErr)*, the test error after injecting bit errors (lower is more robust).

4.1 Robust Fixed-Point Quantization

We consider quantization-aware training [26], [27] using a generic, deterministic fixed-point quantization scheme commonly used in DNN accelerators [5]. However, we focus on the impact of quantization schemes on robustness against random bit errors, mostly neglected so far [14], [15], [16]. We find that quantization affects robustness significantly, even if accuracy is largely unaffected.

Fixed-Point Quantization: Quantization determines how weights are represented in memory, e.g., on SRAM. In a *fixed-point quantization* scheme, m bits allow to represent 2^m distinct values. A weight $w_i \in [-q_{\max}, q_{\max}]$ is represented by a *signed* m -bit integer $v_i = Q(w_i)$ corresponding to the underlying bits. Here, $[-q_{\max}, q_{\max}]$ is the *symmetric* quantization range and signed integers use

two’s complement representation. Then, $Q : [-q_{\max}, q_{\max}] \mapsto \{-2^{m-1} - 1, \dots, 2^{m-1} - 1\}$ is defined as

$$Q(w_i) = \left\lfloor \frac{w_i}{\Delta} \right\rfloor, Q^{-1}(v_i) = \Delta v_i, \Delta = \frac{q_{\max}}{2^{m-1} - 1}. \quad (4)$$

This quantization is symmetric around zero and zero is represented exactly. By default, we only quantize weights, not activations or gradients. However, in contrast to related work [26], [38], [40], [61], we quantize *all* layers, including biases and batch normalization parameters [56] (commonly “folded” into preceding convolutional layers). Flipping the most significant bit (MSB, i.e., sign bit) leads to an absolute error of half the quantization range, i.e., q_{\max} (yellow in Fig. 4). Flipping the least significant bit (LSB) incurs an error of Δ . Thus, the impact of bit errors “scales with” q_{\max} .

Global and Per-Layer Quantization: q_{\max} can be chosen to accommodate all weights, i.e., $q_{\max} = \max_i |w_i|$. This is called *global* quantization. However, it has become standard to apply quantization *per-layer* allowing to adapt q_{\max} to each layer. As in PyTorch [62], we consider weights and biases of each layer separately. By reducing the quantization range for each layer individually, the errors incurred by bit flips are automatically minimized, cf. Fig. 4. The **per-layer, symmetric quantization is our default reference**, referred to as NORMAL. However, it turns out that it is further beneficial to consider arbitrary quantization ranges $[q_{\min}, q_{\max}]$ (allowing $q_{\min} > 0$). In practice, we first map $[q_{\min}, q_{\max}]$ to $[-1, 1]$ and then quantize $[-1, 1]$ using Eq. (4). Overall, per-layer asymmetric quantization has the finest granularity, i.e., lowest Δ and approximation error. Nevertheless it is not the most robust quantization.

Robust Quantization: Eq. (4) does *not* provide optimal robustness against bit errors. First, the floor operation $\lfloor w_i/\Delta \rfloor$ is commonly implemented as float-to-integer conversion. Using proper rounding $\lceil w_i/\Delta \rceil$ instead has negligible impact on accuracy, even though quantization error improves slightly. In stark contrast, bit error robustness is improved considerably. During training, DNNs can compensate the differences in approximation errors, even for small precision $m < 8$. However, at test time, rounding decreases the impact of bit errors considerably. Second, Eq. (4) uses signed integers for symmetric quantization. For asymmetric quantization, with arbitrary $[q_{\min}, q_{\max}]$, we found quantization into *unsigned* integers to improve robustness, i.e., $Q : [q_{\min}, q_{\max}] \mapsto \{0, \dots, 2^m - 1\}$. This is implemented using an additive term of $2^{m-1} - 1$ in Eq. (4). While accuracy is not affected, the effect of bit errors in the sign bit changes: in symmetric quantization, the sign bit mirrors the sign of the weight value. For asymmetric quantization, an unsigned integer representation is more meaningful. Overall, our **robust fixed-point quantization (RQUANT)** uses per-layer, asymmetric quantization into unsigned integers with rounding. These seemingly *small differences* have little to no impact on accuracy but tremendous impact on robustness against bit errors, see Sec. 5.1.

4.2 Training with Weight Clipping as Regularization

Simple **weight clipping** refers to constraining the weights to $[-w_{\max}, w_{\max}]$ during training, where w_{\max} is a hyperparameter. Generally, w_{\max} is independent of the quantization range(s) which always adapt(s) to the weight range(s)




Fig. 6: **Effect of Weight Clipping.** On CIFAR10, weight clipping constrains the weights (right), thereby implicitly limiting the possible range for logits (left, blue). However, even for $w_{\max}=0.1$ the DNN is able to produce high confidences (middle, blue), suggesting that more weights are used to obtain these logits. Furthermore, the impact of random bit errors, $p = 1\%$, on the logits/confidences (red) is reduced significantly. RANDBET (trained with $p = 1\%$, w/o weight clipping), increases the range of weights and is less effective at preserving logit/confidence distribution.

at hand. However, weight clipping limits the maximum possible quantization range (cf. Sec. 4.1), i.e., $q_{\max} \leq w_{\max}$. It might seem that weight clipping with small w_{\max} automatically improves robustness against bit errors as the absolute errors are reduced. However, the *relative* errors are not influenced by rescaling. As the DNN’s decision is usually invariant to rescaling, reducing the scale of the weights does not impact robustness. In fact, the mean relative error of the weights in Fig. 4 (right) increased with clipping at $w_{\max}=0.1$. Thus, weight clipping does *not* “trivially” improve robustness by reducing the scale of weights. Nevertheless, we found that weight clipping actually improves robustness considerably on top of our robust quantization.

The interplay of weight clipping and minimizing the the cross-entropy loss during training is the key. High confidences can only be achieved by large differences in the logits. Because the weights are limited to $[-w_{\max}, w_{\max}]$, large logits can only be achieved using more weights in each layer to produce larger outputs. This is illustrated in Fig. 6 (right): using $w_{\max}=0.1$, the weights are (depending on the layer) up to 5 times smaller. Considering deep NNs, the “effective” scale factor for the logits is significantly larger, scaling exponentially with the number of layers. Thus, using $w_{\max}=0.1$ is a significant constraint on the DNNs ability to produce large logits. As result, weight clipping produces a much more uniform weight distribution. Fig. 6 (left and middle) shows that a DNN constrained at $w_{\max}=0.1$ can produce similar logit and confidence distributions (in blue) as the unclipped DNN. And random bit errors have a significantly smaller impact on the logits and confidences (in red). Fig. 6 (right column) also shows the induced redundancy in the weight distribution. Weight clipping leads to more weights being utilized, i.e., less weights are zero (note log-scale, marked in red, on the y-axis). Also, more weights reach large values. We found weight clipping to be an easy-to-use but effective measure to improve weight robustness.

Building on our preliminary work [22], **per-layer weight clipping** extends “global” weight clipping by allowing per-

TABLE 1: **Quantization Robustness.** RErr for random bit errors at $p = 0.05\%$ and $p = 0.5\%$ for normal training with different quantization schemes discussed in Sec. 4.1. Minor differences can have large impact on RErr while clean test error is largely unaffected. For 8 bit the second row shows NORMAL quantization (symmetric/per-layer) whereas the last row is our RQUANT. For 4 bits we show CLIPPING_{0.1} +RQUANT with and without rounding.

Quantization Schemes (CIFAR10)		Err in %	RErr in %	
			$p=0.05$	$p=0.5$
8 bit	Eq. (4), global	4.63	86.01 ±3.65	90.71 ±0.49
	Eq. (4), per-layer	4.36	5.51 ±0.19	24.76 ±4.71
	+asymmetric	4.36	6.47 ±0.22	40.78 ±7.56
	+unsigned	4.42	6.97 ±0.28	17.00 ±2.77
	+rounding (=RQUANT)	4.32	5.10 ±0.13	11.28 ±1.47
4 bit	w/o rounding*	5.81	90.40 ±0.21	90.36 ±0.2
	w/ rounding*	5.29	5.75 ±0.06	7.71 ±0.36

layer weight constraints $w_{\max,l}$. This is based on the observation that weights in different layers can have radically different ranges. Clipping weights globally to $[-w_{\max}, w_{\max}]$ may result in only few layers being actually constrained and regularized. The regularization effect is less pronounced for the remaining layers, reducing the potential impact in terms of robustness. Thus, *per-layer* weight clipping constraints each layer l individually to $[-w_{\max,l}, w_{\max,l}]$. Here, weights and biases are treated individually as biases exhibit significantly different ranges. The per-layer constraints $w_{\max,l}$ are derived from the relative weight ranges of a DNN without weight clipping. For example, we found that the first convolutional layer as well as the logit layer usually have significantly larger range. Letting $w_{l,i}$ be the weights of layer l with the largest absolute weight value, we define $\kappa_{l'} = \max_i |w_{l',i}| / \max_i |w_{l,i}| \leq 1$ for all other layers l' . Then, for each l' , we define $w_{\max,l'}$ as $\max(0.2, \kappa_{l'})w_{\max}$. CLIPPING _{$w_{\max}=0.1$} to refer to *global* weight clipping with, e.g., $w_{\max} = 0.1$, and PLCLIPPING _{$w_{\max}=0.25$} to denote *per-layer* weight clipping with, e.g., $w_{\max} = 0.25$. For more results supporting the regularization effect of (per-layer) weight clipping, see our supplementary material.

4.3 Random Bit Error Training (RANDBET)

In *addition* to weight clipping and robust quantization, we inject random bit errors with probability p during training to further improve robustness. This results in the following learning problem, which we optimize as illustrated in Fig. 5:

$$\begin{aligned} \min_w \mathbb{E}[\mathcal{L}(f(x; \tilde{w}), y) + \mathcal{L}(f(x; w), y)] \\ \text{s.t. } v = Q(w), \tilde{v} = \text{BErr}_p(v), \tilde{w} = Q^{-1}(\tilde{v}). \end{aligned} \quad (5)$$

where (x, y) are labeled examples, \mathcal{L} is the cross-entropy loss and $v = Q(w)$ denotes the (element-wise) quantized weights w which are to be learned. $\text{BErr}_p(v)$ injects random bit errors with rate p in v . Note that we consider both the loss on clean weights and weights with bit errors. This is desirable to avoid an increase in (clean) test error and stabilizes training compared to training only on bit errors in the weights. Note that bit error rate p implies, in expectation, pmW bit errors. Following Alg. 2, we use stochastic gradient descent to optimize Eq. (5), by performing the gradient computation using the perturbed weights $\tilde{w} = Q^{-1}(\tilde{v})$ with $\tilde{v} = \text{BErr}_p(v)$, while applying the gradient update

TABLE 2: **Weight Clipping Robustness.** Clean Err and RErr as well as clean confidence and confidence at $p=1\%$ bit errors (in %, higher is better, \uparrow) for CLIPPING, CLIPPING with label smoothing (+LS) and PLCLIPPING. Err increases for CLIPPING _{$w_{\max} = 0.025$} where the DNN is not able to produce large (clean) confidences. LS consistently reduces robustness, indicating that robustness is due to enforcing high confidence during training *and* weight clipping. Per-layer weight constraints are beneficial in terms of both robustness and clean performance, i.e., RErr and Err. Finally, using batch normalization (BN) worsens robustness significantly.

Model (CIFAR10)	Err in %	Conf in %	Conf $p=1$	RErr in %	
				$p=0.1$	$p=1$
RQUANT	4.32	97.42	78.43	5.54	32.05
CLIPPING _{0.15}	4.42	96.90	88.41	5.31	13.08
CLIPPING _{0.1}	4.82	96.66	92.97	5.58	8.93
CLIPPING _{0.05}	5.44	95.90	94.73	5.90	7.18
CLIPPING _{0.025}	7.10	84.69	83.28	7.40	8.18
CLIPPING _{0.15} +LS	4.67	88.22	47.55	5.83	29.40
CLIPPING _{0.1} +LS	4.82	87.90	78.89	6.10	10.59
CLIPPING _{0.05} +LS	5.30	87.41	85.04	6.43	7.30
PLCLIPPING _{0.5}	4.61	97.06	91.31	5.48	10.9
PLCLIPPING _{0.25}	4.96	96.90	95.67	5.39	7.04
PLCLIPPING _{0.1}	5.62	94.57	93.98	5.91	6.65
CLIPPING _{0.1} (BN)	4.46	97.09	84.86	5.32	18.32

on the (floating-point) clean weights w . In spirit, this is similar to data augmentation, however, the perturbation is applied on the weights instead of the inputs. As we found that introducing bit errors right from the start may prevent the DNN from converging, we apply bit errors as soon as the (clean) cross-entropy loss is below 1.75. Interestingly, weight clipping and RANDBET have somewhat orthogonal effects, which allows to combine them easily in practice: While weight clipping encourages redundancy in weights by constraining them to $[-w_{\max}, w_{\max}]$, RANDBET (w/o weight clipping) causes the DNN to have larger tails in the weight distribution, as shown in Fig. 6 (bottom). However, considering logits and confidences, especially with random bit errors (in red), RANDBET alone performs slightly worse than CLIPPING_{0.1}. Thus, RANDBET becomes particularly effective when combined with weight clipping, as we make explicit using the notation RANDBET _{w_{\max}} and in Alg. 2.

4.4 Adversarial Bit Error Training (ADVBET)

In order to specifically address adversarial bit errors (cf. Sec. 3.2), RANDBET can be re-formulated to train with adversarial bit errors. Essentially, this results in a min-max formulation similar to [20]:

$$\begin{aligned} \min_w \mathbb{E}[\max_{\tilde{v}} \mathcal{L}(f(x; Q^{-1}(\tilde{v})), y)] \\ \text{s.t. } d_H(\tilde{v}, v) \leq \epsilon, d_H(\tilde{v}_i, v_i) \leq 1 \end{aligned} \quad (6)$$

where the inner maximization problem, i.e., the attack is solved following Alg. 1. In addition to not training on adversarial bit errors for a (clean) cross-entropy above 1.75, we clip gradients to $[-0.05, 0.05]$. This is required as the cross-entropy loss on adversarially perturbed weights \tilde{w} can easily be one or two magnitudes larger than on the clean weights. Unfortunately, training is very sensitive to the hyper-parameters of the attack, including the step size, gradient normalization and momentum. This holds both for convergence during training as well as for the obtained robustness after training.

TABLE 3: **Fixed Pattern Bit Error Training.** RErr for training on an entirely fixed bit error pattern (PATTBET). *Top:* Evaluation on the same pattern; PATTBET trained on $p = 2.5\%$ does not generalize to $p = 1\%$ even though the bit errors for $p = 1\%$ are a subset of those seen during training for $p = 2.5\%$ (in red). *Bottom:* PATTBET also fails to generalize to completely random bit errors.

Model (CIFAR10)	RErr in %, p in %	
Evaluation on Fixed Pattern	$p=1$	$p=2.5$
PATTBET $p=2.5$	14.14	7.87
PATTBET _{0.15} $p=2.5$	8.50	7.41
Evaluation on Random Patterns	$p=1$	$p=2.5$
PATTBET _{0.15} $p=2.5$	12.09	61.59

5 EXPERIMENTS

We present experiments on MNIST [63] and CIFAR [64], considering *random* bit error robustness first, followed by discussing *adversarial* bit errors. To this end, we first analyze the impact of fixed-point quantization schemes on robustness (Sec. 5.1). Subsequently, we discuss weight clipping (CLIPPING, Sec. 5.2), showing that improved robustness originates from increased redundancy in the weight distribution. Then, we focus on random bit error training (RANDBET, Sec. 5.3). We show that related work [4], [19] does not generalize, while RANDBET generalizes across chips and voltages, as demonstrated on profiled bit errors. We further consider random bit errors in inputs and activations (Sec. 5.4). Finally, we discuss our adversarial bit error attack in comparison to BFA [12] (Sec. 5.5) and show that CLIPPING as well as RANDBET or ADVBET increase robustness against adversarial bit errors significantly.

Metrics: We report (clean) test error Err (lower is better, ↓), corresponding to *clean* weights, and **robust test error RErr** (↓) which is the **test error after injecting bit errors into the weights**. For random bit errors we report the *average* RErr and its standard deviation for 50 samples of random bit errors with rate p as detailed in Sec. 3. For adversarial bit errors, we report *max* (i.e., worst-case) RErr across a total of 80 restarts as described in detail in Sec. 5.5. Evaluation is performed on 9000 test examples.

Architecture: We use SimpleNet [65], providing comparable performance to ResNets [66] with only $W=5.5$ Mio weights on CIFAR10. On MNIST, we halve all channel widths, resulting in roughly 1Mio weights. On CIFAR100, we use a Wide ResNet (WRN) [67] with group normalization (GN) [55]. Batch normalization (BN) [56] works as well but models using BN yield consistently worse robustness against bit errors, see Sec. 5.5 or Tab. 2.

Training: We use stochastic gradient descent with an initial learning rate of 0.05, multiplied by 0.1 after $2/5$, $3/5$ and $4/5$ of 100/250 epochs on MNIST/CIFAR. On CIFAR, we whiten the input images and use AutoAugment [68] with Cutout [69]. For RANDBET, random bit error injection starts when the loss is below 1.75 on MNIST/CIFAR10 or 3.5 on CIFAR100. Normal training with the standard and our robust quantization are denoted NORMAL and RQUANT, respectively. Weight clipping with w_{\max} is referred to as CLIPPING _{w_{\max}} , corresponding to results from [22], and its per-layer variant is denoted PLCLIPPING _{w_{\max}} . Similarly, we refer to RANDBET/ADVBET with (global) weight clipping as RANDBET _{w_{\max}} /ADVBET _{w_{\max}} and with per-layer weight

TABLE 4: **Random Bit Error Training (RANDBET).** Average RErr (and standard deviation) of RANDBET evaluated at various bit error rates p and using $m = 8$ or 4 bit precision. For low p , weight clipping provides sufficient robustness, especially considering PLCLIPPING. However for $p \geq 0.5$, RANDBET increases robustness significantly, both based on CLIPPING and PLCLIPPING. This is particularly pronounced for low-precision, e.g., $m = 4$ bits.

	Model (CIFAR10) p in %	Err in %	RErr in %		
			$p=0.5$	$p=1$	$p=1.5$
8bit	RQUANT	4.32	11.28 ±1.47	32.05 ±6	68.65 ±9.23
	CLIPPING _{0.1}	4.82	6.95 ±0.24	8.93 ±0.46	12.22 ±1.29
	PLCLIPPING _{0.25}	4.96	6.21 ±0.16	7.04 ±0.28	8.14 ±0.49
	RANDBET _{0.1} $p=0.1$	4.72	6.74 ±0.29	8.53 ±0.58	11.40 ±1.27
	RANDBET _{0.1} $p=1$	4.90	6.36 ±0.17	7.41 ±0.29	8.65 ±0.37
	PLRANDBET _{0.25} $p=0.1$	4.49	5.80 ±0.16	6.65 ±0.22	7.59 ±0.34
	PLRANDBET _{0.25} $p=1$	4.62	5.62 ±0.13	6.36 ±0.2	7.02 ±0.27
4bit	CLIPPING _{0.1}	5.29	7.71 ±0.36	10.62 ±1.08	15.79 ±2.54
	PLCLIPPING _{0.25}	4.63	6.15 ±0.16	7.34 ±0.33	8.70 ±0.62
	RANDBET _{0.1} $p=1$	5.39	7.04 ±0.21	8.34 ±0.42	9.77 ±0.81
	PLRANDBET _{0.25} $p=1$	4.83	5.95 ±0.12	6.65 ±0.19	7.48 ±0.32

clipping as PLRANDBET _{w_{\max}} . For RQUANT, $m = 8$, we obtain 4.3% Err on CIFAR10 and 18.5% Err on CIFAR100; on MNIST, 0.47% Err for $m = 2$.

Our **supplementary material** includes implementation details, more information on our experimental setup, and complementary experiments: robustness of BN, other architectures, qualitative results for CLIPPING and complete results for $m = 4, 3, 2$ bits precision. Also, we discuss a simple guarantee how the average RErr relates to the true expected robust error. Our **code** will be made available.

5.1 Quantization Choice Impacts Robustness

Quantization schemes affect robustness significantly, even when not affecting accuracy. For example, Tab. 1 shows that per-layer quantization reduces RErr significantly for small bit error rates, e.g., $p = 0.05\%$. While asymmetric quantization further reduces the quantization range, RErr increases, especially for large bit error rates, e.g., $p = 0.5\%$ (marked in red). This is despite Fig. 4 showing a slightly smaller impact of bit errors. This is caused by an asymmetric quantization into *signed* integers: Bit flips in the most significant bit (MSB, i.e., sign bit) are not meaningful if the quantized range is not symmetric as the sign bit does not reflect the sign of the represented weight value. Similarly, replacing integer conversion of w_i/Δ by proper rounding, $\lceil w_i/\Delta \rceil$, reduces RErr significantly (resulting in our RQUANT). This becomes particularly important for $m = 4$. Here, rounding also improves clean Err slightly, but the effect is significantly less pronounced. Proper rounding generally reduces the approximation error of the quantization scheme. These errors are magnified when considering bit errors at test time, even though DNNs can compensate such differences during training to achieve good accuracy, i.e., low Err. For $m = 4$ or lower, we also found weight clipping to help training, obtaining lower Err. Overall, we show that random bit errors induce unique error distributions in DNN weights, heavily dependent on details of the employed fixed-point quantization scheme. We think that robustness against bit errors should become an important criterion for the design of DNN quantization. While our RQUANT performs fairly

TABLE 5: **Generalization to Profiled Bit Errors.** RErr for RANDBET and PLRANDBET on two different profiled chips. The bit error rates differ across chips due to measurements at different voltages, also see Fig. 3. Chip 2 exhibits a bit error distribution significantly different from uniform random bit errors: bit errors are strongly aligned along columns and biased towards 0-to-1 flips, cf. Fig. 3. Nevertheless, RANDBET generalizes surprisingly well.

Chip (Fig. 3)	Model (CIFAR10)	RErr in %	
Chip 1		$p \approx 0.86$	$p \approx 2.75$
	RANDBET _{0.05} $p=1.5$	7.04	9.37
	PLRANDBET _{0.15} , $p=2$	6.14	7.58
Chip 2		$p \approx 0.14$	$p \approx 1.08$
	RANDBET _{0.05} $p=1.5$	6.00	9.00
	PLRANDBET _{0.15} , $p=2$	5.34	7.34

well, finding an “optimal” robust quantization scheme is an interesting open problem.

5.2 Weight Clipping Improves Robustness

While the quantization range adapts to the weight range after every update during training, weight clipping explicitly constraints the weights to $[-w_{\max}, w_{\max}]$. Tab. 2 shows the effect of different w_{\max} for CIFAR10 with 8 bit precision. The clean test error is not affected for CLIPPING _{$w_{\max}=0.15$} but one has already strong robustness improvements for $p = 1\%$ compared to RQUANT (RErr of 13.18% vs 32.05%). Further reducing w_{\max} leads to a slow increase in clean Err and decrease in average clean confidence, while significantly improving RErr to 7.18% for $p = 1\%$ at $w_{\max} = 0.05$. For $w_{\max} = 0.025$ the DNN is no longer able to achieve high confidence (marked in red) which leads to stronger loss of clean Err. Interestingly, the gap between clean and perturbed confidences under bit errors for $p = 1\%$ is (almost) monotonically decreasing. These findings generalize to other datasets and precisions. However, for low precision $m \leq 4$ the effects are stronger as RQUANT alone does not yield any robust models and weight clipping is essential for achieving robustness.

As discussed in Sec. 4.2 the robustness of the DNN originates in the cross-entropy loss enforcing high confidences on the training set and, thus, large logits while weight clipping works against having large logits. Therefore, the network has to utilize more weights with larger absolute values (compared to w_{\max}). In order to test this hypothesis, we limit the confidences that need to be achieved via label smoothing [70], targeting 0.9 for the true class and $0.1/9$ for the other classes. According to Sec. 4.2, this should lead to less robustness, as the DNN has to use “less” weights. Indeed, in Tab. 2, RErr at $p = 1\%$ increases from 13.08% for CLIPPING_{0.15} to 29.4% when using label smoothing (marked in blue). Moreover, the difference between average clean and perturbed confidence is significantly larger for DNNs trained with label smoothing.

Per-layer weight clipping, i.e., PLCLIPPING, further improves robustness and at the same time lowers test error compared to CLIPPING. For example, in Tab. 2, PLCLIPPING_{0.2} reduces RErr for $p=1\%$ to 6.48% compared to 7.18 for CLIPPING_{0.05}. Simultaneously, clean Err improves from 5.44% to 4.84. This emphasizes that layers can have radically different weight ranges and, thus, regularization

TABLE 6: **Robustness of Post-Training Quantization.** RErr for PLCLIPPING and L_0 RANDBET, i.e., our error training with L_0 errors on weights. Note that we train *without* quantization, quantize the DNNs post-training with $m = 8$ or 4 bits and evaluate robustness against $p = 1\%$ random bit errors. Weight clipping and L_0 -based error training allow to train robust models without knowing the quantization scheme in advance. However, note that clean Err generally increases slightly compared to quantization-aware training. * Err reported for the $m = 8$ bit PLRANDBET model.

Model (CIFAR10) ($p_{L_0} = L_0$ error rate in train.)	Err in %	RErr in %, $p = 1\%$	
		8bit	4bit
PLCLIPPING _{0.5}	4.61	11.28 ± 1.14	16.93 ± 2.77
PLCLIPPING _{0.2}	5.08	6.85 ± 0.24	7.21 ± 0.23
PLL ₀ RANDBET _{0.2} , $p_{L_0}=1$	5.01	6.58 ± 0.17	7.01 ± 0.22
PLL ₀ RANDBET _{0.2} , $p_{L_0}=4$	5.23	6.57 ± 0.13	6.89 ± 0.13
PLL ₀ RANDBET _{0.2} , $p_{L_0}=8$	5.49	6.73 ± 0.16	6.95 ± 0.14
PLRANDBET _{0.2} , $p=1$	4.92*	6.29 ± 0.14	6.60 ± 0.18

through weight clipping needs to be layer-specific. In our supplementary material we also show that weight clipping also leads to robustness against L_∞ perturbations which generally affect all weights in contrast to random bit errors, and provide more qualitative results about the change of the weight distribution induced by clipping.

5.3 RANDBET Yields Generalizable Robustness

In the following, we present experiments on RANDBET, showing that training on fixed, profiled bit errors patterns is not sufficient to generalize across voltages and chips. Thus, training on random bit errors in RANDBET is essential, and further improves robustness when applied on top of RQUANT and CLIPPING. Finally, we present results when evaluating RANDBET on real, profiled bit errors corresponding to three different chips. Furthermore, both CLIPPING and RANDBET can also be applied in a post-training quantization setting by replacing random bit errors during RANDBET with L_0 errors in weights.

Training on Profiled Errors Does Not Generalize: Co-design approaches such as [4], [19] combine training DNNs on profiled SRAM or DRAM bit errors with hardware-approaches to limit the errors’ impact. However, profiling SRAM or DRAM requires expensive infrastructure, expert knowledge and time. More importantly, training on profiled bit errors does not generalize to previously unseen bit error distributions (e.g., other chips or voltages): Tab. 3 (top) shows RErr of PATTBET, i.e., pattern-specific bit error training. The main problem is that PATTBET does not even generalize to lower bit error rates (i.e., higher voltages) of the same pattern as trained on (marked in red). This is striking as, following Fig. 3, the bit errors form a subset of the bit errors seen during training: training with $p = 2.5\%$ bit errors does not provide robustness for $p = 1\%$, RErr increases 7.9% to 14.1%. It is not surprising, that Tab. 3 (bottom) also demonstrates that PATTBET does not generalize to random bit error patterns: RErr increases from 7.4% to 61.6% at $p = 2.5\%$. The same observations can be made when training on real, profiled bit errors corresponding to the chips in Fig. 3. Overall, obtaining robustness that generalizes across voltages *and* chips is crucial for low-voltage operation to become practical.




Fig. 7: **Bit Error Robustness on CIFAR10, CIFAR100 and MNIST.** Average RErr plotted against bit error rate p , both in %. We considered various models (in \bullet gray), corresponding to different w_{\max} and p during training. We explicitly plot the best model for each bit error rate: for NORMAL (orange), RQUANT (red), CLIPPING (blue) and RANDBET (violet). Note that these might correspond to different w_{\max} and p (also across datasets). Across all approaches, we plot the per-error-rate best model in black: for $m = 8, 4, 3, 2$ bits, depending on dataset. For 8 bit and low bit error rates, CLIPPING is often sufficient. However, for 4 bit or higher bit error rates, RANDBET is crucial to keep RErr low.

RANDBET Improves Robustness: Our RANDBET, combined with weight clipping, further improves robustness and additionally generalizes across chips and voltages. Tab. 4 shows results for weight clipping and RANDBET with $w_{\max} = 0.1$ and $m = 8, 4$ bits precision. RANDBET is particularly effective against large bit error rates, e.g., $p = 1.5\%$, reducing RErr from 12.22% to 8.65% ($m = 8$ bits) with global weight clipping and even further to 7.02% with per-layer clipping, i.e. PLRANDBET. The effect is pronounced for 4 bits or even lower precision, where models are generally less robust. The optimal combination of weight clipping and RANDBET depends on the bit error rate. However, we note that RANDBET consistently improves over CLIPPING or PLCLIPPING. For example, in Tab. 2, lowering w_{\max} to 0.05 reduces RErr below RANDBET_{0.1} with $p=1\%$ for some bit error rates. Similarly observations hold for PLCLIPPING. We also emphasize that RANDBET generalizes to lower bit errors than trained on, in stark contrast to the fixed-pattern training PATTBET. On other datasets, e.g., MNIST, RANDBET allows to operate at $p = 15\%$ bit error rate with 0.68% RErr and only $m = 2$ bits. At this point, weight clipping alone yields 90% RErr.

RANDBET Generalizes to Profiled Bit Errors: RANDBET also generalizes to bit errors profiled from real chips, corresponding to Fig. 3. Tab. 5 shows results on the two profiled chips of Fig. 3. Profiling was done at various voltage levels, resulting in different bit error rates for each chip. To simulate various weights to memory mappings, we apply various offsets before linearly mapping weights to the profiled SRAM arrays. Tab. 5 reports average RErr, showing that RANDBET generalizes quite well to these profiled bit errors. Regarding chip 1, RANDBET performs very well, even for large $p \approx 2.75$, as the bit error distribution of chip 1 largely matches our error model in Sec. 3, cf. Fig. 3 (left). In contrast, with chip 2 we picked a more difficult bit error distribution which is strongly aligned along columns, potentially hitting many MSBs simultaneously. Thus, RErr is similar for chip 2 even for a lower bit error rate $p \approx 1.08$ (marked in red) but energy savings are still possible without degrading prediction performance.

RANDBET and Post-Training Quantization: So far,

we applied quantization during training, i.e., we performed quantization-aware training [26], [27]. However, both (global and per-layer) weight clipping as well as (bit) error training can be applied in a post-quantization setting. To this end, for RANDBET, bit errors are simulated through L_0 noise on weights. Specifically, with probability p_{L_0} each weight w_i is changed to a (uniformly) random value $\tilde{w}_i \in [-w_{\max}, w_{\max}]$. The same error model applies for per-layer weight clipping. Note that training with L_0 errors with probability p_{L_0} simulates bit error training with $p = m \cdot p_{L_0}$, referred to as L_0 RANDBET. We apply our robust fixed-point quantization with $m = 8$ bits after training to evaluate robustness to random bit errors. In Tab. 6, we demonstrate that both CLIPPING and L_0 RANDBET also provide robustness in a post-quantization context. This allows to train robust models without knowing the exact quantization and precision used for deployment in advance.

Summary: Our experiments are summarized in Fig. 7. We consider NORMAL quantization vs. our robust quantization RQUANT, various CLIPPING and RANDBET models with different w_{\max} and p during training (indicated in \bullet gray) and plot RErr against bit error rate p at test time. On all datasets RQUANT outperforms NORMAL. On CIFAR10 (left), RErr increases significantly for RQUANT (red) starting at $p \approx 0.25\%$ bit error rate. While CLIPPING (blue) generally reduces RErr, only RANDBET (violet) can keep RErr around 6% or lower for a bit error rate of $p \approx 0.5\%$. The best model for each bit error rate p (black and solid for $m = 8$) might vary. CIFAR100 is generally more difficult, while significantly higher bit error rates are possible on MNIST. On CIFAR10, RErr increases slightly for $m = 4$. However, for $m = 3, 2$ RErr increases more significantly as clean Err increases by 1 – 2%. Nevertheless, RErr only increases slightly for larger bit error rates p . In all cases, RErr increases monotonically, ensuring safe operation at higher voltages. The best trade-off depends on the application: higher energy savings require a larger “sacrifice” in terms of RErr. Our supplementary material includes a confidence-interval based guarantee showing that RErr will not deviate strongly from the results in Fig. 7.

TABLE 7: **Bit Errors in Inputs and Activations.** Average RErr for PLCLIPPING and PLRANDBET against bit errors in weights, inputs and activations. We use PLRANDBET to inject bit errors in weights (rate p_w), bit errors in inputs (rate p_i , orange) and/or bit errors in activations (rate p_a , violet) during training. Bit errors in inputs and activations are difficult to tolerate. Extreme CLIPPING (e.g., w_{\max}) might worsen robustness against bit errors in inputs/activations. PLRANDBET against bit errors in weights, inputs and activations is significantly harder, resulting in higher Err, while improving robustness considerably.

Model (CIFAR10) $w_{\max}=0.25$, $m=8$ bit weight/inp./act. quantization bit errors in weights/inp./act., p in %	Err in %	bit errors in weights		bit errors in inp.		Err in % (act. quant.)	bit errors in act.	
		RErr in %		RErr in %			RErr in %	
		$p=0.1$	$p=1$	$p=0.1$	$p=0.5$		$p=0.1$	$p=0.5$
PLCLIPPING	4.96	5.39	7.04	10.80	22.80	5.16	7.38	21.58
PLCLIPPING _{0.1}	5.62	5.91	6.65	12.80	26.50	5.84	8.72	27.36
PLRANDBET, $p_w=0.1$	4.49	4.98	6.65	11.00	22.80	4.71	7.25	24.94
PLRANDBET, $p_w=1$	4.62	5.02	6.36	11.30	22.40	4.83	6.92	19.83
PLRANDBET, $p_w=1$, $p_i=0.1$	5.50	5.99	7.49	7.70	9.10	5.71	8.37	25.83
PLRANDBET, $p_w=1$, $p_i=0.1$, $p_a=0.1$	9.16	9.60	11.09	11.50	13.80	9.31	10.54	13.51
PLRANDBET, $p_a=0.5$	5.43	5.91	7.96	10.90	21.90	5.68	6.74	10.16
PLRANDBET, $p_w=1$, $p_a=0.1$	7.66	8.27	10.47	13.80	24.70	7.89	9.09	12.17

5.4 Robustness to Bit Errors in Inputs and Activations

While RANDBET successfully improves robustness against low-voltage induced bit errors in the *weights*, both inputs and activations might also be subject to random bit errors when (temporarily) stored on the SRAM scratchpad. Thus, we also consider injecting bit errors in inputs and activations, making first steps towards a “fully” robust DNN. First, we take a closer look at the impact of bit errors in inputs and activations. Then, we adapt RANDBET to improve robustness. For Clarity, in text and Tab. 7, we use p_w , p_i and p_a to denote the bit error rate in weights, inputs and activations, respectively. We further color-code bit errors in inputs as orange and activations as violet.

Bit Error Model in Inputs and Activations: Following our description in Sec. 3.1, we inject bit errors in both inputs and activations. Inputs are quantized using $m = 8$ bit with $[q_{\min}, q_{\max}] = [0, 1]$. Note that this does not introduce errors as images are typically provided in 8 bit quantization per channel. Activations are also quantized using $m = 8$ bit using our robust fixed-point quantization scheme. Note that we do not employ any advanced activation quantization schemes such as activation clipping [34]. Bit errors are injected *once* into inputs before being fed to the DNN and *once* into the activations after *each* block consisting of convolutional layer, normalization layer (i.e., GN) and ReLU activation. This assumes that activations after each such block are temporally stored on the SRAM scratchpads. As detailed in Sec. 3.1, while the actual data flow is highly specific to both chip and DNN architecture, this is a realistic assumption. As with bit errors in the weights, we evaluate using 50 random bit error patterns and make sure that for rate $p' \leq p$ the bit errors introduced in inputs/activations are a subset of those for rate p . We refer to our supplementary material for additional details.

Input and Activation Bit Error Robustness: Bit errors have severe impact on accuracy not only when occurring in weights but also in inputs and activations. Tab. 7 shows robustness, i.e., average RErr, of various models on CIFAR10 against bit errors in weights, inputs (in orange) or activations (in violet). For activation quantization, we additionally report the (clean) Err *after* activation quantization (without bit errors). While being simplistic, our activation quantization has negligible impact on Err. We found bit errors in inputs and activations to be challenging in terms

of robustness. Even for small bit error rates, e.g., $p = 0.1\%$, RErr increases significantly, to at least 7.7% and 6.92% RErr for inputs and activations, respectively. While PLRANDBET (training on random bit errors *in weights*) helps against bit errors in activations, it has no impact on robustness against bit errors in inputs. Extreme PLCLIPPING, in contrast, e.g., using $w_{\max} = 0.1$ tends to reduce robustness in both cases. These results show that low-voltage operation is complicated when taking inputs and activations into account. While separate SRAM arrays for weights, inputs and activations can be used, allowing varying levels of bit errors, this is potentially undesirable from a design perspective.

RANDBET for Inputs and Activations: In order to obtain robustness against random bit errors in inputs and/or activations, we adapt RANDBET to allow bit error injection in inputs and/or activations (in addition to weights) during training. Tab. 7 shows that injecting either input bit errors (bit error rate p_i in orange) or activation bit errors (bit error rate p_a in violet) helps robustness, but also makes training significantly more difficult. Indeed, injecting bit errors in weights, inputs *and* activations increases (clean) Err significantly, to 9.16% from 4.62% (for RANDBET with bit errors in weights only). We found that this difficulty mainly stems from injecting bit errors in activations during training: While RANDBET (activations only) with $p_a=0.5\%$ affects (clean) Err only slightly (5.43%), bit errors in weights *and* activations (i.e., $p_w=1\%$ and $p_a=0.1\%$) results in an increase to 7.66%. This increase in Err also translates to an increase in RErr against bit errors in weights or activations. As a result, injecting bit errors only in weights and inputs (e.g., $p_w=1\%$ and $p_i = 0.1\%$) might be beneficial as it avoids a significant increase in (clean) Err, while still providing some robustness against bit errors in activations. Overall, we made a significant step towards DNNs “fully” robust against low-voltage induced random bit errors, but the problem remains difficult.

5.5 Robustness Against Adversarial Bit Errors

In this section, we switch focus and consider *adversarial* bit error robustness. To this end, we consider both the BFA attack from related work [11] and our own adversarial bit error attack from Sec. 3.2. As “defense”, we consider CLIPPING, RANDBET and our adversarial bit error training

TABLE 8: **Bit Flip Attack (BFA)** [11]. Worst RErr for RQUANT, CLIPPING and ADVBET against the bit flip attack (BFA) of [11] for various allowed budgets ϵ of bit errors. On CIFAR10, we also present results when using batch normalization (BN). Surprisingly, CLIPPING is quite successful in “defending” BFA as long as BN is avoided, even for very large ϵ . In Tab. 9, our adversarial bit error attack outperforms BFA significantly.

Model / Dataset	RErr in % for ϵ Bit Errors			
	$\epsilon=80$	$\epsilon=160$	$\epsilon=240$	$\epsilon=320$
MNIST				
RQUANT	77.88	90.11	89.94	90.04
CLIPPING _{0.05}	10.11	11.22	89.18	57.28
ADVBET _{0.05, $\epsilon=160$}	0.42	10.08	10.13	20.09
CIFAR10				
RQUANT BN	89.30	89.26	89.56	89.32
RQUANT (GN)	34.42	89.01	90.10	90.02
CLIPPING _{0.05} BN	89.48	89.16	89.19	89.40
CLIPPING _{0.05} (GN)	14.84	24.96	49.56	51.88
ADVBET _{0.05, $\epsilon=160$} (GN)	13.72	15.53	25.91	44.47




Fig. 8: **BFA Iterations**. RErr and loss (after bit errors, in red) plotted against BFA iterations. We allow 5 bit flips per iteration, totaling 960 bit errors for 192 iterations. RErr tends to increase (roughly) in steps of $\sim 10\%$ by flipping predictions consecutively to a constant one for each class.

(ADVBET) which are able to improve robustness considerably – both against BFA and our adversarial bit level attack.

We train ADVBET using $T = 10$ iterations of our adversarial bit error attack, with learning rate 0.5 (no momentum) after normalizing the gradient by its L_∞ norm, cf. Alg. 1. For evaluation, we use the official BFA implementation and run it for 5 restarts. Each run, we allow 5 bit flips per iteration, resulting in a total of $5 \cdot T$ allowed bit flips with T iterations, i.e., $\epsilon := 5 \cdot T$ in our adversarial bit error model. We run our adversarial bit error attack for $T = 100$ iterations, allowing the same number of bit errors ϵ . For comprehensive evaluation, we consider a total of 80 random restarts for various combinations of hyper-parameters. We compute our adversarial bit error attack, i.e., solve Eq. (1), on 100 held-out test examples and evaluate, as described before, on 9000 test examples.

Limitations of BFA: We start by considering BFA, showing that it is not as effective (and efficient) against our DNNs, compared to the results in [11]. Tab. 8 reports worst (i.e., max) RErr on MNIST and CIFAR10 for various models. On MNIST, BFA is effective in attacking our RQUANT model, even for only $\epsilon=80$ bit errors, increasing RErr to 77.88%. However, CLIPPING seems to provide good inherent robustness, at least for low ϵ up to 160. The same holds on CIFAR10. Here, we also show results considering batch normalization (BN, marked in red), as used in [11]. Similar to RQUANT, when training CLIPPING with BN, the DNN is significantly less robust. In fact, BFA is suddenly able to increase RErr beyond 90%, while RErr for CLIPPING with GN is still at 15.53% for $\epsilon=320$. However, we found that BFA does *not* attack the batch normalization parameters (i.e.,

TABLE 9: **Adversarial Bit Error Ablation**. Worst RErr for RQUANT and CLIPPING, considering different ϵ and settings on CIFAR10: attacking only the **logit** layer (i.e., last layer), or only first **convolutional** layer, using untargeted (“U”) or targeted (“T”) attacks. Targeted attacks are usually easier to optimizer and more effective. The first convolutional or logit layer is particularly vulnerable.

	Err %	Worst RErr in %			
		U (all)	T (all)	log	conv
MNIST ($W \approx 1\text{Mio}$)		$\epsilon=160$			
RQUANT	0.37	0.48	0.51	91.08	85.42
CLIPPING _{0.05}	0.38	2.30	0.74	10.77	85.09
ADVBET _{0.05, $\epsilon=240$}	0.29	11.58	0.34	0.36	0.46
CIFAR10 ($W \approx 5.5\text{Mio}$)		$\epsilon=320$			
RQUANT	4.89	8.54	91.18	91.18	89.06
CLIPPING _{0.05}	5.34	24.04	35.20	35.86	60.76
ADVBET _{0.05, $\epsilon=160$}	5.54	10.01	20.20	26.22	12.33




Fig. 9: **Adversarial Bit Error Iterations**. We plot loss, cf. Eq. (1), and robust error RErr against iterations, both measured on the 100 held-out test examples used to find, i.e., train, adversarial bit errors. Clearly, L_∞ gradient normalization with momentum (in red), targeting first convolutional (yellow) or logit layer (violet) is most effective for untargeted attacks. Unfortunately, the attack gets easily stuck in bad optima if learning rate is not optimal. Targeted attacks simplify optimization and are often more effective (black, right).

scale and bias). Instead, as shown in Tab. 2 against random bit errors, we found that BN is generally less robust. Finally, Fig. 8 shows RErr and loss over BFA iterations. While loss increases continuously, RErr tends to increase roughly in steps of 10%. This is because BFA consecutively flips the labels for each class to a constant class, eventually arriving at 90% RErr which is equivalent to a random or constant classifier. However, BFA needs between 1 and 2 seconds per iteration and the number of bit flips is (indirectly) tied to the number of iterations, which is also the reason why loss increases monotonically in Fig. 8. This makes BFA unfit to be used for ADVBET. We address some of these limitations using our adversarial bit error attack from Sec. 3.2.

More Effective Adversarial Bit Errors: Using appropriate hyper-parameters and considering *both* untargeted and targeted attacks, our adversarial bit error attack is more effective and efficient compared to BFA. Tab. 9 shows (worst) RErr on MNIST and CIFAR10, showing that our adversarial bit errors achieve higher RErr compared to BFA, e.g., for $\epsilon=320$. As also reported in [12], we found that targeted attacks are generally more effective. This is because the “easiest” way to increase RErr is to force the DNN to predict a constant label, which the targeted attacks explicitly do. Similarly, targeting *only* the logit layer is usually sufficient for high RErr. Interestingly, attacking only the first convolutional layer is quite effective, as well. We also emphasize that we are considering more adversarial

TABLE 10: **Adversarial Bit Error Robustness and ADVBET.** RErr against adversarial bit errors for CLIPPING, RANDBET and ADVBET on MNIST and CIFAR10. We consider the worst-case across multiple random restarts, including targeted and untargeted attacks as well as attacks on all or particularly vulnerable (e.g., logit) layers. While ADVBET improves robustness considerably on MNIST, CLIPPING and RANDBET are very strong baselines on CIFAR10. As we generally consider larger ϵ on CIFAR10, this makes it hard for ADVBET to further improve results.

	Err %	RErr in %			
MNIST		$\epsilon=80$	$\epsilon=160$	$\epsilon=240$	$\epsilon=320$
RQUANT	0.37	91.08	91.08	91.08	91.08
CLIPPING _{0.05}	0.38	85.09	88.81	90.11	90.26
RANDBET _{0.05, p=20}	0.39	10.13	69.90	81.16	81.94
ADVBET _{0.05, $\epsilon=160$}	0.31	11.60	21.43	40.30	80.10
ADVBET _{0.05, $\epsilon=240$}	0.31	11.58	28.34	41.66	71.16
ADVBET _{0.05 T, $\epsilon=240$}	0.36	10.10	19.44	31.23	51.01
CIFAR10		$\epsilon=160$	$\epsilon=320$	$\epsilon=480$	$\epsilon=640$
RQUANT	4.89	91.18	91.18	91.18	91.18
CLIPPING _{0.05}	5.34	20.48	60.76	79.12	83.93
RANDBET _{0.05, p=2}	5.42	14.66	33.86	54.24	80.36
ADVBET _{0.05, $\epsilon=160$}	5.54	15.20	26.22	55.06	77.43

bit errors (i.e., larger ϵ) on CIFAR10, even though CIFAR10 is considerably more difficult. This is due to the increased number of weights (roughly 5.5Mio) on CIFAR10. Fig. 9 also shows that gradient normalization and momentum are essential for the untargeted attack to be successful. This is important as running the targeted attack for each target label during ADVBET is prohibitively expensive. Nevertheless, the attack remains sensitive to, e.g., the learning rate, but $\gamma=1$ works reasonably well across models, given enough random restarts to avoid poor optima. Thus, in our evaluation, we run both targeted and untargeted attacks, attacking all weights, only the first convolutional and/or logit layer and consider the worst-case across a total of 80 random restarts. Overall, our attack provides a much more realistic estimate of adversarial bit error robustness. Furthermore, on CIFAR10, our attack requires only between 0.15 and 0.2 seconds per iteration and runtime is independent of ϵ .

CLIPPING and RANDBET Improve Adversarial Bit Error Robustness: As shown for BFA in Tab. 8, we find that CLIPPING and RANDBET are surprisingly robust against adversarial bit errors. Specifically, Tab. 10 reports RErr on MNIST and CIFAR10. While CLIPPING does not perform well on MNIST, RANDBET reduces RErr against $\epsilon=80$ from 85.09% to 10.13%. On CIFAR10, in contrast, considering larger ϵ , CLIPPING alone is quite effective, with 20.48% RErr against $\epsilon=160$. Nevertheless, RANDBET further improves over CLIPPING. This is counter-intuitive considering, e.g., robustness against adversarial examples where training against *random* perturbations does generally not provide *adversarial robustness*. However, RANDBET is trained against large bit error rates, e.g., $p=2\%$ on CIFAR10, with an expected $\epsilon=8 \cdot W \approx 880k$ bit errors, 110k in the most significant bits (MSBs). For adversarial bit error, in contrast, we consider up to $\epsilon=640$ on CIFAR10. In terms of BFA, complementing the results in Tab. 8, we need on average 2253 bit errors to increase RErr above 90% for RANDBET on CIFAR10. In contrast, [13] report 541 required bit flips (ResNet-20, $W \approx 4.3Mio$) to “break” their proposed bina-

rized DNN, which has been reduced to 35 in [12] using targeted BFA. Overall, these results show that random and adversarial bit error robustness are aligned well, allowing to *secure* low-voltage operation of DNN accelerators.

ADVBET Improves Adversarial Bit Error Robustness: Using ADVBET, we can further boost robustness against adversarial bit errors, cf. Tab. 10. On MNIST, in particular, ADVBET is able to reduce RErr from above 80% for RANDBET or CLIPPING, to 40.30% against up to $\epsilon=240$ adversarial bit errors. As Tab. 9 illustrates, targeted attacks are generally considered stronger. Thus, training with a targeted attack, selecting a random ϵ target label in each iteration, further boosts robustness to 31.23% RErr. However, these improvements do not easily generalize to CIFAR10. We suspect this is due to two reasons: First, we found that training with too large ϵ is difficult (also cf. increased Err in Tab. 10), i.e., ADVBET with larger ϵ does not improve robustness because training becomes too hard. This is why we report results for ADVBET trained on $\epsilon=160$. Second, CLIPPING alone is significantly more robust on CIFAR10 than on MNIST, resulting in a particularly strong baseline. We suspect that architectural differences have a significant impact on how effective CLIPPING is against adversarial bit errors. For example, DNNs on CIFAR10 have inherently more weights in the first convolutional layer (relative to W , due to larger input dimensionality,) which Tab. 9 shows to be particularly vulnerable. Overall, ADVBET can be used to further boost robustness against *adversarial* bit errors, beyond CLIPPING.

6 CONCLUSION

We propose a combination of **robust quantization, weight clipping and random bit error training (RANDBET) or adversarial bit error training (ADVBET)** to train DNNs robust against random and adversarial bit errors in their (quantized) weights. This enables secure low-voltage operation of DNN accelerators. Specifically, we consider robustness against random bit errors induced by operating the accelerator memory far below its rated voltage [5]. We show that quantization details have tremendous impact on robustness, even though we use a very simple fixed-point quantization scheme without any outlier treatment [16], [17], [41]. By encouraging redundancy in the weights, clipping is another simple but effective strategy to improve robustness. In contrast to related work, RANDBET does *not* require expert knowledge or profiling infrastructure [4], [19] and generalizes across chips, with different bit error patterns, and voltages. As a result, we also avoid expensive circuit techniques [3], [5]. Furthermore, complementing existing research, we discuss low-voltage induced random bit errors in inputs and activations. Finally, we propose a novel *adversarial* bit error attack that is more effective and efficient compared to existing attacks [11] and can be utilized for ADVBET. Surprisingly, we find that CLIPPING and RANDBET also improve robustness against adversarial bit errors. However, ADVBET further improves robustness specifically against adversarial bit errors. Altogether, by improving DNN robustness against random and adversarial bit errors, we enable both energy-efficient and secure DNN accelerators.

REFERENCES

- [1] V. Sze, Y. Chen, T. Yang, and J. S. Emer, "Efficient processing of deep neural networks: A tutorial and survey," *IEEE*, vol. 105, no. 12, 2017.
- [2] D. D. Lin, S. S. Talathi, and V. S. Annapureddy, "Fixed point quantization of deep convolutional networks," in *ICML*, 2016.
- [3] B. Reagen, P. N. Whatmough, R. Adolf, S. Rama, H. Lee, S. K. Lee, J. M. Hernández-Lobato, G. Wei, and D. M. Brooks, "Minerva: Enabling low-power, highly-accurate deep neural network accelerators," in *ISCA*, 2016.
- [4] S. Kim, P. Howe, T. Moreau, A. Alaghi, L. Ceze, and V. Sathé, "MATIC: learning around errors for efficient low-voltage neural network accelerators," in *DATE*, 2018.
- [5] N. Chandramoorthy, K. Swaminathan, M. Cochet, A. Paidimarri, S. Eldridge, R. V. Joshi, M. M. Ziegler, A. Buyuktosunoglu, and P. Bose, "Resilient low voltage accelerators for high energy efficiency," in *HPCA*, 2019.
- [6] S. Ganapathy, J. Kalamatianos, K. Kasprak, and S. Raasch, "On characterizing near-threshold SRAM failures in FinFET technology," in *DAC*, 2017.
- [7] Z. Guo, A. Carlson, L. Pang, K. Duong, T. K. Liu, and B. Nikolic, "Large-scale SRAM variability characterization in 45 nm CMOS," *JSSC*, vol. 44, no. 11, 2009.
- [8] A. Tang, S. Sethumadhavan, and S. J. Stolfo, "CLKSCREW: exposing the perils of security-oblivious energy management," in *USENIX*, 2017.
- [9] Y. Kim, R. Daly, J. Kim, C. Fallin, J. Lee, D. Lee, C. Wilkerson, K. Lai, and O. Mutlu, "Flipping bits in memory without accessing them: An experimental study of DRAM disturbance errors," in *ISCA*, 2014.
- [10] K. Murdock, D. Oswald, F. D. Garcia, J. Van Bulck, D. Gruss, and F. Piessens, "Plundervolt: Software-based fault injection attacks against intel sgx," in *SP*, 2020.
- [11] A. S. Rakin, Z. He, and D. Fan, "Bit-flip attack: Crushing neural network with progressive bit search," in *ICCV*, 2019.
- [12] A. S. Rakin, Z. He, J. Li, F. Yao, C. Chakrabarti, and D. Fan, "T-BFA: targeted bit-flip adversarial weight attack," *arXiv.org*, vol. abs/2007.12336, 2020.
- [13] Z. He, A. S. Rakin, J. Li, C. Chakrabarti, and D. Fan, "Defending and harnessing the bit-flip based adversarial weight attack," in *CVPR*, 2020.
- [14] A. Murthy, H. Das, and M. A. Islam, "Robustness of neural networks to parameter quantization," *arXiv.org*, vol. abs/1903.10672, 2019.
- [15] P. Merolla, R. Appuswamy, J. V. Arthur, S. K. Esser, and D. S. Modha, "Deep neural networks are robust to weight binarization and other non-linear distortions," *arXiv.org*, vol. abs/1606.01981, 2016.
- [16] W. Sung, S. Shin, and K. Hwang, "Resiliency of deep neural networks under quantization," *arXiv.org*, vol. abs/1511.06488, 2015.
- [17] B. Zhuang, C. Shen, M. Tan, L. Liu, and I. D. Reid, "Towards effective low-bitwidth convolutional neural networks," in *CVPR*, 2018.
- [18] Y. Chen, J. S. Emer, and V. Sze, "Eyeriss: A spatial architecture for energy-efficient dataflow for convolutional neural networks," in *ISCA*, 2016.
- [19] S. Koppula, L. Orosa, A. G. Yaglikçi, R. Azizi, T. Shahroodi, K. Kanellopoulos, and O. Mutlu, "EDEN: enabling energy-efficient, high-performance deep neural network inference using approximate DRAM," in *MICRO*, 2019, pp. 166–181.
- [20] A. Madry, A. Makelov, L. Schmidt, D. Tsipras, and A. Vladu, "Towards deep learning models resistant to adversarial attacks," *ICLR*, 2018.
- [21] D. Stutz, M. Hein, and B. Schiele, "Confidence-calibrated adversarial training: Generalizing to unseen attacks," in *ICML*, 2020.
- [22] D. Stutz, N. Chandramoorthy, M. Hein, and B. Schiele, "Bit error robustness for energy-efficient dnn accelerators," in *MLSys*, 2021.
- [23] Y. Guo, "A survey on methods and theories of quantized neural networks," *arXiv.org*, vol. abs/1808.04752, 2018.
- [24] S. Shin, Y. Boo, and W. Sung, "Fixed-point optimization of deep neural networks with adaptive step size retraining," in *ICASSP*, 2017.
- [25] H. Li, S. De, Z. Xu, C. Studer, H. Samet, and T. Goldstein, "Training quantized nets: A deeper understanding," in *NeurIPS*, I. Guyon, U. von Luxburg, S. Bengio, H. M. Wallach, R. Fergus, S. V. N. Vishwanathan, and R. Garnett, Eds., 2017.
- [26] B. Jacob, S. Kligys, B. Chen, M. Zhu, M. Tang, A. G. Howard, H. Adam, and D. Kalenichenko, "Quantization and training of neural networks for efficient integer-arithmetic-only inference," in *CVPR*, 2018.
- [27] R. Krishnamoorthi, "Quantizing deep convolutional networks for efficient inference: A whitepaper," *arXiv.org*, vol. abs/1806.08342, 2018.
- [28] A. Goncharenko, A. Denisov, S. Alyamkin, and E. Terentev, "Fast adjustable threshold for uniform neural network quantization," *arXiv.org*, vol. abs/1812.07872, 2018.
- [29] R. Banner, Y. Nahshan, and D. Soudry, "Post training 4-bit quantization of convolutional neural networks for rapid-deployment," in *NeurIPS*, 2019.
- [30] "Nvidia tensorrt," <https://developer.nvidia.com/tensorrt>.
- [31] "Nervana neural network distiller," <https://github.com/nervanasystems/distiller>.
- [32] M. Rastegari, V. Ordonez, J. Redmon, and A. Farhadi, "Xnornet: Imagenet classification using binary convolutional neural networks," in *ECCV*, 2016.
- [33] M. Courbariaux, Y. Bengio, and J. David, "Binaryconnect: Training deep neural networks with binary weights during propagations," in *NeurIPS*, 2015.
- [34] J. Choi, Z. Wang, S. Venkataramani, P. I. Chuang, V. Srinivasan, and K. Gopalakrishnan, "PACT: parameterized clipping activation for quantized neural networks," *arXiv.org*, vol. abs/1805.06085, 2018.
- [35] I. Hubara, M. Courbariaux, D. Soudry, R. El-Yaniv, and Y. Bengio, "Quantized neural networks: Training neural networks with low precision weights and activations," *JMLR*, vol. 18, 2017.
- [36] F. Seide, H. Fu, J. Droppo, G. Li, and D. Yu, "1-bit stochastic gradient descent and its application to data-parallel distributed training of speech dnn," in *INTERSPEECH*, 2014.
- [37] D. Alistarh, J. Li, R. Tomioka, and M. Vojnovic, "QSGD: randomized quantization for communication-optimal stochastic gradient descent," *arXiv.org*, vol. abs/1610.02132, 2016.
- [38] S. Zhou, Z. Ni, X. Zhou, H. Wen, Y. Wu, and Y. Zou, "Dorefa-net: Training low bitwidth convolutional neural networks with low bitwidth gradients," *arXiv.org*, vol. abs/1606.06160, 2016.
- [39] M. Alizadeh, A. Behboodi, M. van Baalen, C. Louizos, T. Blankevoort, and M. Welling, "Gradient ℓ_1 regularization for quantization robustness," in *ICLR*, 2020.
- [40] R. Li, Y. Wang, F. Liang, H. Qin, J. Yan, and R. Fan, "Fully quantized network for object detection," in *CVPR*, 2019.
- [41] E. Park, D. Kim, and S. Yoo, "Energy-efficient neural network accelerator based on outlier-aware low-precision computation," in *ISCA*, 2018.
- [42] S. Ganapathy, J. Kalamatianos, B. M. Beckmann, S. Raasch, and L. G. Szafaryn, "Killi: Runtime fault classification to deploy low voltage caches without MBIST," in *HPCA*, 2019.
- [43] K. K. Chang, A. G. Yaalicki, S. Ghose, A. Agrawal, N. Chatterjee, A. Kashyap, D. Lee, M. O'Connor, H. Hassan, and O. Mutlu, "Understanding reduced-voltage operation in modern DRAM devices: Experimental characterization, analysis, and mechanisms," vol. 1, no. 1, 2017.
- [44] G. Srinivasan, P. Wijesinghe, S. S. Sarwar, A. Jaiswal, and K. Roy, "Significance driven hybrid 8t-6t SRAM for energy-efficient synaptic storage in artificial neural networks," in *DATE*, 2016.
- [45] H. Zhang, Y. Yu, J. Jiao, E. P. Xing, L. E. Ghaoui, and M. I. Jordan, "Theoretically principled trade-off between robustness and accuracy," in *ICML*, 2019.
- [46] D. Wu, S. Xia, and Y. Wang, "Adversarial weight perturbation helps robust generalization," *arXiv.org*, vol. abs/2004.05884, 2020.
- [47] T.-W. Weng, P. Zhao, S. Liu, P.-Y. Chen, X. Lin, and L. Daniel, "Towards certified model robustness against weight perturbations," in *AAAI*, 2020.
- [48] N. Cheney, M. Schrimpf, and G. Kreiman, "On the robustness of convolutional neural networks to internal architecture and weight perturbations," *arXiv.org*, vol. abs/1703.08245, 2017.
- [49] C. Neti, M. H. Schneider, and E. D. Young, "Maximally fault tolerant neural networks," *TNN*, vol. 3, no. 1, pp. 14–23, 1992.
- [50] C. Chiu, K. Mehrotra, C. K. Mohan, and S. Ranka, "Training techniques to obtain fault-tolerant neural networks," in *Annual International Symposium on Fault-Tolerant Computing*, 1994.
- [51] Y. Ji, X. Zhang, S. Ji, X. Luo, and T. Wang, "Model reuse attacks on deep learning systems," in *CCS*, 2018.

- [52] J. Dumford and W. J. Scheirer, "Backdooring convolutional neural networks via targeted weight perturbations," *arXiv.org*, vol. abs/1812.03128, 2018.
- [53] Y. N. Wu, J. S. Emer, and V. Sze, "Accelerogy: An architecture-level energy estimation methodology for accelerator designs," in *ICCAD*, D. Z. Pan, Ed., 2019.
- [54] T. Yang, Y. Chen, J. S. Emer, and V. Sze, "A method to estimate the energy consumption of deep neural networks," in *ACSSC*, 2017.
- [55] Y. Wu and K. He, "Group normalization," in *ECCV*, 2018, pp. 3–19.
- [56] S. Ioffe and C. Szegedy, "Batch normalization: Accelerating deep network training by reducing internal covariate shift," in *ICML*, 2015.
- [57] J. Breier, X. Hou, D. Jap, L. Ma, S. Bhasin, and Y. Liu, "Practical fault attack on deep neural networks," in *CCS*, 2018.
- [58] C. Szegedy, W. Zaremba, I. Sutskever, J. Bruna, D. Erhan, I. J. Goodfellow, and R. Fergus, "Intriguing properties of neural networks," in *ICLR*, 2014.
- [59] F. Croce and M. Hein, "Sparse and imperceivable adversarial attacks," in *ICCV*, 2019.
- [60] Y. Dong, F. Liao, T. Pang, H. Su, J. Zhu, X. Hu, and J. Li, "Boosting adversarial attacks with momentum," in *CVPR*, 2018.
- [61] M. D. McDonnell, "Training wide residual networks for deployment using a single bit for each weight," in *ICLR*, 2018.
- [62] A. Paszke, S. Gross, S. Chintala, G. Chanan, E. Yang, Z. DeVito, Z. Lin, A. Desmaison, L. Antiga, and A. Lerer, "Automatic differentiation in pytorch," in *NeurIPS Workshops*, 2017.
- [63] Y. LeCun, L. Bottou, Y. Bengio, and P. Haffner, "Gradient-based learning applied to document recognition," *Proc. of the IEEE*, vol. 86, no. 11, pp. 2278–2324, 1998.
- [64] A. Krizhevsky, "Learning multiple layers of features from tiny images," Tech. Rep., 2009.
- [65] S. H. HasanPour, M. Rouhani, M. Fayyaz, and M. Sabokrou, "Lets keep it simple, using simple architectures to outperform deeper and more complex architectures," *arXiv.org*, vol. abs/1608.06037, 2016.
- [66] K. He, X. Zhang, S. Ren, and J. Sun, "Deep residual learning for image recognition," in *CVPR*, 2016.
- [67] S. Zagoruyko and N. Komodakis, "Wide residual networks," in *BMVC*, 2016.
- [68] E. D. Cubuk, B. Zoph, D. Mané, V. Vasudevan, and Q. V. Le, "Autoaugment: Learning augmentation policies from data," *arXiv.org*, vol. abs/1805.09501, 2018.
- [69] T. Devries and G. W. Taylor, "Improved regularization of convolutional neural networks with cutout," *arXiv.org*, vol. abs/1708.04552, 2017.
- [70] C. Szegedy, V. Vanhoucke, S. Ioffe, J. Shlens, and Z. Wojna, "Rethinking the inception architecture for computer vision," in *CVPR*, 2016.
- [71] D. H. Park, C. M. Ho, Y. Chang, and H. Zhang, "Gradient-coherent strong regularization for deep neural networks," *arXiv.org*, vol. abs/1811.08056, 2018.
- [72] T. Chen, Z. Du, N. Sun, J. Wang, C. Wu, Y. Chen, and O. Temam, "Diannao: a small-footprint high-throughput accelerator for ubiquitous machine-learning," 2014.
- [73] "NVIDIA Deep Learning Accelerator," <http://nvidia.org/>.
- [74] Z. Du, R. Fasthuber, T. Chen, P. lenne, L. Li, T. Luo, X. Feng, Y. Chen, and O. Temam, "Shidiannao: shifting vision processing closer to the sensor," in *ISCA*, 2015.
- [75] H. Sharma, J. Park, N. Suda, L. Lai, B. Chau, J. K. Kim, V. Chandra, and H. Esmaeilzadeh, "Bit fusion: Bit-level dynamically composable architecture for accelerating deep neural networks," in *ISCA*, 2018.
- [76] B. Biggio and F. Roli, "Wild patterns: Ten years after the rise of adversarial machine learning," *arXiv.org*, vol. abs/1712.03141, 2018.
- [77] H. Xu, Y. Ma, H. Liu, D. Deb, H. Liu, J. Tang, and A. K. Jain, "Adversarial attacks and defenses in images, graphs and text: A review," *arXiv.org*, vol. abs/1909.08072, 2019.
- [78] C. Szegedy, W. Zaremba, I. Sutskever, J. Bruna, D. Erhan, I. Goodfellow, and R. Fergus, "Intriguing properties of neural networks," *arXiv.org*, vol. abs/1312.6199, 2013.
- [79] N. Carlini and D. Wagner, "Towards evaluating the robustness of neural networks," in *SP*, 2017.
- [80] Y. Dong, F. Liao, T. Pang, X. Hu, and J. Zhu, "Boosting adversarial attacks with momentum," *arXiv.org*, vol. abs/1710.06081, 2017.
- [81] P. Chiang, J. Geiping, M. Goldblum, T. Goldstein, R. Ni, S. Reich, and A. Shafahi, "Witchcraft: Efficient PGD attacks with random step size," *arXiv.org*, vol. abs/1911.07989, 2019.
- [82] F. Croce and M. Hein, "Reliable evaluation of adversarial robustness with an ensemble of diverse parameter-free attacks," *arXiv.org*, vol. abs/2003.01690, 2020.
- [83] P.-Y. Chen, H. Zhang, Y. Sharma, J. Yi, and C.-J. Hsieh, "ZOO: Zeroth order optimization based black-box attacks to deep neural networks without training substitute models," in *AISec*, 2017.
- [84] A. Ilyas, L. Engstrom, A. Athalye, and J. Lin, "Black-box adversarial attacks with limited queries and information," in *ICML*, 2018.
- [85] F. Croce and M. Hein, "Sparse and imperceivable adversarial attacks," *arXiv.org*, vol. abs/1909.05040, 2019.
- [86] M. Andriushchenko, F. Croce, N. Flammarion, and M. Hein, "Square attack: a query-efficient black-box adversarial attack via random search," *arXiv.org*, vol. abs/1912.00049, 2019.
- [87] Y. Liu, X. Chen, C. Liu, and D. Song, "Delving into transferable adversarial examples and black-box attacks," *arXiv.org*, vol. abs/1611.02770, 2016.
- [88] J. Lu, H. Sibai, E. Fabry, and D. Forsyth, "No need to worry about adversarial examples in object detection in autonomous vehicles," *arXiv.org*, vol. abs/1707.03501, 2017.
- [89] A. Kurakin, I. Goodfellow, and S. Bengio, "Adversarial examples in the physical world," *arXiv.org*, vol. abs/1607.02533, 2016.
- [90] J. Peck, J. Roels, B. Goossens, and Y. Saeys, "Lower bounds on the robustness to adversarial perturbations," in *NeurIPS*, 2017.
- [91] H. Zhang, T. Weng, P. Chen, C. Hsieh, and L. Daniel, "Efficient neural network robustness certification with general activation functions," in *NeurIPS*, 2018, pp. 4944–4953.
- [92] E. Wong and J. Z. Kolter, "Provable defenses against adversarial examples via the convex outer adversarial polytope," in *ICML*, 2018.
- [93] T. Miyato, S.-i. Maeda, M. Koyama, K. Nakae, and S. Ishii, "Distributional smoothing with virtual adversarial training," *arXiv.org*, vol. abs/1507.00677, 2015.
- [94] R. Huang, B. Xu, D. Schuurmans, and C. Szepesvári, "Learning with a strong adversary," *arXiv.org*, vol. abs/1511.03034, 2015.
- [95] D. Stutz, M. Hein, and B. Schiele, "Disentangling adversarial robustness and generalization," *CVPR*, 2019.
- [96] D. Tsipras, S. Santurkar, L. Engstrom, A. Turner, and A. Madry, "Robustness may be at odds with accuracy," *arXiv.org*, vol. abs/1805.12152, 2018.
- [97] Y. Carmon, A. Raghunathan, L. Schmidt, P. Liang, and J. C. Duchi, "Unlabeled data improves adversarial robustness," *arXiv.org*, vol. abs/1905.13736, 2019.
- [98] J. Uesato, J. Alayrac, P. Huang, R. Stanforth, A. Fawzi, and P. Kohli, "Are labels required for improving adversarial robustness?" *arXiv.org*, vol. abs/1905.13725, 2019.
- [99] F. Tramèr and D. Boneh, "Adversarial training and robustness for multiple perturbations," *arXiv.org*, vol. abs/1904.13000, 2019.
- [100] P. Maini, E. Wong, and J. Z. Kolter, "Adversarial robustness against the union of multiple perturbation models," *arXiv.org*, vol. abs/1909.04068, 2019.
- [101] E. B. Khalil, A. Gupta, and B. Dilkina, "Combinatorial attacks on binarized neural networks," in *ICLR*, 2019.
- [102] N. Mu and J. Gilmer, "Mnist-c: A robustness benchmark for computer vision," *ICML Workshops*, 2019.
- [103] D. Hendrycks and T. G. Dietterich, "Benchmarking neural network robustness to common corruptions and perturbations," *arXiv.org*, vol. abs/1903.12261, 2019.
- [104] R. G. Lopes, D. Yin, B. Poole, J. Gilmer, and E. D. Cubuk, "Improving robustness without sacrificing accuracy with patch gaussian augmentation," in *ICML Workshops*, 2019.
- [105] D. Kang, Y. Sun, D. Hendrycks, T. Brown, and J. Steinhardt, "Testing robustness against unforeseen adversaries," *arXiv.org*, vol. abs/1908.08016, 2019.
- [106] C. Alippi, V. Piuri, and M. Sami, "Sensitivity to errors in artificial neural networks: a behavioral approach," *ISCAS*, vol. 6, 1994.
- [107] D. Deodhare, M. Vidyasagar, and S. S. Keerthi, "Synthesis of fault-tolerant feedforward neural networks using minimax optimization," *TNN*, vol. 9, no. 5, pp. 891–900, 1998.
- [108] M. Lee, K. Hwang, and W. Sung, "Fault tolerance analysis of digital feed-forward deep neural networks," *ICASSP*, 2014.
- [109] J. Marques, J. Andrade, and G. Fernandes, "Unreliable memory operation on a convolutional neural network processor," *IEEE International Workshop on Signal Processing Systems (SiPS)*, 2017.

- [110] F. U. Rahman, B. Vasu, and A. E. Savakis, "Resilience and self-healing of deep convolutional object detectors," in *ICIP*, 2018.
- [111] P. Dey, K. Nag, T. Pal, and N. Pal, "Regularizing multilayer perceptron for robustness," *IEEE Transactions on Systems, Man, and Cybernetics: Systems*, vol. 48, 2018.
- [112] A. Leung, H. Wang, and J. Sum, "On the selection of weight decay parameter for faulty networks," *TNN*, vol. 21, 2010.
- [113] L. Xia, M. Liu, X. Ning, K. Chakrabarty, and Y. Wang, "Fault-tolerant training with on-line fault detection for rram-based neural computing systems," *DAC*, 2017.
- [114] V. Duddu, D. V. Rao, and V. E. Balas, "Adversarial fault tolerant training for deep neural networks," *arXiv.org*, vol. abs/1907.03103, 2019.
- [115] A. Azizi, Mazreah, Y. Gu, X. Gu, and L. Chen, "Tolerating soft errors in deep learning accelerators with reliable on-chip memory designs," *NAS*, 2018.
- [116] J. Deng, Y. Fang, Z. Du, Y. Wang, H. Li, O. Temam, P. Ienne, D. Novo, X. Li, Y. Chen, and C. Wu, "Retraining-based timing error mitigation for hardware neural networks," in *DATE*, 2015.
- [117] B. Salami, O. Unsal, and A. Cristal, "On the resilience of rtl nn accelerators: Fault characterization and mitigation," *International Symposium on Computer Architecture and High Performance Computing (SBAC-PAD)*, 2018.
- [118] Z. Du, K. Palem, L. Avinash, O. Temam, Y. Chen, and C. Wu, "Leveraging the error resilience of machine-learning applications for designing highly energy efficient accelerators," *Asia and South Pacific Design Automation Conference (ASP-DAC)*, 2014.
- [119] S. Cavalieri and O. Mirabella, "A novel learning algorithm which improves the partial fault tolerance of multilayer neural networks," *Neural networks: the official journal of the International Neural Network Society*, vol. 12 1, 1999.
- [120] M. Klachko, M. R. Mahmoodi, and D. B. Strukov, "Improving noise tolerance of mixed-signal neural networks," in *IJCNN*, 2019.
- [121] L.-H. Hoang, M. Hanif, and M. Shafique, "Ft-clipact: Resilience analysis of deep neural networks and improving their fault tolerance using clipped activation," *DATE*, 2020.
- [122] V. Duddu, N. R. Pillai, D. V. Rao, and V. E. Balas, "Fault tolerance of neural networks in adversarial settings," *arXiv.org*, vol. abs/1910.13875, 2019.
- [123] C. Torres-Huitzil and B. Girau, "Fault and error tolerance in neural networks: A review," *IEEE Access*, vol. 5, 2017.
- [124] Y. Liu, S. Ma, Y. Aafer, W. Lee, J. Zhai, W. Wang, and X. Zhang, "Trojaning attack on neural networks," in *NDSS*, 2018.
- [125] C. Liao, H. Zhong, A. C. Squicciarini, S. Zhu, and D. J. Miller, "Backdoor embedding in convolutional neural network models via invisible perturbation," *arXiv.org*, vol. abs/1808.10307, 2018.
- [126] J. Zhang, Z. Gu, J. Jang, H. Wu, M. P. Stoecklin, H. Huang, and I. Molloy, "Protecting intellectual property of deep neural networks with watermarking," in *AsiaCCS*, 2018.
- [127] "Cupy: A numpy-compatible array library accelerated by cuda," <https://cupy.dev/>.
- [128] "C foreign function interface for python," <https://cffi.readthedocs.io/en/latest/index.html>.
- [129] K. Simonyan and A. Zisserman, "Very deep convolutional networks for large-scale image recognition," in *ICLR*, 2015.
- [130] K. He, X. Zhang, S. Ren, and J. Sun, "Delving deep into rectifiers: Surpassing human-level performance on imagenet classification," in *ICCV*, 2015.
- [131] A. Galloway, A. Golubeva, T. Tanay, M. Moussa, and G. W. Taylor, "Batch normalization is a cause of adversarial vulnerability," *arXiv.org*, vol. abs/1905.02161, 2019.
- [132] D. Zhang, J. Yang, D. Ye, and G. Hua, "Lq-nets: Learned quantization for highly accurate and compact deep neural networks," in *ECCV*, 2018.
- [133] Y. Zhou, S. Moosavi-Dezfooli, N. Cheung, and P. Frossard, "Adaptive quantization for deep neural network," in *AAAI*, S. A. McIlraith and K. Q. Weinberger, Eds., 2018.
- [134] E. Park, S. Yoo, and P. Vajda, "Value-aware quantization for training and inference of neural networks," in *ECCV*, V. Ferrari, M. Hebert, C. Sminchisescu, and Y. Weiss, Eds., 2018.
- [135] M. Nagel, M. van Baalen, T. Blankevoort, and M. Welling, "Data-free quantization through weight equalization and bias correction," in *ICCV*, 2019.
- [136] L. Dinh, R. Pascanu, S. Bengio, and Y. Bengio, "Sharp minima can generalize for deep nets," in *ICML*, 2017.

A OVERVIEW

IN the main paper, we consider low-voltage operation of deep neural network (DNN) accelerators. This allows to reduce energy consumption significantly, while causing bit errors in the memory storing the (quantized) DNN weights. We show that robust fixed-point quantization (RQUANT), weight clipping (CLIPPING) and random bit error training (RANDBET) improve robustness to the induced *random* bit errors significantly, even for low-precision quantization. In contrast to related work, our approach generalizes across accelerators and operating voltages. Furthermore, this improves security of DNN accelerators against attacks on voltage controllers. Furthermore, we consider DNN robustness against *adversarial* bit errors which have recently been shown to degrade accuracy significantly. To this end, we propose to combine CLIPPING with adversarial bit error training (ADVBET) to achieve robustness against both targeted and untargeted bit-level attacks. In this supplementary material, we provide complementary experimental results and discussion corresponding to the experiments presented in the main paper.

A.1 Outline

This supplementary material is organized as follows:

- Sec. B: additional **details on Fig. 1** from the main paper (corresponding to Fig. A).
- Sec. C: discussion of **related work** considering adversarial and corruption robustness, backdooring and fault tolerance.
- Sec. D: background for our **random bit error models** from the hardware perspective, including details on the profiled bit errors in Sec. D.1 (Fig. B) and a simple probabilistic bound on DNN performance under random bit errors in Sec. D.2.
- Sec. E details on our **adversarial bit error attack**.
- Sec. F: implementation details for quantization and **bit manipulation in PyTorch** [71].
- Sec. G: how to use **weight clipping with group/batch normalization**.
- Sec. H: further details on our **experimental setup** (Tab. A, B).
- Sec. I: complementary **experiments** as outlined below.
 - Sec. I.1: a discussion of bit error robustness and batch normalization (Tab. C).
 - Sec. I.2: ablation for our robust fixed-point quantization (RQUANT, Tab. D).
 - Sec. I.3: details and ablation for weight clipping (CLIPPING, Fig. C and D, Tab. E and F).
 - Sec. I.4: ablation for random bit error training (RANDBET, Tab. G, H, I).
 - Sec. I.5: ablation and details for per-layer clipping (PLCLIPPING, Fig. E and Tab. J).
 - Sec. I.6: additional results on profiled bit errors (Tab. K and L).
 - Sec. I.7: computation of the guarantees from Sec. D.2, Prop. 1 (Tab. M).
 - Sec. I.8: summary results for all datasets and precisions individually (Fig. F).

Bit Error Rate/Normalized Energy vs. Voltage




Fig. A: **Energy and Low-Voltage Operation.** Average bit error rate p (blue, left y-axis) from 32 14nm SRAM arrays of size 512×64 from [5] and energy (red, right y-axis) vs. voltage (x-axis). Voltage is normalized by V_{min} , the minimal measured voltage for error-free operation, as well as the energy per SRAM access at V_{min} . SRAM accesses have significant impact on the DNN accelerator’s energy [18]. Reducing voltage leads to exponentially increasing bit error rates.

- Sec. I.9: additional results and discussion of bit errors in activations and inputs (Tab. N and O).
- Sec. I.10: more results for adversarial bit errors and adversarial bit error training (ADVBET, Fig. G and Tab. P, Q, R).
- Tab. S, T, U, V, W, X: more results on MNIST, CIFAR10 and CIFAR100 in tabular form corresponding to Fig. 7 in the main paper.

B ENERGY SAVINGS IN FIG. A

Fig. A shows bit error rate characterization results of SRAMs in the DNN accelerator chip described in [5], fabricated using 14nm FinFET technology. The average bit error rate is measured from 32 SRAMs, each SRAM array of size 4KB (512×64 bit), as supply voltage is scaled down. *Bit error rate* p (in %) at a given supply voltage is measured as the count of read or write bit cell failures averaged over the total number of bit cells in the SRAM. A bit cell failure refers to reading 1 on writing 0 or reading 0 on writing 1. For a more comprehensive characterization of SRAMs in 14nm technology, the reader is referred to [6]. Fig. A also shows the energy per write and read access of a 4KB (512×64 bit) SRAM, obtained from Cadence Spectre simulations. Energy is obtained at the same constant clock frequency at all supply voltages. The voltage (x-axis) shown is normalized over V_{min} which is the lowest measured voltage at which there are no bit cell failures. Energy shown in the graph (secondary axis on the right) is also normalized over the energy per access at V_{min} .

Accelerators such as [3], [5], [18], [72], [73], [74], [75] have a large amount of on-chip SRAM to store weights and intermediate computations. Total dynamic energy of accelerator SRAMs can be obtained as the total number of SRAM accesses times the energy of a single SRAM access. Optimized dataflow in accelerators leads to better re-use of weights read from memories in computation, reducing




Fig. B: **Low-Voltage Induced Bit Errors on Profiled Chips.** We break the the bit error distribution of chips 1 and 2 down into 1-to-0 and 0-to-1 bit flips. Additionally, we show that most of the bit errors are actually persistent and, thus, not subject to randomness. As before, we show a sub-array of size 64×128 from all profiled bit cells (i.e., across all SRAM arrays). Sec. B includes details on profiling.

the number of such memory accesses [18], [72], [73]. Low voltage operation focuses on reducing the memory access energy, leading to significant energy savings as shown.

C RELATED WORK

In the following, we briefly review work on adversarial robustness, fault tolerance and backdooring. These areas are broadly related to the topic of the main paper.

Adversarial and Corruption Robustness: Robustness of DNNs against adversarially perturbed or randomly corrupted inputs received considerable attention in recent years, see, e.g., relevant surveys [76], [77]. Adversarial examples [78], i.e., nearly imperceptibly perturbed inputs causing misclassification, consider an adversarial environment where potential attackers can actively manipulate inputs. This has been shown to be possible in the white-box setting, with full access to the DNN, e.g., [20], [79], [80], [81], [82], as well as in the black-box setting, without access to DNN weights and gradients, e.g., [83], [84], [85], [86]. Such attacks are also transferable between models [87] and can be applied in the physical world [88], [89]. Obtaining robustness against adversarial inputs is challenging, recent work focuses on achieving certified/provable robustness [90], [91], [92] and variants of adversarial training [20], [93], [94], i.e., training on adversarial inputs generated on-the-fly. Adversarial training has been shown to work well empirically, and flaws such as reduced accuracy [95], [96] or generalization to attacks not seen during training has been addressed repeatedly [21], [97], [98], [99], [100]. Adversarial inputs have also been considered for quantized DNNs [101]. Corrupted inputs, in contrast, consider “naturally” occurring corruptions to which robustness/invariance is desirable for practical applications. Popular benchmarks such as MNIST-C [102], Cifar10-C or ImageNet-C [103] promote research on corruption robustness by extending standard datasets with common corruptions, e.g., blur, noise, saturation changes etc. It is argued that adversarial robustness, and robustness to random corruptions is related. Approaches are often similar, e.g., based on adversarial training [21], [104], [105].

In contrast, we mainly consider random bit errors in the weights, not the inputs.

Fault Tolerance: Fault tolerance, describes structural changes such as removed units, and has been studied in early works such as [49], [50], [106]. These approaches obtain fault tolerant NNs using approaches similar to adversarial training [107], [108]. Recently, hardware mitigation strategies [109], weight regularization [110], [111], [112], fault detection [113] or GAN-based training [114] has been explored. Generally, a wide range of different faults/errors are considered, including node faults [107], [108], hardware soft errors [115], timing errors [116] or transient errors in general [117]. However, to the best of our knowledge, large rates of non-transient bit errors provoked through low-voltage operation has not been considered. Nevertheless, some of these approaches are related to ours in spirit: [118] consider inexact computation for energy-efficiency and [119], [120], [121] constrain weights and/or activations to limit the impact of various errors – similar to our weight clipping. Additionally, fault tolerance of adversarially robust models has been considered in [122]. We refer to [123] for a comprehensive survey. In contrast, we do *not* consider structural changes/errors in DNNs.

Backdooring: The goal of backdooring is to introduce a backdoor into a DNN, allowing to control the classification result by fixed input perturbations at test time. This is usually achieved through data poisoning [124], [125], [126]. However, some works also consider directly manipulating the weights [51], [52]. However, such weight perturbations are explicitly constructed not to affect accuracy on test examples without backdoor. In contrast, we consider random bit errors (i.e., weight perturbations) that degrade accuracy significantly.

D LOW-VOLTAGE INDUCED RANDOM BIT ERRORS IN QUANTIZED DNN WEIGHTS

We provide a more detailed discussion of the considered error model: random bit errors, induced through low-voltage operation of SRAM or DRAM commonly used on DNN

TABLE A: **Architectures, Number of Weights W , Expected Number of Bit Errors.** *Left and Middle:* SimpleNet architectures used for MNIST and CIFAR10 with the corresponding output sizes, channels N_C , height N_H and width N_W , and the total number of weights W . We use group normalization *with* learnable scale/bias, but reparameterized as outlined in App. G. *Right:* The number of expected bit errors for random bit errors, i.e., pmW . With * we mark “blocks” of convolutional, normalization and ReLU layer after which we inject bit errors in activations for the experiments in Sec. I.9.

SimpleNet on MNIST		SimpleNet on CIFAR10		p on MNIST	
Layer	Output Size N_C, N_H, N_W	Layer	Output Size N_C, N_H, N_W	p in %	$pmW, m = 8$
Conv+GN+ReLU*	32, 28, 28	Conv+GN+ReLU*	64, 32, 32	Random Bit Errors	
Conv+GN+ReLU*	64, 28, 28	Conv+GN+ReLU*	128, 32, 32	10	866260
Conv+GN+ReLU*	64, 28, 28	Conv+GN+ReLU*	128, 32, 32	5	433130
Conv+GN+ReLU*	64, 28, 28	Conv+GN+ReLU*	128, 32, 32	1.5	129939
Pool	64, 14, 14	Conv+GN+ReLU*	128, 32, 32	1	86626
Conv+GN+ReLU*	64, 14, 14	Pool	128, 16, 16	0.5	43313
Conv+GN+ReLU*	64, 14, 14	Conv+GN+ReLU*	128, 16, 16	p on CIFAR	
Conv+GN+ReLU*	64, 14, 14	Conv+GN+ReLU*	128, 16, 16	p in %	$pmW, m = 8$
Conv+GN+ReLU*	128, 14, 14	Conv+GN+ReLU*	256, 16, 16	Random Bit Errors	
Pool	128, 7, 7	Pool	256, 8, 8	1	439870
Conv+GN+ReLU*	256, 7, 7	Conv+GN+ReLU*	256, 8, 8	0.5	219935
Conv+GN+ReLU*	1024, 7, 7	Conv+GN+ReLU*	256, 8, 8	0.01	43987
Conv+GN+ReLU*	128, 7, 7	Pool	256, 4, 4		
Pool	128, 3, 3	Conv+GN+ReLU*	512, 4, 4		
Conv+GN+ReLU*	128, 3, 3	Pool	512, 2, 2		
Pool	128, 1, 1	Conv+GN+ReLU*	2048, 2, 2		
FC	10	Conv+GN+ReLU*	256, 2, 2		
W	1,082,826	Pool	256, 1, 1		
		Conv+GN+ReLU*	256, 1, 1		
		Pool	256, 1, 1		
		FC	10		
		W	5,498,378		

accelerators [4], [19]. Work such as [5], [19] model the effect of low-voltage induced bit errors using two parameters: the probability p_{flt} of bit cells in accelerator memory, being faulty and the probability p_{err} that a faulty bit cell results in a bit error on access. Following measurements in works such as [4], [42], we assume that these errors are *not* transient errors by setting $p_{\text{err}} = 100\%$ such that the overall probability of bit errors is $p := p_{\text{flt}} \cdot p_{\text{err}} = p_{\text{flt}}$. In doing so, we consider the worst-case where faulty bit cells *always* induce bit errors. However, the noise model from the main paper remains valid for any arbitrary but fixed $p_{\text{err}} \neq 100\%$. For the remainder of this document, we assume the probability of bit error $p = p_{\text{flt}}$, with $p_{\text{err}} = 100\%$, as in the main paper. In the following, we describe the two parameters, p_{flt} and p_{err} , in more details.

Faulty Bit Cells. Due to variations in the fabrication process, SRAM bit cells become more or less vulnerable to low-voltage operation. For a specific voltage, the resulting bit cell failures can be assumed to be random and independent of each other. We assume a bit to be faulty with probability p_{flt} increasing exponentially with decreased voltage [4], [5], [6], [42]. Furthermore, the faulty bits for $p'_{\text{flt}} \leq p_{\text{flt}}$ can be assumed to be a subset of those for p_{flt} . For a fixed chip, consisting of multiple memory arrays, the pattern (spatial distribution) of faulty cells is fixed for a specific supply voltage. Across chips/memory arrays, however, faulty cells are assumed to be random and independent of each other.

Bit Errors in Faulty Bit Cells: Faulty cells may cause bit errors with probability p_{err} upon read/write access. We note that bit errors read from memory affect *all* computations performed on the read weight value. We assume that a bit error flips the currently stored bit, where flips 0-to-1 and 1-to-0 are assumed equally likely.

D.1 Profiled Bit Errors

Fig. B splits the bit error distributions of Fig. 3 in the main paper into a 0-to-1 flip and a 1-to-0 bit flip map. The obtained maps, $p_{1\to0}$ and $p_{0\to1}$, contain per-bit flip probabilities for 1-to-0 and 0-to-1 bit flips. In this particular profiled chip, Fig. B (bottom), 0-to-1 flips are more likely. Similarly, Fig. B (right) shows that most 0-to-1 flips are actually persistent across time i.e., not random transient errors. The following table summarizing the key statistics of the profiled chips: the overall bit error rate p , the rate of 1-to-0 and 0-to-1 flips $p_{1\to0}$ and $p_{0\to1}$, and the rate of persistent errors p_{sa} , all in %:

Chip	p	$p_{0\to1}$	$p_{1\to0}$	p_{sa}
1	2.744	1.27	1.47	1.223
	0.866	0.38	0.49	0.393
2	4.707	3.443	1.091	0.627
	1.01	0.82	0.19	0.105
3	0.136	0.115	0.021	0.01
	2.297	1.81	0.48	0.204
	0.597	0.496	0.0995	0.206

For evaluation, we assume that the DNN weights are mapped linearly onto the memory of these chips. The bit error maps are of size 8192×128 bits for chips 2 and 3 and 2048×128 bits for chip 1. Furthermore, to simulate various different mappings, we repeat this procedure with various offsets and compute average RErr across all mappings. For results, we refer to App. I.6.

D.2 Bounding Generalization to Random Bit Errors

Let w denote the final weights of a trained DNN f . We test f using n i.i.d. test examples, i.e., $(x_i, y_i)_{i=1}^n$. We denote by w' the weights where each bit of w is flipped with probability p uniformly at random, corresponding to the error model

TABLE B: **Quantization-Aware Training Accuracies.** Clean Err for $m = 8$ bits or lower using our robust fixed-point quantization. We obtain competitive performance for $m = 8$ and $m = 4$ bits. On CIFAR100, a Wide ResNet (WRN) clearly outperforms our standard SimpleNet model. Batch normalization (BN), improving Err slightly on CIFAR10, is significantly less robust than group normalization (GN), cf. Tab. C. * For $m \leq 4$, we report results with weight clipping, CLIPPING_{0.1}.

CIFAR10 SimpleNet+GN		CIFAR10 Arch. Comparison		
Quant. m	Err in %	Model	no Quant.	$m = 8$
-	4.34	SimpleNet+GN	4.34	4.32
8	4.32	SimpleBet+BN	4.04	3.83
4*	5.29	ResNet-50+GN	5.88	6.81
3*	5.71	ResNet-50+BN	3.91	3.67

MNIST		CIFAR100	
Quant. m	Err in %	Quant. m , Model	Err in %
4	0.4	8, SimpleNet	23.68
2*	0.47	8, WRN	18.53

from the main paper. The expected *clean* error of f is given by

$$\mathbb{E}[\mathbb{1}_{f(x;w) \neq y}] = P(f(x;w) \neq y).$$

The expected *robust* error (regarding i.i.d. test examples drawn from the data distribution) with random bit errors in the (quantized) weights is

$$\mathbb{E}[\mathbb{1}_{f(x;w') \neq y}] = P(f(x;w') \neq y).$$

Here, the weights of the neural network are themselves random variables. Therefore, with x, y, w , and w' we denote the random variables corresponding to test example, test label, weights and weights bit random bit errors. With x_j, y_j, w_i and w'_i we denote actual examples. Then, the following proposition derives a simple, probabilistic bound on the deviation of expected robust error from the empirically measured one (i.e., RErr in our experiments):

Proposition 1. *Let $w'_i, i = 1, \dots, l$ be l examples of weights bit random bit errors (each bit flipped with probability p). Then it holds*

$$\begin{aligned} P\left(\frac{1}{nl} \sum_{j=1}^n \sum_{i=1}^l \mathbb{1}_{f(x_j;w'_i) \neq y_j} - P(f(x;w') \neq y) \geq \epsilon\right) \\ \leq (n+1)e^{-n\epsilon^2 / (\sqrt{l} + \sqrt{n})^2}. \end{aligned}$$

As alternative formulation, with probability $1 - \delta$ it holds

$$\begin{aligned} P(f(x;w'_i) \neq y) &< \frac{1}{nl} \sum_{j=1}^n \sum_{i=1}^l \mathbb{1}_{f(x_j;w'_i) \neq y_j} \\ &+ \leq \sqrt{\frac{\log\left(\frac{n+1}{\delta}\right)}{n}} \frac{\sqrt{l} + \sqrt{n}}{\sqrt{l}}. \end{aligned}$$

TABLE C: **Batch Normalization not Robust.** RErr with group normalization (GN) or batch normalization (BN). RErr increases when using BN even though clean Err improves slightly compared GN. However, using batch statistics at test time (i.e., “training mode” in PyTorch) improves RErr significantly indicating that the statistics accumulated throughout training do not account for random bit errors. We use **group normalization as default**.

CIFAR10 ($m = 8$ bit): robustness of BN				
		Err	RErr in %	
		in %	$p=0.1$	$p=0.5$
GN	NORMAL	4.32	5.54	11.28
	CLIPPING _{0.1}	4.82	5.58	6.95
BN w/ Accumulated Statistics				
BN	NORMAL	3.83	6.36	52.52
	CLIPPING _{0.1}	4.46	5.32	8.25
BN w/ Batch Statistics at Test Time				
BN	NORMAL	3.83	6.65	9.63
	CLIPPING _{0.1}	4.46	6.57	7.29

Proof. Let $0 < \alpha < 1$. Using the Hoeffding inequality and union bound, we have:

$$\begin{aligned} &P\left(\max_{j=1, \dots, n} \frac{1}{l} \sum_{i=1}^l \mathbb{1}_{f(x_j;w'_i) \neq y_j} - \mathbb{E}_{w'}[\mathbb{1}_{f(x_j;w') \neq y_j}] > \alpha\epsilon\right) \\ &= P\left(\bigcup_{j=1, \dots, n} \left\{\frac{1}{l} \sum_{i=1}^l \mathbb{1}_{f(x_j;w'_i) \neq y_j} - \mathbb{E}_{w'}[\mathbb{1}_{f(x_j;w') \neq y_j}] > \alpha\epsilon\right\}\right) \\ &\leq n e^{-l\alpha^2\epsilon^2}. \end{aligned}$$

Then, again by Hoeffding’s inequality, it holds:

$$\begin{aligned} &P\left(\frac{1}{n} \sum_{j=1}^n \mathbb{E}_{w'}[\mathbb{1}_{f(x_j;w') \neq y_j}] - \mathbb{E}_{x,y}[\mathbb{E}_{w'}[\mathbb{1}_{f(x;w') \neq y}]] > (1-\alpha)\epsilon\right) \\ &\leq e^{-n\epsilon^2(1-\alpha)^2}. \end{aligned}$$

Thus, using

$$a + b > \epsilon \implies \{a > \alpha\epsilon\} \cup \{b > (1-\alpha)\epsilon\}$$

gives us:

$$\begin{aligned} &P\left(\frac{1}{nl} \sum_{j=1}^n \sum_{i=1}^l \mathbb{1}_{f(x_j;w'_i) \neq y_j} - P(f(x;w') \neq y) \geq \epsilon\right) \\ &= P\left(\frac{1}{n} \sum_{j=1}^n \left(\frac{1}{l} \sum_{i=1}^l \mathbb{1}_{f(x_j;w'_i) \neq y_j} - \mathbb{E}_{w'}[\mathbb{1}_{f(x_j;w') \neq y_j}]\right) \right. \\ &\quad \left. + \frac{1}{n} \sum_{j=1}^n \mathbb{E}_{w'}[\mathbb{1}_{f(x_j;w') \neq y_j}] - P(f(x;w') \neq y) \geq \epsilon\right) \\ &\leq P\left(\frac{1}{n} \sum_{j=1}^n \left(\frac{1}{l} \sum_{i=1}^l \mathbb{1}_{f(x_j;w'_i) \neq y_j} - \mathbb{E}_{w'}[\mathbb{1}_{f(x_j;w') \neq y_j}]\right) > \alpha\epsilon\right) \\ &\quad + P\left(\frac{1}{n} \sum_{j=1}^n \mathbb{E}_{w'}[\mathbb{1}_{f(x_j;w') \neq y_j}] - P(f(x;w') \neq y) \geq (1-\alpha)\epsilon\right) \\ &\leq n e^{-l\alpha^2\epsilon^2} + e^{-n\epsilon^2(1-\alpha)^2} \end{aligned}$$

Having both exponential terms have the same exponent yields $\alpha = \frac{\sqrt{n}}{\sqrt{l} + \sqrt{n}}$ and we get the upper bound of the proposition. \square

Remarks: The samples of bit error injected weights $\{w'_i\}_{i=1}^l$ can actually be different for any test example (x_j, y_j) , even though this is not the case in our evaluation. Thus, the above bound involves a stronger result: for any

TABLE D: **Impact of Quantization Scheme on Robustness.** We report Err and RErr for various bit error rates p for the quantization scheme in Eq. (13) with global, per-layer and asymmetric quantization, $m = 8$ bits. Instead of quantizing into signed integer, using unsigned integers works better for asymmetric quantization. Furthermore, proper rounding instead of integer conversion also improves robustness. Note that influence on clean Err is negligible, i.e., the DNN can “learn around” these difference in quantization-aware training. Especially for $m = 4$ bit, the latter makes a significant difference in terms of robustness.

CIFAR10: quantization robustness								
	Model (see text)	Err in %	RErr in %, p in % $p=0.01$					
			0.01	0.05	0.1	0.5	1	1.5
$m = 8$ bit	Eq. (13), global	4.63	10.70 \pm 1.37	86.01 \pm 3.65	90.36 \pm 0.66	90.71 \pm 0.49	90.57 \pm 0.43	–
	Eq. (13), per-layer (= NORMAL)	4.36	4.82 \pm 0.07	5.51 \pm 0.19	6.37 \pm 0.32	24.76 \pm 4.71	72.65 \pm 6.35	87.40 \pm 2.47
	+asymmetric	4.36	5.76 \pm 0.09	6.47 \pm 0.22	7.85 \pm 0.46	40.78 \pm 7.56	76.72 \pm 7.01	85.83 \pm 2.58
	+unsigned	4.42	6.58 \pm 0.13	6.97 \pm 0.28	7.49 \pm 0.41	17.00 \pm 2.77	54.57 \pm 8.58	83.18 \pm 3.94
	+rounded (= RQUANT)	4.32	4.60 \pm 0.08	5.10 \pm 0.13	5.54 \pm 0.2	11.28 \pm 1.47	32.05 \pm 6	68.65 \pm 9.23
4 bit	integer conversion	5.81	90.46 \pm 0.2	90.40 \pm 0.21	90.39 \pm 0.22	90.36 \pm 0.2	90.36 \pm 0.22	90.39 \pm 0.22
	proper rounding	5.29	5.49 \pm 0.04	5.75 \pm 0.06	5.99 \pm 0.09	7.71 \pm 0.36	10.62 \pm 1.08	15.79 \pm 2.54

test example, the empirical test error with random bit errors (i.e., robust test error RErr) and the expected one have to be similar with the same margin. Note also that this bound holds for any fixed bit error distribution as the only requirement is that the bit error patterns we draw are i.i.d. but not the bit errors on the pattern. In App. I.7, we consider results with $l = 10^6$, i.e., $l \gg n$ with $n = 10^4$ on CIFAR10 such that $l/(\sqrt{l} + \sqrt{n})^2$ tends towards one. With $\delta = 0.99$ the

excess term $\sqrt{\frac{\log\left(\frac{n+1}{\delta}\right)}{n} \frac{\sqrt{l} + \sqrt{n}}{\sqrt{l}}}$ in the Proposition is equal to 4.1%. Thus larger test sets would be required to get stronger guarantees e.g. for $n = 10^5$ one would get 1.7%.

E ADVERSARIAL BIT ERRORS

As introduced in the main paper, our adversarial bit error attack can be formulated as the following optimization problem on a fixed mini-batch of examples $\{(x_b, y_b)\}_{b=1}^B$:

$$\begin{aligned} \max_{\tilde{v}} \sum_{b=1}^B \mathcal{L}(f(x_b; Q^{-1}(\tilde{v})), y_b) \\ \text{s.t. } d_H(\tilde{v}, v) \leq \epsilon, \quad d_H(\tilde{v}_i, v_i) \leq 1 \end{aligned} \quad (7)$$

where \tilde{v} are the quantized weights (signed or unsigned m -bit integers) and d_H denotes the (bit-level) Hamming distance. The total number of bit errors $d_H(\tilde{v}, v)$ is constrained by ϵ , and we allow at most one bit error per weight value, i.e., $d_H(\tilde{v}_i, v_i) \leq 1$. These constraints are enforced through projection, after iteratively computing:

$$\begin{aligned} \tilde{w}^{(t+1)} &= \tilde{w}^{(t)} + \gamma \Delta^{(t)} \quad \text{with} \\ \Delta^{(t)} &= \sum_{b=1}^B \mathcal{L}(f(x_b; \tilde{w}_q^{(t)}), y_b), \quad \tilde{w}_q^{(t)} = Q^{-1}(Q(\tilde{w}^{(t)})) \end{aligned} \quad (8)$$

where γ is the step size. We note that the forward pass is performed on the de-quantized weights $\tilde{w}_q^{(t)} = Q^{-1}(Q(\tilde{w}^{(t)}))$, while the update is performed in floating point.

The projection after the update of Eq. (8) requires solving the following optimization problem:

$$\begin{aligned} \min_{\tilde{v}'} \|Q^{-1}(\tilde{v}) - Q^{-1}(\tilde{v}')\|_2^2 \\ \text{s.t. } d_H(v_i, \tilde{v}'_i) \leq 1, \quad d_H(v, \tilde{v}') \leq \epsilon \end{aligned} \quad (9)$$

where we dropped the superscript t for simplicity. Here, $\tilde{v} = Q(\tilde{w})$ are the quantized, perturbed weights after Eq. (8)

and $\tilde{w}' = Q^{-1}(\tilde{v}')$ will be the projected weights. As the objective and the constraint set are separable, this problem can be divided into the following two problems: First, we rank the weights by their corresponding changes

$$|Q^{-1}(Q(w_i)) - Q^{-1}(\tilde{v}_i)| = |w_{q,i} - \tilde{w}_{q,i}| \quad (10)$$

where w are the original, clean weights and w_q the corresponding de-quantized weights. Then, only the top- ϵ changes are kept. All other perturbed weights $\tilde{w}_{q,i}$ are reset to the original, clean weights $w_{q,i}$. For the selected weights, only the most significant changed bit is kept. In practice, considering \tilde{v}_i and v_i from Eq. (9) corresponding to one of the top- ϵ changes, if $d_H(\tilde{v}_i, v_i) > 1$, only the highest changed bit is kept. In practice, this can be implemented (and parallelized) easily on the m -bit integers \tilde{v}_i and v_i while computing the (bit-level) Hamming distance d_H .

The optimization problem Eq. (7) is challenging due to the non-convex constraint set that we project onto after each iteration. Therefore, we use several random restarts, each initialized by randomly selecting $k \in [0, \epsilon]$ bits to be flipped in v to obtain $\tilde{v}^{(0)}$. We note that initialization by randomly flipping bits is important as, without initialization, i.e., $\tilde{w}^{(0)} := w$, the loss \mathcal{L} in Eq. (7) will be close to zero. We also found that initializing with $k = \epsilon$ leads to difficulties in the first few iterations, which is why we sample $k \in [0, \epsilon]$ uniformly. Additionally, we normalize the gradient $\Delta^{(t)}$ in Eq. (8):

$$\hat{\Delta}^{(t,l)} = \frac{\Delta^{(t,l)}}{\|\Delta^{(t,l)}\|_\infty} \quad (11)$$

for each layer l individually (considering biases as separate layer), before applying the update, i.e., $\tilde{w}^{(t+1)} = \tilde{w}^{(t)} + \gamma \hat{\Delta}^{(t)}$. Instead of considering $\tilde{w}^{(T)}$, i.e., the perturbed weights after exactly T iterations, we use

$$\tilde{w}^{(t^*)} \quad \text{with } t^* = \operatorname{argmax}_t \sum_{b=1}^B \mathcal{L}(f(x_b; \tilde{w}_q^{(t)}), y_b) \quad (12)$$

instead. Finally, we also use momentum. Nevertheless, despite these optimization tricks, the attack remains very sensitive to hyper-parameters, especially regarding the step-size. Thus, running multiple random restarts are key.




Fig. C: **Weight Clipping Improves L_∞ Robustness.** On CIFAR10, we plot RErr for *relative* L_∞ perturbations on weights: Random noise with L_∞ -norm smaller than or equal to $x\%$ of the weight range is applied. CLIPPING clearly improves robustness. Again, the relative magnitude of noise is not affected by weight clipping. Note that L_∞ noise usually affects all weights, while random bit errors affect only a portion of the weights.

F QUANTIZATION AND BIT MANIPULATION IN PYTORCH

Our fixed-point quantization Q , as introduced in the main paper, is defined as

$$Q(w_i) = \left\lfloor \frac{w_i}{\Delta} \right\rfloor, \quad Q^{-1}(v_i) = \Delta v_i, \quad \Delta = \frac{q_{\max}}{2^{m-1} - 1}. \quad (13)$$

This quantizes weights $w_i \in [-q_{\max}, q_{\max}] \subset \mathbb{R}$ into signed integers $\{-2^{m-1} - 1, \dots, 2^{m-1} - 1\}$. Here, the quantization range $[-q_{\max}, q_{\max}]$ is symmetric around zero. Note that zero is represented exactly. To implement asymmetric quantization, the same scheme can be used to quantize weights $w_i \in [q_{\min}, q_{\max}]$ within any arbitrary, potentially asymmetric, interval. To this end, Eq. (13) with $q_{\max} = 1$ is used and the weights in $[q_{\min}, q_{\max}]$ are mapped linearly to $[-1, 1]$ using the transformation N :

$$N(w_i) = \left(\frac{w_i - q_{\min}}{q_{\max} - q_{\min}} \right) \cdot 2 - 1. \quad (14)$$

Generally, q_{\min} and q_{\max} are chosen to reflect minimum and maximum weight value – either from all weights (global quantization) or per-layer. Furthermore, we argue that asymmetric quantization becomes more robust when using *unsigned* integers as representation. In this case, Eq. (13) can be adapted using a simple additive term:

$$\begin{aligned} Q(w_i) &= \left\lceil \frac{w_i}{\Delta} \right\rceil + (2^{m-1} - 1) \\ Q^{-1}(v_i) &= \Delta(v_i - (2^{m-1} - 1)) \end{aligned} \quad (15)$$

We use asymmetric quantization using N in Eq. (14) with Eq. (15) as our *robust* fixed-point quantization.

We implement “fake” fixed-point quantization for quantization-aware training and bit error injection directly in PyTorch [62]. Here, fake quantization means that computation is performed in floating point, but before doing a forward pass, the DNN is quantized and dequantized, i.e., $w_q = Q^{-1}(Q(w))$. Note that we quantize into *unsigned* 8 bit integers, irrespective of the target precision $m \leq 8$. To

TABLE E: **Weight Clipping with Weight Scaling.** For group normalization (GN) without the reparameterization in Sec. G, our DNNs are scale-invariant. Scaling RQUANT down to the weight range of $\text{CLIPPING}_{0.25}$, however, does not improve robustness. More importantly, scaling $\text{CLIPPING}_{0.05}$ up to have the same weight range as RQUANT preserves robustness. Thus, the robustness benefit of CLIPPING is *not* due to reduced quantization range or smaller absolute errors.

CIFAR10 ($m = 8$ bit): scaling w/o reparameterized GN			
Model	Err	RErr in %, p in %	
(see text)	in %	$p=0.1$	$p=1$
NORMAL	4.32	5.54 ± 0.2	32.05 ± 6
$\text{CLIPPING}_{0.1}$	4.82	5.58 ± 0.1	8.93 ± 0.46
$\text{NORMAL} \rightarrow \text{CLIPPING}_{0.1}$	4.32	5.55 ± 0.2	88.71 ± 2.42
$\text{CLIPPING}_{0.1} \rightarrow \text{NORMAL}$	4.82	78.47 ± 0.49	9.20 ± 0.67

later induce random bit errors, the $8 - m$ most significant bits (MSBs) are masked for $m < 8$. Bit manipulation of unsigned 8 bit integers is then implemented in C/CUDA and interfaced to Python using CuPy [127] or CFFI [128]. These functions can directly operate on PyTorch tensors, allowing bit manipulation on the CPU as well as the GPU. We will make our code publicly available to facilitate research into DNN robustness against random bit errors.

G WEIGHT CLIPPING WITH GROUP/BATCH NORMALIZATION

While weight clipping, i.e., globally constraining weights to $[-w_{\max}, w_{\max}]$ during training, is easy to implement, we make a simple adjustment to group and batch normalization layers: we reparameterize the scale parameter α of batch/group normalization, which usually defaults to $\alpha = 1$ and may cause problems when clipped, e.g., to $[-0.1, 0.1]$. In particular with aggressive weight clipping, $\alpha \leq w_{\max} < 1$, the normalization layers lose their ability to represent the identity function, considered important for batch normalization in [56]. Our reparameterization introduces a learnable, auxiliary parameter α' such that α is $\alpha = 1 + \alpha'$ to solve this problem.

H EXPERIMENTAL SETUP

Datasets: We conduct experiments on MNIST¹ [63] and CIFAR² [64]. MNIST consists of 60k training and 10k test images from 10 classes. These are gray-scale and of size 28×28 pixels. CIFAR consists of 50k training and 10k test images of size $32 \times 32 \times 3$ (i.e., color images). CIFAR10 has images corresponding to 10 classes, CIFAR100 contains images from 100 classes.

Architecture: The used SimpleNet architectures [65] are summarized in Tab. A, including the total number of weights W . On CIFAR, this results in a total of roughly $W \approx 5.5\text{M}$ weights. Due to the lower resolution on MNIST, channel width in each convolutional layer is halved, and one stage of convolutional layers including a pooling layer is skipped. This results in a total of roughly $W \approx 1\text{M}$ weights.

1. <http://yann.lecun.com/exdb/mnist/>
2. <https://www.cs.toronto.edu/~kriz/cifar.html>

TABLE F: **Weight Clipping Improves Robustness.** We report Err and RErr for various experiments on the robustness of weight clipping with w_{\max} , i.e., $\text{CLIPPING}_{w_{\max}}$. First, we show that the robustness benefit of CLIPPING is independent of quantization-aware training, robustness also improves when applying post-training quantization. Then, we show results for both symmetric and asymmetric quantization. For the latter we demonstrate that label smoothing [70] reduces the obtained robustness. This supports our hypothesis that weight clipping, driven by minimizing cross-entropy loss during training, improves robustness through redundancy.

CIFAR10 (m = 8 bit): clipping robustness for post- and during-training quantization								
	Model	Err in %	RErr in %, p in % p=0.01					
			0.01	0.05	0.1	0.5	1	1.5
Post-Training Asymmetric	NORMAL	4.37	4.95 ±0.11	5.47 ±0.17	6.03 ±0.22	15.42 ±3.4	51.83 ±9.92	81.74 ±5.14
	RQUANT	4.27	4.59 ±0.08	5.10 ±0.13	5.54 ±0.15	10.59 ±1.11	30.58 ±6.05	63.72 ±6.89
	CLIPPING _{0.25}	4.96	5.24 ±0.07	5.73 ±0.14	6.16 ±0.21	10.51 ±0.91	26.27 ±5.65	61.49 ±9.03
	CLIPPING _{0.2}	5.24	5.48 ±0.05	5.87 ±0.09	6.23 ±0.13	9.47 ±0.7	19.78 ±3.58	43.64 ±8.2
	CLIPPING _{0.15}	5.38	5.63 ±0.05	6.03 ±0.09	6.38 ±0.13	8.80 ±0.41	15.74 ±2.24	36.29 ±7.34
	CLIPPING _{0.1}	5.32	5.52 ±0.04	5.82 ±0.06	6.05 ±0.07	7.45 ±0.26	9.80 ±0.62	17.56 ±3.08
Symmetric (during training)	NORMAL	4.36	4.82 ±0.07	5.51 ±0.19	6.37 ±0.32	24.76 ±4.71	72.65 ±6.35	87.40 ±2.47
	RQUANT	4.39	4.77 ±0.08	5.43 ±0.21	6.10 ±0.32	17.11 ±3.07	55.35 ±9.4	82.84 ±4.52
	CLIPPING _{0.25}	4.63	4.99 ±0.07	5.53 ±0.1	6.06 ±0.16	13.55 ±1.42	41.64 ±7.35	73.39 ±7.15
	CLIPPING _{0.2}	4.50	4.79 ±0.06	5.25 ±0.09	5.65 ±0.16	9.64 ±0.99	21.37 ±4.23	45.68 ±7.9
	CLIPPING _{0.15}	5.18	5.42 ±0.05	5.76 ±0.08	6.07 ±0.09	8.36 ±0.43	13.80 ±1.45	24.70 ±3.77
	CLIPPING _{0.1}	4.86	5.07 ±0.04	5.34 ±0.06	5.59 ±0.1	7.12 ±0.3	9.44 ±0.7	13.14 ±1.79
Asymmetric (default) quant. (during training)	NORMAL	4.36	4.82 ±0.07	5.51 ±0.19	6.37 ±0.32	24.76 ±4.71	72.65 ±6.35	87.40 ±2.47
	RQUANT	4.32	4.60 ±0.08	5.10 ±0.13	5.54 ±0.2	11.28 ±1.47	32.05 ±6	68.65 ±9.23
	CLIPPING _{0.25}	4.58	4.84 ±0.05	5.29 ±0.12	5.71 ±0.16	10.52 ±1.14	27.95 ±4.16	62.46 ±8.89
	CLIPPING _{0.2}	4.63	4.91 ±0.05	5.28 ±0.08	5.62 ±0.11	8.27 ±0.35	18.00 ±2.84	53.74 ±8.89
	CLIPPING _{0.15}	4.42	4.66 ±0.05	5.01 ±0.09	5.31 ±0.12	7.81 ±0.6	13.08 ±2.21	23.85 ±5.07
	CLIPPING _{0.1}	4.82	5.04 ±0.04	5.33 ±0.07	5.58 ±0.1	6.95 ±0.24	8.93 ±0.46	12.22 ±1.29
	CLIPPING _{0.05}	5.44	5.59 ±0.04	5.76 ±0.07	5.90 ±0.07	6.53 ±0.13	7.18 ±0.16	7.92 ±0.25
	CLIPPING _{0.2} +LS	4.48	4.77 ±0.05	5.19 ±0.1	5.55 ±0.12	9.46 ±0.82	32.49 ±5.07	68.60 ±7.33
	CLIPPING _{0.15} +LS	4.67	4.86 ±0.05	5.23 ±0.08	5.83 ±0.12	7.99 ±0.43	29.40 ±6.99	68.99 ±8.48
	CLIPPING _{0.1} +LS	4.82	5.05 ±0.04	5.37 ±0.08	6.10 ±0.11	7.36 ±0.4	10.59 ±1.01	18.31 ±2.84
CLIPPING _{0.05} +LS	5.30	5.43 ±0.03	5.63 ±0.06	6.43 ±0.07	6.51 ±0.15	7.30 ±0.23	8.06 ±0.38	

In both cases, we replaced batch normalization (BN) [56] with group normalization (GN) [55]. The GN layers are reparameterized as in App. G to facilitate weight clipping. Tab. A also includes the expected number of bit errors given various rates p for random bit errors. Regarding the number of weights W , SimpleNet compares favorably to, e.g., VGG [129]: VGG-16 has 14M weights on CIFAR. Additionally, we found SimpleNet to be easier to train without BN, which is desirable as BN reduces robustness to bit errors significantly, cf. App. I.1. The ResNet-50 [66] used for experiments in App. I.4 follows the official PyTorch [62] implementation. The Wide ResNet (WRN) [67] used on CIFAR100 is adapted from³, but we use 12 base channels, instead of 16, reducing W from roughly 36.5Mio to 20.5Mio.

Training: We use stochastic gradient descent to minimize cross-entropy loss. We use an initial learning rate of 0.05, multiplied by 0.1 after $2/5$, $3/5$ and $4/5$ of 100/250 epochs on MNIST/CIFAR. Our batch size is 128 and momentum of 0.9 is used together with weight decay of $5 \cdot 10^{-4}$. On CIFAR, we whiten the input images and use AutoAugment⁴ [68] with Cutout [69]. Cutout is applied with a window size of 16×16 , and independent of AutoAugment, we apply random cropping with up to 4 pixels. Created black spaces are filled using the mean image color (grayish). Initialization follows [130]. The full training set is used for training, and we do *not* rely on early stopping. For RANDBET, we use $\lambda = 1$ and start injecting bit errors when the loss is below 1.75 on MNIST/CIFAR10 or 3.5 on CIFAR100. Tab. B high-

lights clean test error (Err) obtained for various precision m and compared to other architectures, e.g., ResNet-50, on CIFAR10, which performs worse when using GN. For ADVBET, we use $\lambda = 0$ and also start injecting adversarial bit errors when the loss is 1.75 or smaller (3.5 on CIFAR100). We use $T = 10$ iterations of our adversarial bit error attack, with learning rate 0.5, no backtracking [21] or momentum [60], and per-layer L_∞ gradient normalization as outlined in the main paper.

Random Bit Errors: We simulate 50 different chips with enough memory arrays to accommodate all weights by drawing uniform samples $u^{(c)} \sim U(0,1)^{W \times m}$ for each chip c and all m bits for a total of W weights. Then, for chip c , bit j in weight w_i is flipped iff $u_{ij}^{(c)} \leq p$. This assumes a linear memory layout of all W weights. The pattern, i.e., spatial distribution, of bit errors for chip c is fixed by $u^{(c)}$, while across all 50 chips, bit errors are uniformly distributed. We emphasize that we pre-determine $u^{(c)}$, $c = 1, \dots, 50$, once for all our experiments using fixed random seeds. Thus, our robustness results are entirely comparable across all models as well as bit error rates p . Also note that the bit errors for a fixed chip c at probability $p' < p$ are a subset of those for bit error rate p . The expected number of bit errors for various rates p is summarized in Tab. A. For random bit errors in activations and inputs we follow a similar strategy as outlined in Sec. I.9.

Adversarial Bit Errors: For evaluation, and fixed ϵ , we run our adversarial bit error attack for a total of 80 random restarts using the following settings: 5 restarts for the untargeted attack with learning rate 1 with and without

3. <https://github.com/meliketoy/wide-resnet.pytorch>

4. <https://github.com/DeepVoltaire/AutoAugment>




Fig. D: **Weight Clipping Increases Redundancy.** We show weight distributions of selected layers (top) for RQUANT, RANDBET (without weight clipping) as well as CLIPPING_{0.1} and CLIPPING_{0.05}. We show weights and biases for the logit layer as well as the first and last (13th) convolutional layer. Scale/Bias parameters of GN are also included. Below (left), this is shown for the scaling experiment from Tab. E. Note that RANDBET only affects the logit layer, while CLIPPING increases the used (relative) weight range significantly. On the bottom (right), we plot various measures of redundancy, see the text for discussion and details. The relative absolute error is computed considering random bit errors with probability $p = 1\%$.

momentum 0.9 (10 restarts in total) and 10 restarts for the targeted attack (1 for each potential target label on MNIST and CIFAR10). This is done attacking all layers. Furthermore, we use 5 untargeted restarts with momentum, and 10 targeted restarts for: attacking only the logit layer, only the first convolutional layer, both the logit and the first convolutional layer, or all layers *except* the logit or first convolutional layer. In total, this makes $20 + 4 \cdot 15 = 80$ restarts of our adversarial bit error attack.

Bit Flip Attack (BFA) [11]: We follow the official PyTorch code⁵. Specifically, we use the provided implementation of BFA to attack our models by integrating our SimpleNet models into the provided attack/evaluation code. This means that we also use the quantization scheme of [11], not our robust fixed-point quantization scheme. However, our models still used RQUANT (and optionally CLIPPING or RANDBET) during training. We use $m = 8$ bits. We allow 5 bit flips per iteration, for a total of T iterations, equalling

$\epsilon = 5 \cdot T$ bit flips. For comparability, we adapted the code to compute adversarial bit flips on the last 100 test examples and evaluate on the first 9000 test examples. We allow 5 restarts for each ϵ .

I EXPERIMENTS

I.1 Batch Normalization

We deliberately replace batch normalization (BN) [56] by group normalization (GN) [55] in our experiments. Tab. C demonstrates that RErr increases significantly when using BN compared to GN indicating that BN is more vulnerable to bit errors in DNN weights. For example, without clipping, RErr increases from 11.28% to staggering 52.52% when replacing GN with BN. Note that, following App. G, the BN/GN parameters (i.e., scale/bias) are reparameterized to account for weight clipping. The observations in Tab. C can also be confirmed without quantization, e.g., considering random L_∞ noise in the weights. We suspect that the running statistics accumulated during training do not account

5. <https://github.com/elliothe/BFA>

TABLE G: **RANDBET Robustness with Symmetric Quantization.** Average RErr and standard deviation for CLIPPING and RANDBET with $w_{\max} = 0.1$ and symmetric quantization, i.e., larger quantization range than asymmetric quantization. Also cf. Tab. F and Tab. S. Robustness decreases slightly compared to asymmetric quantization, however, CLIPPING and RANDBET are still effective in reducing RErr against high bit error rates p .

CIFAR10 ($m = 8$ bit): RANDBET with symmetric quantization							
Model	Err in %	RErr in %, p in % $p=0.01$					
		0.01	0.05	0.1	0.5	1	1.5
NORMAL	4.36	4.82 \pm 0.07	5.51 \pm 0.19	6.37 \pm 0.32	24.76 \pm 4.71	72.65 \pm 6.35	87.40 \pm 2.47
RQUANT	4.39	4.77 \pm 0.08	5.43 \pm 0.21	6.10 \pm 0.32	17.11 \pm 3.07	55.35 \pm 9.4	82.84 \pm 4.52
CLIPPING _{0.1}	4.86	5.07 \pm 0.04	5.34 \pm 0.06	5.59 \pm 0.1	7.12 \pm 0.3	9.44 \pm 0.7	13.14 \pm 1.79
RANDBET _{0.1} $p=0.01$	5.07	5.27 \pm 0.04	5.54 \pm 0.07	5.73 \pm 0.11	7.18 \pm 0.29	9.63 \pm 0.9	13.81 \pm 2.2
RANDBET _{0.1} $p=0.1$	4.62	4.83 \pm 0.04	5.09 \pm 0.08	5.31 \pm 0.08	6.70 \pm 0.28	8.89 \pm 0.59	12.20 \pm 1.33
RANDBET _{0.1} $p=1$	5.03	5.22 \pm 0.04	5.43 \pm 0.06	5.61 \pm 0.07	6.56 \pm 0.13	7.70 \pm 0.26	8.99 \pm 0.42
RANDBET _{0.1} $p=1.5$	5.24	5.37 \pm 0.03	5.57 \pm 0.06	5.76 \pm 0.07	6.66 \pm 0.14	7.62 \pm 0.25	8.71 \pm 0.42
RANDBET _{0.1} $p=2$	5.82	5.97 \pm 0.04	6.19 \pm 0.07	6.37 \pm 0.09	7.22 \pm 0.19	8.03 \pm 0.23	8.96 \pm 0.38

for the random bit errors at test time, even for RANDBET. This is confirmed in Tab. C (bottom) showing that RErr reduces significantly when using the batch statistics at test time. Generally, BN improves accuracy, but might not be beneficial in terms of robustness, as also discussed for adversarial examples [131]. Using GN also motivates our use of SimpleNet instead of, e.g., ResNet-50, which generally performs worse with GN, cf. Tab. B.

I.2 Robust Quantization

Tab. D shows results complementary to the main paper, considering additional bit error rates p . Note that, for $m = 8$ bit, changes in the quantization has negligible impact on clean Err. Only the change from global to per-layer quantization makes a difference. However, considering RErr for larger bit error rates, reducing the quantization range, e.g., through per-layer and asymmetric quantization, improves robustness significantly. Other aspects of the quantization scheme also play an important role, especially for low-precision such as $m = 4$ bit, cf. Tab. D, as outlined in the following.

For example, using asymmetric quantization into *signed* integers actually increases RErr for larger p compared to “just” using symmetric per-layer quantization (rows 2 and 3). Using *unsigned* integers instead reduces RErr significantly. We believe this to be due to the two’s complement representation of signed integers being used with an asymmetric quantization range. In symmetric quantization (around 0, i.e., $[-q_{\max}, q_{\max}]$), bit errors in the sign bit incur not only a change of the integer’s sign, but also the corresponding change in the weights sign⁶. Assuming an asymmetric quantization of $[q_{\min}, q_{\max}]$ with $0 < q_{\min} < q_{\max}$, bit errors in sign bits are less meaningful. For example, flipping any bit 0-to-1 usually increases the value of the integer. However, a 0-to-1 flip in the sign bit actually decreases the value and produces a *negative* integer. However, this change from positive to negative is not reflected in the corresponding weight value (as $q_{\min} > 0$). For high bit error rates $p\%$, this happens more and more frequently and these

6. An *unsigned* integer of value 127 is represented as 01111111. Flipping the most (left-most) significant bit results in 11111111 corresponding to 255, i.e., the value increases. For a signed integer in two’s complement representation, the same bit flip changes the value from 127 to -1 , while 0-to-1 not affecting the sign bit generally increase value (also for negative integers).

changes seem to have larger impact on DNN performance, i.e., RErr.

Additionally, we considered the difference between using integer conversion for w_i/Δ and using proper rounding, i.e., $\lceil w_i/\Delta \rceil$. We emphasize that, for $m = 8$ bit, there is *no* significant difference in terms of clean Err. However, using proper rounding reduces the approximation error slightly. For $m = 8$ bit, using $p = 2.5\%$ bit error rate, the average absolute error (in the weights) across 10 random bit error patterns reduces by 2%. Nevertheless, it has significantly larger impact on RErr. For $m = 4$, this is more pronounced: rounding reduces the average absolute error by roughly 67%. Surprisingly, this is not at all reflected in the clean Err, which only decreases from 5.81% to 5.29%. It seems that the DNN learns to compensate these errors during training. At test time, however, RErr reflects this difference in terms of robustness.

Overall, we found that robust quantization plays a key role. While both weight clipping (CLIPPING) and random bit error training (RANDBET) can improve robustness further, robust quantization lays the foundation for these improvements to be possible. Thus, we encourage authors to consider robustness in the design of future DNN quantization schemes. Even simple improvements over our basic fixed-point quantization scheme may have significant impact in terms of robustness. For example, proper handling of outliers [16], [17], learned quantization [132], or adaptive/non-uniform quantization [133], [134], [135] are promising directions to further improve robustness. Finally, we believe that this also poses new theoretical challenges, i.e., studying (fixed-point) quantization with respect to robustness *and* quantization error.

I.3 (Global) Weight Clipping (CLIPPING)

In Tab. F we present robustness results, i.e., RErr, for weight clipping. Note that weight clipping constraints the weights during training to $[-w_{\max}, w_{\max}]$ through projection. We demonstrate that weight clipping can also be used independent of quantization. To this end, we train DNNs with weight clipping, but without quantization. We apply post-training quantization and evaluate bit error robustness. While the robustness is reduced slightly compared to quantization-aware training *and* weight clipping, the robustness benefits of weight clipping are clearly visible. For example, clipping at $w_{\max} = 0.1$ improves RErr from 30.58%

TABLE H: **RANDBET Variants**. Err and RErr for RANDBET and two variants: curricular RANDBET, with p being increased slowly from $p/20$ to p during the first half of training; and “alternating” RANDBET where weight updates increasing quantization range, i.e., increasing the maximum absolute weight per layer, are not possible based on gradients from perturbed weights, see Sec. I.4 for details. Both variants decrease robustness slightly. This is in contrast to, e.g., [19], using curricular training on profiled bit errors with success.

CIFAR10 (m = 8 bit): RANDBET variants			
	Err	RErr in %	
	in %	$p=0.1$	$p=1$
RANDBET $p=0.1, w_{\max} = 0.1$	4.93	5.67	8.65
RANDBET $p=1, w_{\max} = 0.1$	5.06	5.87	7.60
Curriculum RANDBET $p=1, w_{\max} = 0.1$	4.89	5.78	8.51
Curriculum RANDBET $p=1, w_{\max} = 0.1$	5.32	6.13	7.98
Alternating RANDBET $p=1, w_{\max} = 0.1$	5.07	5.91	8.93
Alternating RANDBET $p=1, w_{\max} = 0.1$	5.24	6.25	8.02

to 9.8% against $p = 1\%$ bit error rate when performing post-training quantization. With symmetric quantization-aware training, CLIPPING_{0.1} improves slightly to 7.31%. Below (middle), we show results for weight clipping and symmetric quantization. These results are complemented in Tab. G with RANDBET. Symmetric quantization might be preferable due to reduced computation and energy cost compared to asymmetric quantization. However, this also increases RErr slightly. Nevertheless, CLIPPING consistently improves robustness, independent of the difference in quantization. Finally, on the bottom, we show results confirming the adverse effect of label smoothing [70] on RErr. Fig. C also shows that the obtained robustness generalizes to other error models such as L_{∞} weight perturbations, see caption for details.

We hypothesize that weight clipping improves robustness as it encourages redundancy in weights and activations during training. This is because cross-entropy loss encourages large logits and weight clipping forces the DNN to “utilize” many different weights to produce large logits. Tab. E presents a simple experiment in support of our hypothesis. We already emphasized that, relatively, weight clipping does *not* reduce the impact of bit errors. Nevertheless, when using group normalization (GN), the trained DNNs are scale-invariant in their weights (e.g., as discussed in [136]). Note that the GN parameters (scale and bias) are *not* scaled. We down-scale the weights of RQUANT to have the same maximum absolute weight value as CLIPPING_{0.1} (RQUANT \rightarrow CLIPPING_{0.1}). This scaling is applied globally, not per layer. Similarly, we up-scale the weights of CLIPPING_{0.1} to the same maximum absolute weight value as RQUANT (CLIPPING_{0.1} \rightarrow RQUANT). Tab. E shows that “just” down-scaling does not induce robustness, as expected. More importantly, up-scaling the weights after training with weight clipping, $w_{\max} = 0.1$, preserves robustness. This simple experiment supports our argument that CLIPPING does not improve robustness due to the reduced quantization range but acts as a regularizer as described in the main paper.

Fig. D presents further supporting evidence for our hypothesis: While RANDBET mainly affects the logits layer, CLIPPING clearly increases the weight range used by the DNN. Here, the weight range is understood relative to

TABLE I: **RANDBET with ResNets**. We report RErr for RQUANT, CLIPPING and RANDBET using ResNet-20 and ResNet-50. According to Tab. B, Err increases significantly when using group normalization for ResNet-50, explaining the generally higher RErr. However, using ResNets, CLIPPING and RANDBET continue to improve robustness significantly, despite a ResNet-50 having roughly 23.5Mio weights.

CIFAR10 (m = 8 bit): ResNet architectures			
	Err	RErr in %	
	in %	$p=0.5$	$p=1.5$
ResNet-20			
RQUANT	4.34	13.89 ± 2.45	81.25 ± 5.08
CLIPPING _{0.1}	4.83	6.76 ± 0.16	11.23 ± 0.97
RANDBET _{0.1, p=1}	5.28	6.72 ± 0.19	8.96 ± 0.49
ResNet-50			
RQUANT	6.81	32.94 ± 5.51	90.98 ± 0.67
CLIPPING _{0.1}	5.99	9.27 ± 0.44	36.39 ± 7.03
RANDBET _{0.1, p=1}	6.04	7.87 ± 0.22	11.27 ± 0.6

w_{\max} (or the maximum absolute weight value for NORMAL). This is pronounced in particular when up-scaling the clipped model (bottom left). Finally, Fig. D (bottom right) also considers three attempts to measure redundancy in weights and activations. The relative absolute error is computed with respect to $p = 1\%$ bit error rate and decreases for CLIPPING, meaning that random bit errors have less impact. *Weight relevance* is computed as the sum of absolute weights, i.e., $\sum_i |w_i|$, normalized by the maximum absolute weight: $\sum_i |w_i| / \max_i |w_i|$. This metric measures how many weights are, considering their absolute value, relevant. Finally, We also measure activation redundancy using ReLU relevance, computing the fraction of non-zero activations after the final ReLU activation. CLIPPING increases redundancy in the final layer significantly. Finally, Fig. D (bottom left) shows the difference in weight distributions by upscaling CLIPPING_{0.25} to the same weight range as NORMAL. Clearly, CLIPPING causes more non-zero weights be learned by the DNN. This can be observed across all types of parameters, i.e., weights or biases as well as convolutional or fully connected layers.

As CLIPPING adds an additional hyper-parameter, Tab. F also illustrates that w_{\max} can easily be tuned based on clean performance. Specifically, lower w_{\max} will eventually increase Err and reduce confidences (alongside increasing cross-entropy loss). This increase in Err is usually not desirable except when optimizing for robust performance, i.e., considering RErr. Also, we found that weight clipping does not (negatively) interact with any other hyper-parameters or regularizers. For example, as described in Sec. H, we use weight clipping in combination with AutoAugment/Cutout and weight decay without problems. Furthermore, it was not necessary to adjust our training setup (i.e., optimizer, learning rate, epochs, etc.), even for low w_{\max} .

I.4 Random Bit Error Training (RANDBET)

Tab. G shows complementary results for RANDBET using *symmetric* quantization. Symmetric quantization generally tends to reduce robustness, i.e., increase RErr, across all bit error rates p . Thus, the positive impact of RANDBET is pronounced, i.e., RANDBET becomes more important to obtain




Fig. E: **Per-Layer Weight Clipping**. On CIFAR, we show the weight ranges, per layer, corresponding to RQUANT (i.e., without weight clipping) and the architecture from Tab. A. As can be seen, few layers exhibit large ranges. Thus, per-layer clipping computes a layer-specific weight constraint $[-w_{\max,l}, w_{\max,l}]$, derived from a global w_{\max} and based on the weight range relative to the layer with largest range. As not to “over-constraint” layers with small weight range, a minimum range of $[-0.2w_{\max}, 0.2w_{\max}]$ is enforced.

TABLE J: **PLCLIPPING and PLRANDBET Further Push Robustness**. Err and RErr for PLCLIPPING and PLRANDBET with various configurations of w_{\max} and p used for training. Compared to Tab. G, reporting results for CLIPPING and RANDBET, i.e., without per-layer weight clipping, robustness can be improved significantly, while simultaneously reducing (clean) Err.

CIFAR10 (m = 8 bit): <i>per-layer</i> clipping and RANDBET robustness							
Model	Err in %	RErr in %, p in % $p=0.01$					
		0.01	0.05	0.1	0.5	1	1.5
PLCLIPPING ₁	4.68	4.98 ± 0.1	5.52 ± 0.16	6.06 ± 0.2	13.56 ± 2.74	40.72 ± 10.6	73.66 ± 7.74
PLCLIPPING _{0.5}	4.49	4.73 ± 0.06	5.07 ± 0.11	5.36 ± 0.12	7.76 ± 0.48	13.04 ± 1.61	23.54 ± 4.67
PLCLIPPING _{0.25}	4.78	4.93 ± 0.04	5.15 ± 0.07	5.32 ± 0.1	6.17 ± 0.17	7.16 ± 0.33	8.25 ± 0.56
PLCLIPPING _{0.2}	4.84	4.95 ± 0.04	5.08 ± 0.05	5.19 ± 0.07	5.81 ± 0.13	6.48 ± 0.2	7.18 ± 0.32
PLCLIPPING _{0.15}	5.31	5.41 ± 0.03	5.54 ± 0.05	5.63 ± 0.06	6.06 ± 0.08	6.53 ± 0.14	6.93 ± 0.2
PLCLIPPING _{0.1}	5.62	5.69 ± 0.03	5.78 ± 0.05	5.86 ± 0.05	6.27 ± 0.09	6.66 ± 0.13	6.96 ± 0.16
PLRANDBET _{0.25} $p=0.1$	4.49	4.62 ± 0.04	4.82 ± 0.07	4.98 ± 0.08	5.80 ± 0.16	6.65 ± 0.22	7.59 ± 0.34
PLRANDBET _{0.25} $p=1$	4.62	4.73 ± 0.03	4.90 ± 0.06	5.02 ± 0.06	5.62 ± 0.13	6.36 ± 0.2	7.02 ± 0.27
PLRANDBET _{0.1} $p=1$	5.66	5.76 ± 0.03	5.88 ± 0.06	5.96 ± 0.05	6.29 ± 0.09	6.59 ± 0.11	6.87 ± 0.12
PLRANDBET _{0.25} $p=2$	4.94	5.06 ± 0.04	5.22 ± 0.06	5.33 ± 0.06	5.92 ± 0.13	6.48 ± 0.19	7.04 ± 0.25
PLRANDBET _{0.1} $p=2$	5.60	5.67 ± 0.02	5.77 ± 0.05	5.84 ± 0.05	6.20 ± 0.09	6.49 ± 0.09	6.72 ± 0.13

high robustness when less robust fixed-point quantization is used. These experiments also demonstrate the utility of RANDBET independent of the quantization scheme at hand.

As ablation for RANDBET, we consider two variants of RANDBET motivated by related work [19]. Specifically, in [19], the bit error rate seen during training is increased slowly during training. Note that [19] trains on fixed bit error patterns. Thus, increasing the bit error rate during training is essential to ensure that the DNN is robust to any bit error rate $p' < p$ smaller than the target bit error rate. While this is generally the case using our RANDBET, Tab. H shows that slowly increasing the random bit error rate during training, called “curricular” RANDBET, has no significant benefit over standard RANDBET. In fact, RErr increases slightly. Similarly, we found that RANDBET tends to increase the range of weights: the weights are “spread out”, cf. Fig. D (top right). This also increases the quantization range, which has negative impact on robustness. Thus, we experimented with RANDBET using two weight updates per iteration: one using clean weights, one on weights with bit errors. This is in contrast to averaging both updates as described in the main paper. Updates computed from perturbed weights are limited to the current quantization

ranges, i.e., the maximum absolute error cannot change. This is ensured through projection. This makes sure that RANDBET does not increase the quantization range during training as changes in the quantization range are limited to updates from clean weights. Again, Tab. H shows this variant to perform slightly worse.

Tab. I also shows results on CIFAR10 using ResNet-20 and ResNet-50. We note that, in both cases, we use group normalization (GN) instead of batch normalization (BN) as outlined in Sec. I.1. ResNet-50, in particular, suffers from using GN due to the significant depth: the clean Err reduces from 3.67% to 6.81% in Tab. B. Nevertheless, CLIPPING and RANDBET remain effective against random bit errors, even for higher bit error rates of $p = 1.5\%$. This is striking as ResNet-50 consists of roughly 23.5Mio weights, compared to 5.5Mio of the used SimpleNet in the main paper.

Following the RANDBET algorithm outlined in the main paper, RANDBET adds an additional forward and backward pass during training, increasing training complexity roughly by a factor of two. In practice, however, we found that training time for RANDBET (in comparison with CLIPPING) roughly triples. This is due to our custom implementation of bit error injection, which was not optimized for speed.

TABLE K: **Generalization to Profiled Bit Errors.** We show RErr on profiled bit errors, chips 1-3, for RANDBET as well as CLIPPING. Note that for chip 3, CLIPPING_{0.05} performs slightly better than RANDBET. However, using per-layer clipping, PLRANDBET performs best.

CIFAR10: Generalization to Profiled Bit Errors					
Chip	Model (CIFAR10)	Err in %	RErr in %		
			$p \approx 0.86$	$p \approx 2.7$	
1	RQUANT	4.32	23.57	89.84	
	CLIPPING _{0.05}	5.44	7.17	10.50	
	RANDBET _{0.05} $p=1.5$	5.62	7.04	9.37	
	PLCLIPPING _{0.15}	5.27	6.52	8.48	
	PLRANDBET _{0.25} , $p=1$	4.62	6.22	9.81	
	PLRANDBET _{0.15} , $p=2$	4.99	6.14	7.58	
			$p \approx 0.14$	$p \approx 1$	
2	RQUANT	4.32	6.00	74.00	
	CLIPPING _{0.05}	5.44	5.98	10.02	
	RANDBET _{0.05} $p=1.5$	5.62	6.00	9.00	
	PLCLIPPING _{0.15}	5.27	5.64	8.97	
	PLRANDBET _{0.25} , $p=1$	4.62	5.13	8.86	
	PLRANDBET _{0.15} , $p=2$	4.99	5.34	7.34	
			$p \approx 0.03$	$p \approx 0.5$	
3	RQUANT	4.32	5.47	80.49	
	CLIPPING _{0.05}	5.44	5.78	11.88	
	RANDBET _{0.05} $p=1.5$	5.62	5.85	12.44	
	PLCLIPPING _{0.15}	5.27	5.52	16.14	
	PLRANDBET _{0.25} , $p=1$	4.62	4.91	11.94	
	PLRANDBET _{0.15} , $p=2$	4.99	5.19	8.63	

However, we believe that training time can be reduced significantly using an efficient CUDA implementation of bit error injection. We also note that inference time remains unchanged. In this respect, bit error mitigation strategies in hardware are clearly less desirable due to increased inference time, space and energy consumption.

I.5 Per-Layer CLIPPING and RANDBET

Fig. E shows the per-layer weight ranges of RQUANT trained without weight clipping that we used to determine the constraints for *per-layer* weight clipping (PLCLIPPING) on CIFAR10. Specifically, we found that only few layers exhibit large weight ranges, e.g., the first few convolutional layers (“conv1” and “conv2” in Fig. E), few group normalization layers (“regn7” or “regn9”) and the final logit layer (“logits”). Thus, these layers are affected significantly when reducing w_{\max} and lead to poor (clean) Err in Tab. L, e.g., for $w_{\max} = 0.05$. Therefore, we also consider per-layer weight clipping, i.e., using individual values $w_{\max, l}$ for each layer, as described in detail in the main paper. We use the RQUANT model from Fig. E as reference for all models on CIFAR10. On MNIST and CIFAR100, we use the corresponding RQUANT models as reference. When additionally combined with RANDBET, we use PLRANDBET to denote random bit error training *with* per-layer weight clipping.

Tab. J shows results for PLCLIPPING and PLRANDBET considering various bit error rates p . In comparison to the results in Tab. G, robustness can be improved considerably, while also improving clean performance. For example, CLIPPING_{0.1} (i.e., global) obtains 13.14% RErr a bit error rate of $p = 1.5\%$. Using PLCLIPPING, this can be improved to 6.96% for PLCLIPPING_{0.1}. Similarly, RANDBET benefits from per-layer clipping. However, the difference between PLCLIPPING and PLRANDBET, considering RErr, is sig-

TABLE L: **Fixed Pattern Bit Error Training.** We report RErr for training on fixed, profiled bit error patterns (PATTBET). Note that for PATTBET on chip 1/2 we used only the stuck-at-errors shown in Fig. B, which is why the bit error rates deviate from those reported in the main paper, cf. Fig. B.

CIFAR10: Fixed Pattern Training		
Model (CIFAR10)	RErr in %, p in %	
Profiled Bit Errors (Chip 1)		
PATTBET, $p \approx 1.22$	$p \approx 0.39$	$p \approx 1.22$
PATTBET, $p \approx 0.39$	9.52	7.20
PATTBET _{0.15} , $p \approx 1.22$	5.77	67.87
PATTBET _{0.15} , $p \approx 0.39$	7.67	6.52
	5.94	30.96
Profiled Bit Errors (Chip 2)		
PATTBET $p \approx 0.63$	$p \approx 0.1$	$p \approx 0.63$
PATTBET, $p \approx 0.1$	85.84	10.76
PATTBET _{0.15} $p \approx 0.63$	90.56	5.93
PATTBET _{0.15} $p \approx 0.1$	12.02	8.70
	90.68	6.51

TABLE M: **Results for Probabilistic Guarantees.** Average RErr and standard deviation for $l = 1$ Mio random bit error patterns. In comparison with the results for $l = 50$ from the main paper, there are no significant changes in RErr.

CIFAR10: Stress Test for Guarantees			
Model (CIFAR10)	Err in %	RErr in %, $p = 1\%$ $l = 50$	$l = 1$ Mio
RQUANT	4.32	32.05 \pm 6	31.97 \pm 6.35
CLIPPING _{0.05}	5.44	7.18 \pm 0.16	7.19 \pm 0.2
RANDBET _{0.05} $p=2$	5.42	6.71 \pm 0.11	6.73 \pm 0.15
PLCLIPPING _{0.15}	5.31	6.53 \pm 0.14	6.52 \pm 0.14
PLRANDBET _{0.25} , $p=1$	4.62	6.36 \pm 0.2	6.29 \pm 0.2
PLRANDBET _{0.15} , $p=2$	4.99	6.12 \pm 0.13	6.12 \pm 0.14

nificantly smaller than before. This illustrates that *per-layer* weight clipping can have tremendous impact on robustness.

I.6 Profiled Bit Errors

Following the evaluation on profiled bit errors outlined in App. D.1, Tab. K shows complementary results for CLIPPING_{0.05}, RANDBET_{0.05}, PLCLIPPING_{0.15} and PLRANDBET_{0.15} trained with $p = 1.5\%$ and $p = 2\%$, respectively, on all profiled chips. Note that for particularly extreme cases, such as chip 3, CLIPPING might perform slightly better than RANDBET, indicating a significantly different bit error distribution as assumed in the main paper. Nevertheless, PLCLIPPING as well as PLRANDBET are able to cope even with particularly difficult bit error distributions. Overall, PLRANDBET generalizes reasonably well, with very good results on chip 1 and chip 2. Note that, following Fig. B, the bit errors in chip 2 are strongly aligned along columns. Results on chip 3 are slightly worse. However, PLRANDBET does not fail catastrophically with only a $\sim 1\%$ increase in RErr compared to chips 1 and 2.

In Tab. L, we follow the procedure of App. D.1 considering only stuck-at-0 and stuck-at-1 bit errors (i.e., where p_{10} and p_{01} are 1). This is illustrated in Fig. B (right). Thus, the bit error rates deviate slightly from those reported in Tab. K, see the table in App. D.1 for details. Furthermore, We consider only one weight-to-SRAM mapping, i.e., without offset. PATTBET is trained and evaluated on the exact same bit error pattern, but potentially with different bit error rates p . Note that the bit errors for $p' < p$ are a subset of those for bit error rate p . Thus, it is surprising that, on both chips




Fig. F: **Summary Results on CIFAR10, CIFAR100 and MNIST.** We plot RErr against bit error rate, highlighting individual CLIPPING, RANDBET, PLCLIPPING and PLRANDBET models. Note that the main paper, in contrast, presents the best, i.e., lowest RErr, model for each bit error rate p individually. Instead, individual models help to illustrate the involved trade-offs: CLIPPING with small w_{\max} or RANDBET with high bit error rate p increases the clean Err, thereby also increasing RErr for very small bit error rates. However, RErr against large bit error rates can be reduced significantly.

1 and 2, PATTBET trained on higher bit error rates does not even generalize to lower bit error rates (i.e., higher voltage). This is problematic in practice as the DNN accelerator should not perform worse when increasing voltage.

I.7 Guarantees from Prop. 1

Based on the bound derived in Sec. D.2, we conduct experiments with $l = 1\text{Mio}$ random bit error patterns, such that $l \gg n$ where $n = 10\text{k}$ is the number of test examples on CIFAR10. Considering Prop. 1, this would guarantee a deviation in RErr of at most 4.1% with probability at least 99%. As shown in Tab. M, the obtained RErr with 1Mio random bit error patterns deviates insignificantly from the results in the main paper. Only standard deviation of RErr increases slightly. These results emphasize that the results for CLIPPING and RANDBET from the main paper generalize well.

I.8 Summary Results

Fig. F summarizes our results: In contrast to the main paper, we consider individual CLIPPING and RANDBET models instead of focusing on the best results per bit error rate p . Additionally, we show our complete results for lower precisions, i.e., $m = 4, 3, 2$ on CIFAR10 and MNIST. Note that these results, in tabular form, are included in Tab. S to X.

Moderate CLIPPING, e.g., using $w_{\max} = 0.15$ on CIFAR10 (in red solid), has negligible impact on clean Err (i.e., $p = 0$ on the x-axis) while improving robustness beyond $p = 0.1\%$ bit error rate. Generally, however, higher robustness is obtained at the cost of increased clean Err, e.g., for $w_{\max} = 0.05$ (in blue dotted). Here, it is important to note that in low-voltage operation, only RErr matters – clean Err is only relevant for voltages higher than V_{\min} . Per-layer weight clipping, i.e., PLCLIPPING, is able to avoid the increase in Err in many cases, while preserving improved robustness. RANDBET further improves robustness, both on top of CLIPPING and PLCLIPPING, for high bit error rates while continuing to increase (clean) Err slightly. For example, RANDBET with $w_{\max} = 0.05$ and trained with $p = 2\%$ bit errors increases clean Err to 5.42% but is also able to keep RErr below 7% up to $p = 1\%$ bit error rate (in violet dotted). While per-layer clipping, i.e., $\text{PLCLIPPING}_{0.15}$ (in yellow), does not improve robustness compared to $\text{CLIPPING}_{0.05}$, clean Err is lowered. More importantly, using $\text{PLRANDBET}_{0.15}$ (in brown) clearly outperforms most other approaches, showing that RANDBET is particularly effective on top of PLCLIPPING, in contrast to “just” CLIPPING. Similar observations can be made for MNIST as well as CIFAR100.

The advantage of per-layer clipping, i.e., PLCLIPPING and PLRANDBET, are pronounced when reducing precision. For example, using $m = 2$, PLCLIPPING not only

TABLE N: **Input Robustness for CLIPPING and PLRANDBET**. Average RErr for bit errors in inputs. Images are quantized using $m = 8$ bit quantization (per channel) in $[0, 1]$, which does *not* introduce errors as the images are already provided in 8-bit (per channel). Note that PLRANDBET considers only bit errors in weights during training. We note that Err is reported on the first 1k test images, to be comparable with RErr for bit errors in inputs. Extreme CLIPPING generally reduces robustness to such input perturbations. Similarly, PLRANDBET (bit errors in weights during training) may reduce robustness, indicating that robustness against bit errors in weights is in conflict with robustness against bit errors in the inputs. Nevertheless, PLRANDBET (training on bit errors in inputs) can improve robustness significantly.

CIFAR10: Bit Error Robustness in Inputs (RANDBET)			
Model (CIFAR10) bit errors in inputs , p in %	Err in %	RErr in %	
		$p=0.1$	$p=0.5$
RQUANT	4.22	11.10	23.70
CLIPPING _{0.25}	4.53	11.30	22.70
CLIPPING _{0.1}	4.81	12.50	25.40
PLCLIPPING _{0.25}	4.92	10.80	22.80
PLCLIPPING _{0.1}	5.73	12.80	26.50
PLRANDBET _{0.75} (weights only), $p_w=0.1$	4.59	10.20	22.20
PLRANDBET _{0.5} (weights only), $p_w=0.1$	4.48	10.90	21.00
PLRANDBET _{0.25} (weights only), $p_w=0.1$	4.46	11.00	22.80
PLRANDBET _{0.5} (weights only), $p_w=1$	5.04	11.00	24.20
PLRANDBET _{0.25} (weights only), $p_w=1$	4.64	11.30	22.40
PLRANDBET _{0.1} (weights only), $p_w=1$	5.63	13.00	25.80
PLRANDBET _{0.25} weights+inputs, $p_w=0.1$, $p_i=0.1$	4.94	7.60	11.70
PLRANDBET _{0.25} weights+inputs, $p_w=0.1$, $p_i=0.5$	4.74	8.00	12.90
PLRANDBET _{0.1} weights+inputs, $p_w=0.1$, $p_i=0.1$	5.94	9.00	15.10
PLRANDBET _{0.1} weights+inputs, $p_w=0.1$, $p_i=0.5$	5.72	8.80	17.50
PLRANDBET _{0.25} weights+inputs, $p_w=1$, $p_i=0.1$	5.57	7.70	9.10
PLRANDBET _{0.25} weights+inputs, $p_w=1$, $p_i=0.5$	5.39	7.60	8.90
PLRANDBET _{0.25} weights+inputs+activations, $p_w=0.1$, $p_i=0.1$, $p_a=0.1$	5.16	7.90	12.20
PLRANDBET _{0.25} weights+inputs+activations, $p_w=0.1$, $p_i=0.1$, $p_a=0.5$	5.02	7.60	12.00
PLRANDBET _{0.25} weights+inputs+activations, $p_w=1$, $p_i=0.1$, $p_a=0.1$	9.09	11.50	13.80
PLRANDBET _{0.25} weights+inputs+activations, $p_w=1$, $p_i=0.1$, $p_a=0.5$	8.97	11.10	14.10

boosts robustness significantly, but also avoids a significant increase in Err. As result, using PLRANDBET instead of PLCLIPPING is only necessary for high bit error rates, e.g., above $p = 1\%$. Similar trade-offs can be observed on CIFAR100 and MNIST. On CIFAR100, we see that task difficulty also reduces the bit error rate that is tolerable without significant increase in RErr. Here, $p = 0.1\%$ increases RErr by more than 3%, even with RANDBET (and weight clipping). Furthermore, CIFAR100 demonstrates that CLIPPING and RANDBET are applicable to significantly larger architectures such as Wide ResNets without problems. On MNIST, in contrast, bit error rates of up to $p = 20\%$ are easily possible. At such bit error rates, the benefit of RANDBET is extremely significant as even CLIPPING_{0.025} exhibits very high RErr of 32.68% at $p = 20\%$, cf. Tab. W.

1.9 Bit Errors in Activations and Inputs

Setup: We quantize inputs using $m = 8$ bits and $q_{\min} = 0/q_{\max} = 1$ in Eq. (13) (using asymmetric quantization into unsigned integers). This does not introduce errors as images are typically provided using 8 bit (i.e., 256 distinct values) per pixel per color (i.e., channel). Random bit errors are injected once before the forward pass, this can easily be done per batch. As with random bit errors in weights, we consider 50 samples of random bit errors per example per model. The bit error patterns are the same across models for comparison, i.e., in the notation of the main paper, we sample $u \sim U(0, 1)^{D \times m}$ for each image and attempt. Here, D is the input dimensionality ($D = 32 \cdot 32 \cdot 3$ on CIFAR10). For bit error rate p , bit i, j is flipped iff $u_{i,j} \leq p$. Again, this ensures that bit errors at probability $p' \leq p$ also




Fig. G: **Adversarial Bit Error Iterations**. We plot loss \mathcal{L} and robust error RErr against iterations, both measured on the 100 held-out test examples used to find adversarial bit errors for the “smaller” model on CIFAR10, corresponding to halved channels in Tab. Q. Thus, we also reduced ϵ compared to the main paper. Again, the targeted attack is most effective. For the untargeted one, first convolutional and logit layers are particularly vulnerable.

occur at bit error rate p . Note that u is fixed across models for comparability. Implementing bit error injection in input x is straight-forward considering Sec. F, i.e., computing $\tilde{x} = Q^{-1}(\text{BErr}_p(Q(x)))$.

For activations, we inject random bit errors after “blocks” consisting of convolution, normalization and ReLU. On CIFAR10, using our SimpleNet architecture, this results in bit errors being injected after 13 such blocks, as illustrated by a * in Tab. A. We assume that these activations are temporally stored on the SRAM and thus subject to bit errors. As discussed in the main paper, this is a reasonable approximation of how the data flow could look on an actual accelerator. As with inputs, we pre-sample $u \in U(0, 1)^{A_l \times m}$ for each block l and for 50 attempts, with A_l being the dimensionality of activations, and flip bit i, j iff $u_{i,j} \leq p$.

TABLE O: **Activation Robustness for CLIPPING and PLRANDBET.** Average RErr for bit errors in activations; the same $m = 8$ bit quantization is used for weights and activations. PLRANDBET considers only bit errors in weights during training. We note that activation quantization without bit errors has negligible impact on Err. However, when training on bit errors in activations, Err may increase similarly as with bit errors in the weights. Regarding robustness against bit errors in activations, CLIPPING and PLRANDBET improve robustness, however, extreme clipping or RANDBET with large bit error rates in the weights reduces robustness.

CIFAR10: Bit Error Robustness in Activations				
Model (CIFAR10) 8-bit activation quantization, bit errors in activations, p in %	Err in % (w/o quant. act.)	Err in % (quant. act.)	RErr in %	
			$p=0.1$	$p=0.5$
RQUANT	4.32	4.53	8.93	47.12
CLIPPING _{0.25}	4.58	4.67	7.97	31.98
CLIPPING _{0.1}	4.82	5.13	7.86	24.38
PLCLIPPING _{0.25}	4.96	5.16	7.38	21.58
PLCLIPPING _{0.1}	5.62	5.84	8.72	27.36
PLRANDBET _{0.75} (weights only), $p_w=0.1$	4.57	4.78	8.74	38.99
PLRANDBET _{0.5} (weights only), $p_w=0.1$	4.48	4.79	7.46	27.67
PLRANDBET _{0.25} (weights only), $p_w=0.1$	4.49	4.71	7.25	24.94
PLRANDBET _{0.5} (weights only), $p_w=1$	5.11	5.33	8.10	26.90
PLRANDBET _{0.25} (weights only), $p_w=1$	4.62	4.83	6.92	19.83
PLRANDBET _{0.1} (weights only), $p_w=1$	5.66	5.92	9.31	35.79
PLRANDBET _{0.25} activations only, $p_a=0.1$	4.73	4.84	6.40	12.10
PLRANDBET _{0.25} activations only, $p_a=0.5$	5.43	5.68	6.74	10.16
PLRANDBET _{0.1} activations only, $p_a=0.1$	5.92	6.09	7.56	12.62
PLRANDBET _{0.1} activations only, $p_a=0.5$	6.52	6.63	7.77	10.81
PLRANDBET _{0.25} weights+activations, $p_w=1, p_a=0.1$	7.59	7.80	8.88	11.79
PLRANDBET _{0.25} weights+activations, $p_w=1, p_a=0.5$	7.66	7.89	9.09	12.17
PLRANDBET _{0.25} weights+activations, $p_w=1, p_a=1$	7.68	7.83	9.05	12.07
PLRANDBET _{0.25} weights+inputs+activations, $p_w=1, p_i=0.1, p_a=0.1$	9.16	9.31	10.54	13.51
PLRANDBET _{0.25} weights+inputs+activations, $p_w=1, p_i=0.1, p_a=0.5$	9.01	9.32	10.56	13.65

TABLE P: **Required Bit Flips for BFA [11].** We report the average number (and standard deviation) of required bit flips ϵ_{BFA} for BFA to increase RErr to 90% or above. This is complementary to the main paper, where we do not ask how many bit errors are required to reduce accuracy to random guessing but rather consider the RErr given a limited amount of allowed bit errors ϵ .

MNIST	ϵ_{BFA}
RQUANT	98 \pm 7.5
CLIPPING _{0.05}	437 \pm 49.7
RANDBET _{0.05, p=20}	754 \pm 58.5
ADVBET _{0.05, $\epsilon=160$}	1403 \pm 263.3
CIFAR10	ϵ_{BFA}
RQUANT BN	54 \pm 8.5
RQUANT GN	385 \pm 33.9
CLIPPING _{0.05} BN	213 \pm 20.9
CLIPPING _{0.05} GN	1725 \pm 60.8
RANDBET _{0.05, p=2}	2253 \pm 26
ADVBET _{0.05, $\epsilon=160$}	2187 \pm 11.2

Again, we use $m = 8$ bits. However, in contrast to inputs, quantization itself introduces an error and might increase (clean) Err. Pre-sampling u for each block independently essentially assumes that activations of different blocks are stored in different portions of the SRAM. This might be a simplification but ensures that bit errors are uncorrelated across blocks. Injecting bit errors in activations in PyTorch boils down to computing $\tilde{a}_l = Q^{-1}(\text{BErr}_p(Q(a_l)))$ after each block l (marked by * in Tab. A). When training with bit errors in activations, we use the straight-through estimator to compute gradients.

Bit Errors in Inputs: Tab. N presents results against random bit errors in inputs (orange). We report RErr for

bit error rates $p = 0.1\%$ and $p = 0.5\%$. We emphasize that in these experiments the weights are *not* subject to random bit errors. Nevertheless, bit errors in the inputs can be devastating, resulting in RErr above 20% for CLIPPING and PLCLIPPING with $p = 0.5\%$. While 0.5% does not seem like much, it is important to remember that effectively $0.5 \cdot 8 = 4\%$ of pixels are affected. Also, more extreme clipping does result in higher RErr, showing that robustness in weights and inputs might be contradictory to some extent. Similarly, RANDBET on bit errors in weights does *not* improve robustness. RANDBET on bit errors in weights and inputs, in contrast, can reduce RErr considerably.

Bit Errors in Activations: Tab. O shows results for random bit errors in activations (violet). As, by default, we do *not* train with activation quantization, we report Err w/ and w/o activation quantization (in $m = 8$ bits). As can be seen, our simple activation quantization leads to a slight increase of 0.2 to 0.3% in Err. Bit errors in activations turn out to be difficult to handle, even for CLIPPING and PLCLIPPING. In contrast to bit errors in inputs, weight clipping has a positive effect on robustness against bit errors in activations. However, the benefit is less pronounced than for bit errors in weights, e.g., PLCLIPPING does not improve over CLIPPING. Similarly, RANDBET with bit errors in weights can improve robustness, but does not so consistently, see the variations in RErr for RANDBET (weights only) in tabreftab:supp-activations. RANDBET with bit errors in activations, in contrast, has the expected effect of reducing RErr considerably, allowing reasonably low RErr for $p = 0.1\%$.

I.10 Adversarial Bit Error Robustness

Bit Flip Attack (BFA): Tab. P reports additional experimental results for the BFA attack proposed in [11]. Our

TABLE Q: **Adversarial Bit Error Ablation on MNIST and CIFAR10.** (Worst) RErr for various models on MNIST and CIFAR10 against our adversarial bit error attack with ϵ allowed bit errors. For CIFAR10, we consider an MNIST-like architecture (cf. Tab. A), a model with halved channels, and the model as used in the main paper. We report worst RErr across all attacks and restarts as well as individually for: attacking all weights, attacking only **logit** layer, attacking only the first **convolutional** layer, attacking only both logit and conv1 layer (“**l+c**”) and attacking all layers except logit and conv1 (“*****”). In all cases, we consider targeted or untargeted attacks. Just because the first convolutional layer for the MNIST-like model on CIFAR10 has $3\times$ more weights, CLIPPING_{0.05} is significantly more robust for $\epsilon=160$. This is emphasized when considering the slightly larger “halved channels” model and can be confirmed using a ResNet-20. Across all datasets, attacking logit or conv1 layer is highly effective. Only ADVBET is able to reduce the vulnerability of these layers.

MNIST		Worst RErr in %											
	Err in %	$\epsilon=80$	$\epsilon=160$										
$W\approx 1\text{Mio}$		(all U+T)	(all U+T)	U (all)	T (all)	U (log)	T (log)	U (conv)	T (conv)	U (l+c)	T (l+c)	U (*)	T (*)
RQUANT	0.37	91.08	91.08	0.48	0.51	89.86	91.08	85.42	84.27	89.86	91.08	0.48	0.48
CLIPPING _{0.05}	0.38	1.00	85.09	2.30	0.74	10.77	0.72	83.09	85.09	9.90	0.90	0.39	0.41
ADVBET _{0.05, $\epsilon=160$}	0.29	0.33	10.37	10.37	0.36	10.03	0.37	0.40	0.47	0.36	0.41	0.29	0.29
CIFAR10		Worst RErr in %											
	Err in %	$\epsilon=160$	$\epsilon=320$										
<i>like MNIST</i> $W\approx 1\text{Mio}$		(all U+T)	(all U+T)	U (all)	T (all)	U (log)	T (log)	U (conv)	T (conv)	U (l+c)	T (l+c)	U (*)	T (*)
RQUANT	6.63	91.49	91.49	61.34	91.49	90.42	91.49	86.91	86.46	90.42	91.49	37.77	45.56
CLIPPING _{0.05}	7.31	50.40	75.40	59.74	70.16	59.21	75.40	60.16	64.91	58.91	68.43	8.44	10.01
<i>half channels</i> $W\approx 1.3\text{Mio}$	Err in %	$\epsilon=160$	$\epsilon=320$										
		(all U+T)	(all U+T)	U (all)	T (all)	U (log)	T (log)	U (conv)	T (conv)	U (l+c)	T (l+c)	U (*)	T (*)
RQUANT	6.67	91.58	91.58	46.96	91.58	90.44	91.58	87.46	87.78	90.44	91.58	53.96	52.46
CLIPPING _{0.05}	7.79	37.47	82.80	58.22	82.60	54.61	82.80	64.96	62.26	53.50	82.59	8.32	9.69
CLIPPING _{0.05} (ResNet-20)	7.30	38.91	64.72	35.19	35.57	43.96	62.37	47.94	55.60	45.53	64.72	8.19	8.94
<i>full channels</i> $W\approx 5.5\text{Mio}$	Err in %	$\epsilon=160$	$\epsilon=320$										
		(all U+T)	(all U+T)	U (all)	T (all)	U (log)	T (log)	U (conv)	T (conv)	U (l+c)	T (l+c)	U (*)	T (*)
RQUANT	4.89	91.18	91.18	8.54	91.18	90.68	91.18	86.28	89.06	90.68	91.18	6.73	7.46
CLIPPING _{0.05}	5.34	20.48	60.76	24.04	35.20	23.67	35.86	52.57	60.76	25.27	35.86	5.80	5.61
ADVBET _{0.05, $\epsilon=160$}	5.54	15.20	26.22	10.01	20.20	25.70	26.22	8.84	12.33	8.91	25.47	5.82	6.18

experimental setup is described in detail in Sec. H. We report the average number of bit flips required by BFA in order to increase RErr to 90% or above (i.e., reduce performance to random guessing, as also used in [11]). Furthermore, we report the standard deviation across these 5 restarts. As shown, BFA requires significantly more bit flips ϵ_{BFA} to break our models than reported in [11]. We believe that this is mainly due to [11] relying on batch normalization (BN) [56] in their ResNet models. In contrast, we use group normalization (GN) [55]. On CIFAR10, we demonstrate that using BN reduces robustness significantly, i.e., far fewer bit flips are required to achieve $\text{RErr} \geq 90\%$. Furthermore, our CLIPPING, RANDBET or ADVBET model, specifically trained to be robust against random or adversarial bit errors, improve robustness significantly. On MNIST, more than 1k and on CIFAR10 more than 2k bit flips are required.

Adversarial Bit Error Attack: Tab. Q presents a comprehensive ablation study regarding our adversarial bit error attack. We report RErr on MNIST and CIFAR10, considering an additional MNIST-like architecture and an architecture with “halved channels” on CIFAR10. Specifically, considering Tab. A, the MNIST-like architecture is the same architecture as used for MNIST, but using a larger first convolutional layer (conv1) due to the larger input dimensionality on CIFAR10. Specifically, the number of weights in conv1 increase from 288 to 864 (factor 3 due to 3 input channels on CIFAR10). Then, we consider the CIFAR10 architecture but with all channel widths halved (similar to MNIST). These two architecture result in roughly 1Mio and 1.3Mio weights. While attacks on all weights (targeted or untargeted) are not very effective on MNIST, compared to attacks on conv1

or logit layer, the models on CIFAR10 are more vulnerable in this regard, specially RQUANT. However, even on CIFAR10, the conv1 and logit layers are most susceptible to bit errors. Attacking all *other* layers (i.e., all layers except conv1 and logit), in contrast, is not very fruitful in terms of increasing RErr, especially considering CLIPPING. Only ADVBET is able to reduce the vulnerability of these layers. Interestingly, CLIPPING_{0.05} is more robust on CIFAR10, even when using the MNIST-like architecture. Here, for $\epsilon=160$, RErr is 58.09% on MNIST but only 50.4% on CIFAR10. As the only difference between both models is the larger first convolutional layer conv1 on CIFAR10, this further supports our experiments showing that conv1 is particularly vulnerable. In all cases, targeted attacks are more successful. This is also illustrated in Fig. G showing loss and RErr over iterations for the half channels model on CIFAR10. As in the main paper, proper L_∞ gradient normalization and momentum make the attack more effective. However, the targeted attack is most effective and less prone to poor local minima (i.e., does rarely get stuck during optimization).

Overall Results: Tab. R summarizes our results against adversarial bit errors: We report RErr against RQUANT, CLIPPING, RANDBET and ADVBET. On MNIST, we consider various variants of ADVBET: training with or without using momentum (0.9) in the attack and training against targeted attacks (random target label in each iteration). As demonstrated in Tab. Q, targeted attacks are generally easier to optimize and more successful. Thus, ADVBET with targeted attack outperforms training with untargeted attacks. On CIFAR10, we present results for ADVBET trained with larger ϵ . Unfortunately, using larger ϵ does not increase

TABLE R: **Adversarial Bit Error Robustness on MNIST and CIFAR10.** Complementing the results from the main paper, we report RErr for RQUANT, CLIPPING RANDBET and ADVBET on MNIST and CIFAR10. We evaluate adversarial bit error robustness for various ϵ and also train ADVBET with different ϵ . On MNIST, we also present an ablation when training ADVBET against attacks with or without momentum 0.9 or with targeted attack (“T”). As targeted attacks are generally more effective, this also helps improve robustness using ADVBET. On CIFAR10, we found ADVBET with $\epsilon > 160$ to reduce robustness. We suspect that training gets more difficult and might require additional capacity or more sophisticated training schemes.

	Err %	RErr in %			
MNIST		$\epsilon=80$	$\epsilon=160$	$\epsilon=240$	$\epsilon=320$
RQUANT	0.37	91.08	91.08	91.08	91.08
CLIPPING _{0.05}	0.38	85.09	88.81	90.11	90.26
RANDBET _{0.05, p=20}	0.39	10.13	69.90	81.16	81.94
ADVBET _{0.05, $\epsilon=160$}	0.33	11.63	21.08	31.71	61.01
ADVBET _{0.05, $\epsilon=240$}	0.32	66.92	82.83	85.12	87.98
ADVBET _{0.05, $\epsilon=320$}	0.27	10.41	85.73	85.57	88.12
ADVBET _{0.05 (mom 0.9), $\epsilon=160$}	0.29	10.37	86.12	84.83	87.28
ADVBET _{0.05 (mom 0.9), $\epsilon=240$}	0.29	11.58	21.66	41.27	50.73
ADVBET _{0.05 (mom 0.9), $\epsilon=320$}	0.30	10.38	21.76	39.92	69.61
ADVBET _{0.05 T, $\epsilon=160$}	0.39	10.54	21.41	29.72	49.77
ADVBET _{0.05 T, $\epsilon=240$}	0.36	10.10	19.44	31.23	51.01
ADVBET _{0.05 T, $\epsilon=320$}	0.36	10.51	19.72	31.28	50.77
CIFAR10		$\epsilon=160$	$\epsilon=320$	$\epsilon=480$	$\epsilon=640$
RQUANT	4.89	91.18	91.18	91.18	91.18
CLIPPING _{0.05}	5.34	20.48	60.76	79.12	83.93
RANDBET _{0.05, p=2}	5.42	14.66	33.86	54.24	80.36
ADVBET _{0.05, $\epsilon=160$}	5.54	15.20	26.22	55.06	77.43
ADVBET _{0.05, $\epsilon=320$}	5.78	15.27	42.79	70.56	91.13
ADVBET _{0.05, $\epsilon=480$}	5.99	15.41	44.66	83.39	91.47
ADVBET _{0.05, $\epsilon=640$}	6.49	15.90	33.79	70.61	90.48

robustness. We suspect that training with large ϵ , e.g., 320, is significantly more difficult. That is, our model might lack capacity or more sophisticated training schemes are necessary. As result, (clean) Err increases, while robustness does not further improve or even decreases.

TABLE S: **Overall Robustness Results on CIFAR10.** Tabular results corresponding to Fig. F for $m = 8, 4, 3$ and 2 bits. We show RErr for NORMAL, CLIPPING and RANDBET with various w_{\max} and p across a subset of evaluated bit error rates. Results with per-layer weight clipping can be found in Tab. T.

		CIFAR10								
Model		Err in %	RErr in %, p in % $p=0.01$							
			0.01	0.05	0.1	0.5	1	1.5	2	2.5
$m = 8$ bit	NORMAL	4.36	4.82	5.51	6.37	24.76	72.65	87.40	89.76	90.15
	RQUANT	4.32	4.60	5.10	5.54	11.28	32.05	68.65	85.28	89.01
	CLIPPING _{0.25}	4.58	4.84	5.29	5.71	10.52	27.95	62.46	82.61	88.08
	CLIPPING _{0.2}	4.63	4.91	5.28	5.62	8.27	18.00	53.74	82.02	88.27
	CLIPPING _{0.15}	4.42	4.66	5.01	5.31	7.81	13.08	23.85	42.12	61.20
	CLIPPING _{0.1}	4.82	5.04	5.33	5.58	6.95	8.93	12.22	17.80	27.02
	CLIPPING _{0.05}	5.44	5.59	5.76	5.90	6.53	7.18	7.92	8.70	9.56
	CLIPPING _{0.025}	7.10	7.20	7.32	7.40	7.82	8.18	8.43	8.74	-
	RANDBET ₁ $p=0.01$	4.56	4.93	5.50	6.06	14.14	66.07	86.86	89.80	90.35
	RANDBET ₁ $p=0.1$	4.50	4.80	5.27	5.72	10.33	41.10	75.90	86.52	89.03
	RANDBET ₁ $p=1$	7.38	7.69	8.17	8.58	11.10	14.90	21.08	41.11	71.09
	RANDBET _{0.2} $p=0.01$	4.44	4.67	5.09	5.48	8.64	17.97	41.53	68.95	82.48
	RANDBET _{0.2} $p=0.1$	4.51	4.73	5.07	5.39	7.99	19.21	54.94	80.12	86.55
	RANDBET _{0.2} $p=1$	5.46	5.68	5.97	6.20	7.63	9.47	12.38	21.47	50.86
	RANDBET _{0.15} $p=0.01$	4.64	4.87	5.17	5.45	7.54	15.83	54.07	81.41	86.75
	RANDBET _{0.15} $p=0.1$	4.86	5.07	5.36	5.64	7.74	12.33	22.38	40.09	60.78
	RANDBET _{0.15} $p=1$	5.27	5.44	5.68	5.88	7.11	8.63	11.13	27.74	64.97
	RANDBET _{0.1} $p=0.01$	4.99	5.15	5.39	5.62	6.93	9.01	12.83	22.81	41.04
	RANDBET _{0.1} $p=0.1$	4.72	4.92	5.15	5.37	6.74	8.53	11.40	15.97	23.59
	RANDBET _{0.1} $p=1$	4.90	5.05	5.26	5.43	6.36	7.41	8.65	12.25	27.21
	RANDBET _{0.1} $p=1.5$	5.53	5.67	5.87	6.03	6.84	7.76	8.80	10.03	11.68
	RANDBET _{0.1} $p=2$	5.71	5.87	6.07	6.22	7.00	7.83	8.69	9.70	10.91
	RANDBET _{0.05} $p=0.1$	5.32	5.41	5.59	5.72	6.34	6.96	7.62	8.28	9.13
	RANDBET _{0.05} $p=1$	5.24	5.36	5.50	5.60	6.18	6.73	7.26	7.88	8.49
RANDBET _{0.05} $p=1.5$	5.62	5.71	5.84	5.95	6.50	7.02	7.52	7.97	8.51	
RANDBET _{0.05} $p=2$	5.42	5.55	5.68	5.78	6.26	6.71	7.13	7.58	8.02	
RANDBET _{0.025} $p=1$	6.78	6.88	7.00	7.08	7.46	7.75	8.02	8.24	8.47	
RANDBET _{0.025} $p=1.5$	6.89	6.99	7.11	7.19	7.58	7.94	8.26	8.52	8.77	
RANDBET _{0.025} $p=2$	6.93	7.02	7.12	7.20	7.57	7.87	8.11	8.33	8.58	
RANDBET _{0.025} $p=2.5$	6.91	6.99	7.08	7.14	7.50	7.83	8.10	8.36	8.63	
$m = 4$ bit	RQUANT	4.83	5.29	5.98	6.59	15.72	50.45	79.86	87.17	89.47
	CLIPPING _{0.25}	4.78	5.16	5.75	6.26	12.08	30.62	60.52	80.07	87.01
	CLIPPING _{0.2}	4.90	5.20	5.65	6.04	9.67	27.24	63.96	82.63	87.21
	CLIPPING _{0.15}	4.78	5.07	5.43	5.79	8.40	14.61	28.53	50.83	70.32
	CLIPPING _{0.1}	5.29	5.49	5.75	5.99	7.71	10.62	15.79	24.97	37.94
	CLIPPING _{0.05}	5.78	5.92	6.08	6.21	6.98	7.86	8.77	9.76	11.04
	RANDBET _{0.2} $p=0.01$	5.14	5.42	5.85	6.23	10.44	23.84	49.25	73.35	83.16
	RANDBET _{0.2} $p=0.1$	4.77	5.01	5.41	5.76	8.66	16.06	32.40	56.69	75.21
	RANDBET _{0.2} $p=1$	6.27	6.52	6.86	7.12	8.78	11.33	15.17	21.43	32.19
	RANDBET _{0.15} $p=0.01$	4.88	5.13	5.54	5.92	8.51	14.21	26.26	46.02	66.13
	RANDBET _{0.15} $p=0.1$	4.50	4.72	5.05	5.36	7.58	14.12	43.00	76.28	85.54
	RANDBET _{0.15} $p=1$	5.99	6.18	6.45	6.65	8.00	9.74	12.50	16.73	24.09
	RANDBET _{0.1} $p=0.01$	5.07	5.29	5.58	5.83	7.54	10.46	15.34	24.63	39.76
	RANDBET _{0.1} $p=0.1$	4.82	5.04	5.32	5.53	6.82	8.85	12.48	21.36	40.03
	RANDBET _{0.1} $p=1$	5.39	5.55	5.77	5.96	7.04	8.34	9.77	11.85	14.91
	RANDBET _{0.05} $p=0.1$	5.14	5.26	5.46	5.61	6.38	7.19	8.06	9.16	10.46
	RANDBET _{0.05} $p=1$	5.60	5.71	5.85	5.97	6.54	7.10	7.68	8.28	8.99
	RANDBET _{0.05} $p=1.5$	5.51	5.64	5.77	5.87	6.38	6.98	7.51	8.10	8.72
RANDBET _{0.05} $p=2$	5.49	5.62	5.77	5.90	6.43	6.99	7.53	8.06	8.62	
$m = 3$ bit	RQUANT	79.59	83.95	88.57	91.07	96.15	97.81	98.20	98.60	99.07
	CLIPPING _{0.25}	6.89	7.34	8.00	8.65	14.46	28.70	53.64	75.51	85.13
	CLIPPING _{0.2}	5.82	6.21	6.79	7.30	11.90	23.31	43.00	65.68	78.79
	CLIPPING _{0.15}	5.84	6.16	6.60	6.95	9.95	15.92	27.84	47.54	67.08
	CLIPPING _{0.1}	5.71	6.01	6.39	6.73	8.99	13.06	20.88	35.13	51.76
	CLIPPING _{0.05}	5.61	5.78	6.01	6.19	7.07	8.13	9.34	10.95	13.16
	RANDBET _{0.2} $p=0.01$	5.72	6.14	6.77	7.30	12.84	26.46	50.52	72.46	83.09
	RANDBET _{0.2} $p=0.1$	6.23	6.55	7.04	7.53	11.38	21.36	41.93	65.54	79.94
	RANDBET _{0.2} $p=1$	7.61	7.84	8.20	8.52	10.30	12.82	16.65	21.81	29.64
	RANDBET _{0.15} $p=0.01$	5.61	5.94	6.40	6.77	9.59	15.72	28.06	46.88	64.39
	RANDBET _{0.15} $p=0.1$	5.33	5.56	5.99	6.33	9.01	14.06	23.44	40.36	59.92
	RANDBET _{0.15} $p=1$	7.26	7.52	7.82	8.07	9.58	11.47	13.87	17.58	23.01
	RANDBET _{0.1} $p=0.01$	5.13	5.41	5.72	6.00	8.06	11.25	17.22	26.96	42.72
	RANDBET _{0.1} $p=0.1$	5.69	5.96	6.26	6.51	8.04	10.81	15.51	23.88	37.52
	RANDBET _{0.1} $p=1$	5.76	5.95	6.22	6.44	7.59	8.97	10.76	13.21	16.95
	RANDBET _{0.05} $p=0.01$	5.50	5.62	5.83	5.99	6.83	7.79	9.05	10.48	12.32
	RANDBET _{0.05} $p=0.1$	5.44	5.58	5.76	5.90	6.72	7.60	8.60	9.92	11.70
	RANDBET _{0.05} $p=1$	5.57	5.69	5.87	6.01	6.68	7.38	8.08	8.96	9.96
$m = 2$ bit	RQUANT	88.68	89.53	91.62	93.23	97.74	98.40	97.85	99.20	98.74
	CLIPPING _{0.25}	90.14	90.54	91.13	91.82	95.96	96.90	97.21	96.66	97.12
	CLIPPING _{0.2}	82.00	84.86	90.79	94.17	97.25	96.69	97.16	97.73	97.01
	CLIPPING _{0.15}	14.62	15.29	16.30	17.16	22.88	33.18	50.86	71.17	84.30
	CLIPPING _{0.1}	7.87	8.29	8.93	9.57	13.95	23.65	42.43	64.65	80.89
	CLIPPING _{0.05}	6.59	6.78	7.05	7.26	8.55	10.26	12.73	15.99	20.51
	CLIPPING _{0.025}	6.94	7.06	7.23	7.34	7.96	8.57	9.16	9.77	10.47
	RANDBET _{0.05} $p=0.01$	6.00	6.21	6.47	6.66	7.88	9.51	11.53	14.99	19.60
	RANDBET _{0.05} $p=0.1$	5.83	6.04	6.30	6.52	7.73	9.32	11.41	14.49	19.77
	RANDBET _{0.025} $p=0.01$	6.93	7.07	7.24	7.37	8.05	8.65	9.23	9.72	10.43
	RANDBET _{0.025} $p=0.1$	7.02	7.13	7.31	7.41	7.98	8.48	9.00	9.65	10.32
	RANDBET _{0.025} $p=1$	7.10	7.23	7.38	7.49	8.10	8.65	9.14	9.54	10.07

TABLE T: **Overall Robustness Results on CIFAR10.** Tabular results corresponding to Fig. F for $m = 8$ and 4 bits. We show RErr for PLCLIPPING and PLRANDBET with various w_{\max} and p across a subset of evaluated bit error rates. Results for $m = 3, 2$ in Tab. U.

CIFAR10: results with per-layer weight clipping for $m = 8, 4$ bit										
	Model	Err in %	RErr in %, p in % $p=0.01$							
			0.01	0.05	0.1	0.5	1	1.5	2	2.5
$m = 8$ bit	PLCLIPPING ₁	4.38	4.69	5.16	5.61	10.73	27.53	58.40	80.65	87.61
	PLCLIPPING _{0.5}	4.61	4.89	5.21	5.48	7.39	10.90	20.05	38.24	60.01
	PLCLIPPING _{0.25}	4.96	-	5.25	5.39	6.21	7.04	8.14	9.36	10.88
	PLCLIPPING _{0.2}	4.71	4.88	5.07	5.20	5.86	6.53	7.20	7.88	8.79
	PLCLIPPING _{0.15}	5.27	5.38	5.51	5.60	6.09	6.52	6.99	7.43	7.94
	PLCLIPPING _{0.1}	5.62	5.72	5.81	5.91	6.31	6.65	6.92	7.18	7.46
	PLCLIPPING _{0.05}	7.23	7.32	7.43	7.50	7.88	8.13	8.35	8.58	8.75
	PLRANDBET _{0.75} $p=0.01$	4.20	4.45	4.90	5.23	8.13	16.73	40.38	69.40	83.09
	PLRANDBET _{0.5} $p=0.01$	4.59	4.85	5.19	5.46	7.37	11.06	17.77	29.32	45.72
	PLRANDBET _{0.4} $p=0.01$	4.49	4.67	4.96	5.20	6.68	8.88	12.37	19.06	29.74
	PLRANDBET _{0.3} $p=0.01$	4.52	4.66	4.86	5.06	6.15	7.49	9.28	11.87	15.43
	PLRANDBET _{0.25} $p=0.01$	4.83	5.00	5.16	5.29	6.01	6.90	7.87	9.11	10.79
	PLRANDBET _{0.75} $p=0.1$	4.57	4.78	5.15	5.47	8.02	13.39	26.01	49.54	71.45
	PLRANDBET _{0.5} $p=0.1$	4.48	4.72	5.07	5.33	7.09	10.12	14.90	25.54	39.41
	PLRANDBET _{0.4} $p=0.1$	4.43	4.64	4.93	5.18	6.48	8.40	11.39	16.36	24.36
	PLRANDBET _{0.3} $p=0.1$	4.54	4.67	4.87	5.02	5.96	7.09	8.47	10.13	12.89
	PLRANDBET _{0.25} $p=0.1$	4.49	4.62	4.82	4.98	5.80	6.65	7.59	8.72	10.36
	PLRANDBET _{0.2} $p=0.1$	4.90	5.02	5.21	5.36	6.05	6.72	7.40	8.14	9.02
	PLRANDBET _{0.15} $p=0.1$	5.10	5.21	5.35	5.46	5.97	6.43	6.84	7.23	7.67
	PLRANDBET _{0.5} $p=1$	5.11	5.27	5.52	5.73	6.89	8.30	10.25	13.04	17.35
	PLRANDBET _{0.4} $p=1$	4.80	4.94	5.15	5.31	6.24	7.31	8.61	10.51	13.78
	PLRANDBET _{0.3} $p=1$	4.86	4.98	5.13	5.27	6.01	6.82	7.70	8.80	10.05
	PLRANDBET _{0.25} $p=1$	4.62	4.73	4.90	5.02	5.62	6.36	7.02	7.79	8.76
	PLRANDBET _{0.2} $p=1$	4.92	5.02	5.15	5.25	5.78	6.29	6.76	7.26	7.89
	PLRANDBET _{0.15} $p=1$	5.10	5.19	5.31	5.41	5.87	6.28	6.70	7.02	7.45
	PLRANDBET _{0.1} $p=1$	5.66	5.76	5.88	5.96	6.29	6.59	6.87	7.11	7.34
	PLRANDBET _{0.25} $p=2$	4.94	5.06	5.22	5.33	5.92	6.48	7.04	7.59	8.25
	PLRANDBET _{0.2} $p=2$	5.02	5.12	5.24	5.33	5.85	6.30	6.74	7.18	7.62
	PLRANDBET _{0.15} $p=2$	4.99	5.08	5.20	5.29	5.74	6.12	6.49	6.80	7.15
	PLRANDBET _{0.1} $p=2$	5.60	5.67	5.77	5.84	6.20	6.49	6.72	6.95	7.19
PLRANDBET _{0.25} $p=3$	5.46	5.56	5.69	5.77	6.29	6.84	7.26	7.74	8.25	
PLRANDBET _{0.2} $p=3$	5.13	5.21	5.34	5.43	5.92	6.26	6.71	7.05	7.41	
PLRANDBET _{0.15} $p=3$	5.21	5.29	5.39	5.47	5.87	6.18	6.49	6.75	7.06	
PLRANDBET _{0.1} $p=3$	5.84	5.89	5.99	6.06	6.42	6.71	6.94	7.18	7.36	
PLRANDBET _{0.05} $p=3$	7.57	7.63	7.73	7.80	8.13	8.38	8.61	8.78	8.98	
$m = 4$ bit	PLCLIPPING ₁	4.93	5.31	5.87	6.37	12.35	33.07	62.83	80.24	87.59
	PLCLIPPING _{0.75}	4.66	4.96	5.43	5.85	9.59	20.57	44.09	69.93	82.21
	PLCLIPPING _{0.5}	4.58	4.82	5.16	5.45	7.62	12.25	21.01	37.48	60.24
	PLCLIPPING _{0.4}	4.87	5.04	5.35	5.59	7.18	9.67	14.06	22.08	35.51
	PLCLIPPING _{0.3}	4.59	4.75	4.97	5.17	6.31	7.73	9.65	12.86	18.05
	PLCLIPPING _{0.25}	4.63	4.79	5.01	5.20	6.15	7.34	8.70	10.70	13.49
	PLCLIPPING _{0.1}	5.59	5.68	5.80	5.89	6.32	6.69	7.06	7.46	7.75
	PLCLIPPING _{0.05}	7.63	7.74	7.84	7.94	8.30	8.62	8.88	9.16	9.40
	PLRANDBET _{0.75} $p=0.01$	4.63	4.94	5.43	5.90	9.67	20.90	45.58	72.21	82.73
	PLRANDBET _{0.5} $p=0.01$	4.69	4.94	5.31	5.60	7.63	12.50	23.41	42.24	63.73
	PLRANDBET _{0.4} $p=0.01$	4.79	5.01	5.27	5.47	7.12	10.10	14.98	23.01	35.11
	PLRANDBET _{0.3} $p=0.01$	4.87	5.02	5.26	5.45	6.64	8.14	10.11	13.11	17.71
	PLRANDBET _{0.25} $p=0.01$	4.90	5.04	5.23	5.40	6.32	7.44	8.73	10.41	12.68
	PLRANDBET _{0.5} $p=0.1$	5.29	5.52	5.90	6.22	8.47	12.65	20.36	33.56	51.59
	PLRANDBET _{0.4} $p=0.1$	4.81	5.05	5.34	5.60	7.26	9.98	14.48	21.85	33.04
	PLRANDBET _{0.3} $p=0.1$	4.84	5.00	5.25	5.44	6.54	7.88	9.86	12.47	16.31
	PLRANDBET _{0.25} $p=0.1$	4.89	5.02	5.24	5.39	6.33	7.27	8.52	10.09	12.24
	PLRANDBET _{0.2} $p=0.1$	4.69	4.80	4.95	5.07	5.72	6.41	7.18	8.07	9.09
	PLRANDBET _{0.25} $p=1$	4.83	4.94	5.10	5.24	5.95	6.65	7.48	8.45	9.58
	PLRANDBET _{0.2} $p=1$	4.96	5.10	5.24	5.35	5.97	6.60	7.17	7.83	8.64
	PLRANDBET _{0.15} $p=1$	5.18	5.27	5.41	5.50	5.97	6.41	6.82	7.23	7.70
	PLRANDBET _{0.1} $p=1$	5.81	5.89	6.00	6.10	6.52	6.88	7.20	7.52	7.86
	PLRANDBET _{0.2} $p=2$	5.42	5.53	5.64	5.74	6.19	6.65	7.10	7.63	8.23
	PLRANDBET _{0.15} $p=2$	5.31	5.43	5.57	5.68	6.14	6.54	6.91	7.23	7.67
	PLRANDBET _{0.1} $p=2$	5.69	5.78	5.91	6.00	6.37	6.68	6.98	7.27	7.56
	PLRANDBET _{0.2} $p=3$	5.20	5.32	5.44	5.55	6.00	6.41	6.82	7.22	7.70
	PLRANDBET _{0.15} $p=3$	5.42	5.51	5.63	5.73	6.11	6.51	6.87	7.21	7.51
	PLRANDBET _{0.1} $p=3$	6.04	6.11	6.23	6.31	6.67	6.97	7.26	7.53	7.81

TABLE U: **Overall Robustness Results on CIFAR10.** Continued from Tab. T. Tabular results corresponding to Fig. F for $m = 3$ and 2 bits. We show RErr for PLCLIPPING and PLRANDBET with various w_{\max} and p across a subset of evaluated bit error rates.

CIFAR10: results with per-layer weight clipping for $m = 3, 2$ bit										
	Model	Err in %	RErr in %, p in % $p=0.01$							
			0.01	0.05	0.1	0.5	1	1.5	2	2.5
$m = 3$ bit	PLCLIPPING ₁	6.34	6.75	7.40	8.02	13.31	26.54	49.60	72.07	83.24
	PLCLIPPING _{0.75}	5.69	6.04	6.58	7.14	11.34	23.23	44.63	67.71	80.39
	PLCLIPPING _{0.5}	5.21	5.46	5.87	6.21	8.66	13.42	21.82	36.08	54.85
	PLCLIPPING _{0.25}	5.08	5.29	5.58	5.91	7.73	10.82	16.32	26.57	40.63
	PLCLIPPING _{0.2}	4.81	4.98	5.17	5.37	6.72	10.14	19.80	40.39	64.79
	PLCLIPPING _{0.15}	5.21	5.37	5.59	5.76	6.78	8.16	10.00	12.70	16.80
	PLCLIPPING _{0.1}	6.02	6.10	6.22	6.31	6.76	7.20	7.61	8.01	8.46
	PLCLIPPING _{0.05}	7.54	7.65	7.79	7.91	8.42	8.83	9.20	9.50	9.84
	PLRANDBET _{0.75} $p=0.01$	6.38	6.77	7.30	7.88	12.26	22.93	41.96	64.96	78.82
	PLRANDBET _{0.5} $p=0.01$	5.23	5.51	5.90	6.26	8.50	12.72	20.99	36.41	55.51
	PLRANDBET _{0.4} $p=0.01$	5.07	5.30	5.62	5.94	7.88	11.48	17.38	28.41	42.84
	PLRANDBET _{0.3} $p=0.01$	4.98	5.16	5.39	5.58	6.80	8.67	11.20	15.12	21.41
	PLRANDBET _{0.25} $p=0.01$	4.94	5.09	5.30	5.48	6.49	7.76	9.47	11.97	16.02
	PLRANDBET _{0.5} $p=0.1$	5.24	5.55	5.93	6.24	8.33	12.73	20.74	36.59	55.12
	PLRANDBET _{0.4} $p=0.1$	5.12	5.34	5.63	5.89	7.62	10.66	16.12	25.76	39.06
	PLRANDBET _{0.3} $p=0.1$	5.08	5.28	5.52	5.73	6.95	8.73	11.37	15.61	22.20
	PLRANDBET _{0.25} $p=0.1$	5.12	5.28	5.52	5.71	6.70	7.98	9.61	11.93	15.23
	PLRANDBET _{0.2} $p=0.1$	5.29	5.45	5.60	5.73	6.48	7.40	8.31	9.46	11.02
	PLRANDBET _{0.25} $p=1$	5.22	5.39	5.59	5.75	6.55	7.46	8.38	9.47	10.96
	PLRANDBET _{0.2} $p=1$	5.32	5.47	5.63	5.78	6.40	7.03	7.69	8.42	9.32
	PLRANDBET _{0.15} $p=1$	5.28	5.37	5.51	5.63	6.19	6.76	7.29	7.89	8.46
	PLRANDBET _{0.1} $p=1$	5.67	5.74	5.84	5.92	6.36	6.75	7.12	7.48	7.87
	PLRANDBET _{0.2} $p=2$	5.32	5.45	5.57	5.69	6.24	6.83	7.36	8.00	8.68
	PLRANDBET _{0.15} $p=2$	5.32	5.45	5.59	5.69	6.18	6.58	7.03	7.46	7.88
	PLRANDBET _{0.1} $p=2$	5.97	6.04	6.13	6.22	6.65	6.99	7.31	7.69	8.06
	PLRANDBET _{0.05} $p=2$	7.62	7.70	7.78	7.85	8.21	8.51	8.75	9.01	9.26
	PLRANDBET _{0.2} $p=3$	5.63	5.74	5.85	5.94	6.40	6.83	7.25	7.72	8.20
	PLRANDBET _{0.15} $p=3$	5.46	5.56	5.69	5.77	6.25	6.65	7.02	7.36	7.75
	PLRANDBET _{0.1} $p=3$	6.14	6.25	6.38	6.48	6.86	7.20	7.47	7.79	8.07
	PLRANDBET _{0.05} $p=3$	7.60	7.67	7.76	7.84	8.22	8.54	8.77	8.99	9.23
$m = 2$ bit	PLCLIPPING ₁	90.02	94.01	98.97	98.94	99.57	99.19	99.40	99.23	99.00
	PLCLIPPING _{0.75}	66.16	67.94	71.39	74.31	85.34	91.21	93.56	95.35	95.92
	PLCLIPPING _{0.5}	9.98	10.42	11.16	11.86	17.37	30.49	51.27	71.19	83.54
	PLCLIPPING _{0.25}	8.10	8.54	9.17	9.74	14.12	21.93	36.88	55.20	73.57
	PLCLIPPING _{0.2}	6.66	6.92	7.31	7.64	10.21	14.50	22.09	34.82	50.34
	PLCLIPPING _{0.15}	6.08	6.35	6.66	6.96	8.65	11.43	15.87	22.66	33.32
	PLCLIPPING _{0.1}	6.02	6.15	6.30	6.41	7.00	7.51	8.06	8.65	9.33
	PLCLIPPING _{0.05}	7.52	7.62	7.76	7.87	8.45	8.95	9.41	9.87	10.35
	PLRANDBET _{0.75} $p=0.01$	20.74	21.63	23.09	24.25	33.17	46.33	62.06	76.96	85.40
	PLRANDBET _{0.5} $p=0.01$	10.22	10.79	11.56	12.21	17.29	28.67	48.03	70.85	83.98
	PLRANDBET _{0.4} $p=0.01$	8.37	8.84	9.43	9.92	13.24	20.07	31.92	51.07	69.03
	PLRANDBET _{0.3} $p=0.01$	6.48	6.81	7.24	7.61	10.04	14.53	22.43	37.15	53.81
	PLRANDBET _{0.25} $p=0.01$	5.81	6.06	6.42	6.68	8.41	11.01	14.90	20.72	30.63
	PLRANDBET _{0.5} $p=0.1$	11.03	11.50	12.23	12.86	16.98	25.83	40.03	60.23	77.68
	PLRANDBET _{0.4} $p=0.1$	7.82	8.18	8.75	9.20	12.65	20.00	35.49	57.15	74.91
	PLRANDBET _{0.3} $p=0.1$	6.17	6.42	6.80	7.15	9.28	13.15	19.52	30.75	49.51
	PLRANDBET _{0.25} $p=0.1$	6.01	6.24	6.54	6.84	8.50	11.05	14.78	21.00	30.41
	PLRANDBET _{0.2} $p=0.1$	5.70	5.88	6.13	6.36	7.44	8.71	10.45	13.06	16.44
	PLRANDBET _{0.25} $p=1$	6.01	6.23	6.48	6.69	7.75	8.88	10.28	12.11	14.71
	PLRANDBET _{0.2} $p=1$	5.82	5.98	6.19	6.35	7.13	8.02	9.00	10.05	11.47
	PLRANDBET _{0.15} $p=1$	5.71	5.85	6.01	6.14	6.81	7.45	8.09	8.77	9.64
	PLRANDBET _{0.1} $p=1$	6.34	6.43	6.55	6.65	7.19	7.67	8.12	8.55	9.07
	PLRANDBET _{0.2} $p=2$	6.09	6.20	6.38	6.54	7.26	7.95	8.66	9.48	10.46
	PLRANDBET _{0.15} $p=2$	6.22	6.37	6.55	6.70	7.29	7.73	8.17	-	-
	PLRANDBET _{0.1} $p=2$	6.18	6.26	6.37	6.46	6.90	7.31	7.71	8.13	8.50
	PLRANDBET _{0.05} $p=2$	7.79	7.89	8.02	8.13	8.61	8.97	9.32	9.65	10.04
	PLRANDBET _{0.05} $p=3$	7.67	7.75	7.88	7.98	8.41	8.81	9.15	9.46	9.74

TABLE V: **Overall Robustness Results on CIFAR100.** Tabular results corresponding to Fig. F for $m = 8$. We show RErr for NORMAL, CLIPPING and RANDBET with various w_{\max} and p across a subset of test bit error rates.

CIFAR100							
Model	Err in %	RErr in %, p in % $p=0.01$					
		0.005	0.01	0.05	0.1	0.5	1
NORMAL	18.21	19.84	20.50	25.05	32.39	97.49	99.10
RQUANT	18.53	19.46	19.95	22.68	25.90	87.24	98.77
CLIPPING _{0.25}	18.88	19.76	20.11	21.89	23.74	62.25	96.62
CLIPPING _{0.2}	18.64	19.36	19.71	21.33	23.07	49.79	94.02
CLIPPING _{0.15}	19.41	20.00	20.24	21.68	23.02	37.85	79.45
CLIPPING _{0.1}	20.31	20.86	21.09	22.14	23.10	31.78	51.71
CLIPPING _{0.05}	21.82	22.16	22.29	22.94	23.46	26.86	31.47
RANDBET _{0.1} $p=0.01$	19.68	20.21	20.46	21.52	22.56	30.59	48.93
RANDBET _{0.1} $p=0.05$	19.94	20.47	20.69	21.72	22.60	29.93	46.76
RANDBET _{0.1} $p=0.1$	19.18	19.67	19.86	20.87	21.69	28.03	41.29
RANDBET _{0.1} $p=0.5$	19.90	20.24	20.41	21.17	21.83	25.66	31.55
RANDBET _{0.1} $p=1$	21.08	21.43	21.59	22.24	22.76	25.73	29.31
RANDBET _{0.05} $p=0.01$	21.86	22.17	22.31	23.00	23.57	26.84	31.33
RANDBET _{0.05} $p=0.05$	20.97	21.30	21.44	22.12	22.72	25.95	30.14
RANDBET _{0.05} $p=0.1$	21.22	21.53	21.66	22.29	22.81	25.88	29.93
RANDBET _{0.05} $p=0.5$	21.29	21.55	21.65	22.13	22.60	25.01	27.70
RANDBET _{0.05} $p=1$	20.83	21.08	21.20	21.73	22.16	24.33	26.49
PLCLIPPING ₁	18.42	19.30	19.66	21.79	24.15	67.32	97.64
PLCLIPPING _{0.75}	19.13	19.80	20.08	21.65	23.27	48.91	92.80
PLCLIPPING _{0.5}	19.32	19.87	20.09	21.28	22.37	32.70	63.37
PLCLIPPING _{0.4}	18.79	19.34	19.58	20.65	21.59	29.08	48.17
PLCLIPPING _{0.3}	19.51	19.89	20.08	20.92	21.69	26.62	34.52
PLCLIPPING _{0.25}	19.06	19.48	19.64	20.35	20.99	24.78	30.88
PLCLIPPING _{0.2}	19.67	20.01	20.14	20.77	21.34	24.35	27.77
PLCLIPPING _{0.15}	20.34	20.54	20.63	21.15	21.56	23.59	25.78
PLCLIPPING _{0.1}	21.49	21.68	21.76	22.16	22.44	23.98	25.37
PLRANDBET _{0.4} $p=0.001$	18.60	19.12	19.35	20.52	21.58	30.06	51.75
PLRANDBET _{0.3} $p=0.001$	19.10	19.60	19.82	20.80	21.60	26.58	34.63
PLRANDBET _{0.25} $p=0.001$	19.68	20.03	20.18	20.91	21.55	25.16	30.52
PLRANDBET _{0.2} $p=1$	19.08	19.30	19.41	19.92	20.35	22.40	24.40
PLRANDBET _{0.15} $p=1$	19.72	19.92	20.01	20.40	20.72	22.35	23.86
PLRANDBET _{0.1} $p=1$	21.04	21.21	21.27	21.60	21.88	23.16	24.26

TABLE W: **Overall Robustness Results on MNIST.** Tabular results corresponding to Fig. F for $m = 8, 4, 2$ bits. We show RErr for NORMAL, CLIPPING and RANDBET with various w_{\max} and p across a subset of test bit error rates. Results for per-layer weight clipping in Tab. X.

MNIST									
	Model	Err in %	RErr in %, p in % $p=0.01$						
			1	5	10	12.5	15	17.5	20
$m = 8$ bit	NORMAL	0.39	0.77	86.37	89.92	89.82	89.81	90.09	90.03
	RQUANT	0.40	0.69	85.96	90.20	89.86	90.10	89.72	89.83
	CLIPPING _{0.1}	0.39	0.48	18.21	88.93	90.35	90.06	90.56	90.18
	CLIPPING _{0.05}	0.42	0.47	0.63	8.67	51.38	80.64	87.79	89.57
	CLIPPING _{0.025}	0.43	0.47	0.56	0.71	0.95	1.81	7.22	32.68
	RANDBET _{0.1} $p=1$	0.36	0.44	3.41	86.29	89.05	89.85	90.10	89.93
	RANDBET _{0.05} $p=1$	0.34	0.39	0.59	8.92	51.32	79.35	87.63	89.15
	RANDBET _{0.05} $p=5$	0.34	0.38	0.50	1.02	5.12	41.31	79.19	87.88
	RANDBET _{0.05} $p=10$	0.40	0.43	0.51	0.67	0.86	1.74	9.77	47.58
	RANDBET _{0.05} $p=15$	0.39	0.40	0.45	0.56	0.64	0.78	1.10	2.72
RANDBET _{0.05} $p=20$	0.39	0.42	0.48	0.53	0.57	0.63	0.74	0.94	
$m = 4$ bit	RQUANT	0.36	0.72	87.21	90.23	90.01	89.88	89.97	89.67
	CLIPPING _{0.1}	0.38	0.51	38.75	88.33	89.47	89.57	90.10	89.67
	CLIPPING _{0.05}	0.31	0.39	0.78	44.15	78.64	87.32	89.03	89.71
	CLIPPING _{0.025}	0.37	0.41	0.50	0.67	0.99	4.63	29.46	67.21
	RANDBET _{0.1} $p=1$	0.38	0.48	13.29	87.43	89.70	89.63	89.41	90.02
	RANDBET _{0.1} $p=5$	0.38	0.48	0.78	24.73	74.88	87.04	88.72	89.55
	RANDBET _{0.1} $p=10$	0.40	0.47	0.64	1.22	2.62	16.72	64.33	83.80
	RANDBET _{0.1} $p=15$	0.56	0.59	0.73	1.03	1.28	1.87	3.71	14.39
	RANDBET _{0.1} $p=20$	0.56	9.48	14.29	7.39	6.07	5.80	6.10	8.12
	RANDBET _{0.05} $p=1$	0.37	0.43	0.67	36.99	77.12	85.97	88.62	89.94
	RANDBET _{0.05} $p=5$	0.38	0.42	0.53	1.38	12.90	60.73	83.69	88.75
	RANDBET _{0.05} $p=10$	0.34	0.39	0.47	0.65	0.91	2.11	19.15	71.25
	RANDBET _{0.05} $p=15$	0.37	0.39	0.43	0.52	0.63	0.79	1.17	3.16
	RANDBET _{0.05} $p=20$	0.44	0.48	0.53	0.60	0.65	0.72	0.86	1.04
$m = 2$ bit	CLIPPING _{0.1}	0.47	3.82	89.19	89.92	90.22	90.14		
	CLIPPING _{0.05}	0.41	0.62	77.19	89.47	90.40	90.06		
	RANDBET _{0.05} $p=3$	0.47	0.53	1.36	82.71	88.66	90.28		
	RANDBET _{0.05} $p=5$	0.40	0.49	0.77	25.72	78.71	88.22		
	RANDBET _{0.05} $p=15$	0.46	0.51	0.60	0.77	0.91	1.21		

TABLE X: **Overall Robustness Results on MNIST.** Tabular results corresponding to Fig. F for $m = 8, 4, 2$ bits for per-layer weight clipping, i.e., PLCLIPPING and PLRANDBET with various w_{\max} and p across a subset of bit error rates.

MNIST: results with per-layer weight clipping							
	Model	Err	RErr in %, p in % $p=0.01$				
		in %	1	5	10	15	20
$m = 8$ bit	PLCLIPPING ₁	0.40	0.88	88.09	90.19	90.21	90.20
	PLCLIPPING _{0.5}	0.37	0.60	77.62	89.70	89.66	89.91
	PLCLIPPING _{0.25}	0.36	0.44	3.87	80.29	89.30	89.52
	PLCLIPPING _{0.2}	0.33	0.42	1.31	48.85	87.60	89.68
	PLCLIPPING _{0.15}	0.39	0.44	0.68	6.31	67.90	88.08
	PLCLIPPING _{0.1}	0.39	0.42	0.52	0.85	5.88	56.97
	PLCLIPPING _{0.05}	0.38	0.41	0.45	0.54	0.77	3.52
	PLRANDBET _{0.2 p=1}	0.34	0.42	0.88	35.33	86.96	89.74
	PLRANDBET _{0.15 p=1}	0.38	0.43	0.65	3.23	58.71	87.13
	PLRANDBET _{0.1 p=1}	0.33	0.42	0.53	0.85	5.71	53.31
	PLRANDBET _{0.2 p=3}	0.37	0.45	0.71	9.03	77.97	89.59
	PLRANDBET _{0.15 p=3}	0.38	0.42	0.57	1.86	43.08	86.21
	PLRANDBET _{0.1 p=3}	0.37	0.40	0.49	0.70	2.60	42.77
	PLRANDBET _{0.2 p=5}	0.36	0.40	0.59	2.83	62.93	87.39
	PLRANDBET _{0.15 p=5}	0.39	0.43	0.57	1.27	25.75	82.66
	PLRANDBET _{0.1 p=5}	0.40	0.44	0.53	0.72	2.00	37.44
	PLRANDBET _{0.05 p=5}	0.36	0.39	0.44	0.52	0.68	1.59
	PLRANDBET _{0.15 p=10}	0.36	0.41	0.48	0.67	1.85	38.64
	PLRANDBET _{0.1 p=10}	0.39	0.41	0.47	0.59	0.96	8.96
	PLRANDBET _{0.05 p=10}	0.38	0.39	0.43	0.47	0.57	0.98
PLRANDBET _{0.1 p=15}	0.36	0.39	0.43	0.49	0.65	1.42	
PLRANDBET _{0.05 p=15}	0.36	0.38	0.42	0.47	0.52	0.67	
PLRANDBET _{0.1 p=20}	0.38	0.40	0.44	0.48	0.56	0.76	
PLRANDBET _{0.05 p=20}	0.33	0.34	0.38	0.42	0.47	0.56	
$m = 4$ bit	PLCLIPPING ₁	0.44	1.16	88.78	89.89	90.05	89.78
	PLCLIPPING _{0.5}	0.44	0.68	78.09	89.89	89.66	90.49
	PLCLIPPING _{0.25}	0.39	0.52	7.51	82.87	89.75	89.55
	PLCLIPPING _{0.2}	0.40	0.49	1.93	66.75	88.17	89.83
	PLCLIPPING _{0.15}	0.40	0.48	0.81	12.92	78.62	89.15
	PLCLIPPING _{0.1}	0.39	0.45	0.56	1.23	23.15	80.47
	PLCLIPPING _{0.05}	0.36	0.39	0.46	0.57	1.03	13.81
	PLRANDBET _{0.25 p=1}	0.34	0.47	3.44	80.84	89.82	89.83
	PLRANDBET _{0.2 p=1}	0.34	0.44	1.27	59.95	88.07	90.14
	PLRANDBET _{0.15 p=1}	0.38	0.44	0.73	9.22	78.16	89.18
	PLRANDBET _{0.1 p=1}	0.34	0.41	0.55	1.17	20.42	79.29
	PLRANDBET _{0.25 p=3}	0.39	0.47	1.04	35.72	87.54	90.17
	PLRANDBET _{0.2 p=3}	0.31	0.39	0.80	22.57	85.08	89.74
	PLRANDBET _{0.15 p=3}	0.33	0.40	0.62	3.37	65.18	88.82
	PLRANDBET _{0.1 p=3}	0.40	0.44	0.55	0.92	10.87	78.08
	PLRANDBET _{0.2 p=5}	0.36	0.45	0.67	3.79	66.59	88.48
	PLRANDBET _{0.15 p=5}	0.38	0.44	0.59	1.56	36.84	86.87
	PLRANDBET _{0.1 p=5}	0.46	0.49	0.58	0.82	5.05	70.44
	PLRANDBET _{0.05 p=5}	0.31	0.35	0.41	0.51	0.78	6.44
	PLRANDBET _{0.15 p=10}	0.38	0.41	0.49	0.72	2.68	54.87
PLRANDBET _{0.1 p=10}	0.44	0.50	0.55	0.66	1.10	21.86	
PLRANDBET _{0.05 p=10}	0.30	0.33	0.38	0.47	0.63	1.50	
PLRANDBET _{0.1 p=15}	0.40	0.42	0.45	0.53	0.69	1.68	
PLRANDBET _{0.05 p=15}	0.40	0.43	0.46	0.50	0.58	0.79	
PLRANDBET _{0.1 p=20}	0.36	0.39	0.43	0.47	0.57	0.82	
$m = 2$ bit	PLCLIPPING ₁	1.01	65.76	90.02	90.04	90.10	89.85
	PLCLIPPING _{0.5}	0.52	27.23	89.24	89.97	89.88	90.34
	PLCLIPPING _{0.25}	0.50	3.84	87.87	90.33	89.88	90.10
	PLCLIPPING _{0.2}	0.49	0.91	63.98	89.79	90.51	90.32
	PLCLIPPING _{0.15}	0.48	0.62	30.61	87.62	89.72	89.77
	PLCLIPPING _{0.1}	0.34	0.43	0.91	38.84	87.94	90.09
	PLCLIPPING _{0.05}	0.42	0.48	0.61	1.42	42.80	88.61
	PLRANDBET _{0.25 p=1}	0.42	0.67	67.48	89.64	90.03	89.97
	PLRANDBET _{0.2 p=1}	0.32	0.53	19.68	88.73	90.11	89.91
	PLRANDBET _{0.15 p=1}	0.38	0.52	6.07	85.03	90.04	90.18
	PLRANDBET _{0.1 p=1}	0.42	0.51	1.04	42.66	88.81	89.93
	PLRANDBET _{0.25 p=3}	0.42	0.56	5.06	86.20	90.21	90.05
	PLRANDBET _{0.2 p=3}	0.33	0.48	2.44	81.45	89.73	89.97
	PLRANDBET _{0.15 p=3}	0.33	0.41	1.18	60.65	89.23	90.07
	PLRANDBET _{0.1 p=3}	0.31	0.39	0.63	12.21	85.13	90.17
	PLRANDBET _{0.2 p=5}	0.41	0.52	1.00	32.74	88.28	90.04
	PLRANDBET _{0.15 p=5}	0.37	0.44	0.77	21.81	86.35	90.02
	PLRANDBET _{0.1 p=5}	0.44	0.50	0.65	2.72	74.74	89.42
	PLRANDBET _{0.05 p=5}	0.40	0.43	0.52	0.76	6.26	84.26
	PLRANDBET _{0.1 p=10}	0.43	0.47	0.57	0.87	6.36	82.09
PLRANDBET _{0.05 p=10}	0.34	0.39	0.46	0.55	0.93	61.55	
PLRANDBET _{0.1 p=15}	0.42	0.44	0.51	0.62	1.15	13.14	
PLRANDBET _{0.05 p=15}	0.36	0.40	0.45	0.51	0.68	4.77	
PLRANDBET _{0.1 p=20}	0.49	0.53	0.62	0.70	0.86	1.75	
PLRANDBET _{0.05 p=20}	0.44	0.48	0.53	0.60	0.72	1.38	